
HEWLETT-PACKARD

HP-67/HP-97

Games Pac I



The program material contained herein is supplied without representation or warranty of any kind. Hewlett-Packard Company therefore assumes no responsibility and shall have no liability, consequential or otherwise, of any kind arising from the use of this program material or any part thereof.

Printed in Singapore

© HEWLETT-PACKARD COMPANY 1976

Introduction

The 19 programs of Games Pac I are designed primarily to provide fun, and also to help teach principles of math, physics and logic. Included are card games, dice games, mathematical puzzles, outdoor sports and war games. Characteristics of each program are shown below.

We hope that Games Pac I will provide you with pleasure and education. We would very much appreciate knowing your reactions to the programs in this pac, and to this end we have provided a questionnaire inside the front cover of this manual. Would you please take a few minutes to give us your comments on these programs? It is in the comments we receive from you that we learn how best to increase the usefulness of programs like these.

PROGRAM CHARACTERISTICS	SOLITAIRE	2 PLAYERS	2 OR MORE PLAYERS	EASY TO WIN	HARD TO WIN	VARIABLE DIFFICULTY	CHANCE	SOME SKILL	TWO CALCULATORS CAN PLAY EACH OTHER	NOT A GAME
1 GAME OF 21	●	●		●				●		
2 DICE	●		●				●			
3 SLOT MACHINE	●			●			●			
4 SUBMARINE HUNT	●					●		●		
5 ARTILLERY	●					●		●		
6 SPACE WAR	●				●			●		
7 SUPER BAGELS	●					●		●		
8 NIM_k	●					●		●	●	
9 QUEEN BOARD	●			●				●		
10 HEXAPAWN	●					●		●	●	
11 TIC-TAC-TOE	●				●			●		
12 WARI	●	●			●			●	●	
13 RACETRACK	●		●		●			●		
14 TEASER	●				●			●		
15 GOLF	●	●				●		●		
16 THE DEALER	●		●							●
17 BOWLING SCOREKEEPER	●		●							●
18 BIORHYTHMS	●									●
19 TIMER	●									●

CONTENTS

Program **Page**

Introduction i

A Word about Program Usage iv

GAMES

1. Game of 21 **01-01**
 This card game is also known as blackjack.
2. Dice **02-01**
 This includes the game of "Craps" as well as a dice roller.
3. Slot machine **03-01**
 The familiar one armed bandit.
4. Submarine Hunt **04-01**
 Find and then sink the moving submarine with your depth charges.
5. Artillery **05-01**
 Can you locate and destroy the moving target before it destroys you?
6. Space War **06-01**
 Your mission: Search out and annihilate the 3 evil Alglogs before time and energy are gone.
7. Super Bagels **07-01**
 Based on "Mastermind." How fast can you guess the secret number?
8. Nim_k **08-01**
 Who will pick the last object from the last pile, you or the machine?
9. Queen Board **09-01**
 You and the calculator take turns moving a chess queen to its target. The one who moves last, wins.
10. Hexapawn **10-01**
 You and the 67/97 command armies of 3 chess pawns each. Caution: The calculator learns from its mistakes.
11. Tic-Tac-Toe **11-01**
 Your best hope is to play the machine to a draw.
12. Wari **12-01**
 You have a reasonable chance of beating the HP-67/97, but beware of a smart human. This ancient game is also known as Man-Kalah.
13. Racetrack **13-01**
 Up to 5 players can race. Be alert to the differences between velocity and acceleration.
14. Teaser **14-01**
 Changing from one pattern to the other looks easy, but ...
15. Golf **15-01**
 The HP Country Club course is challenging, but a duffer with his handicap can beat a champion.
16. The Dealer **16-01**
 This shuffles and deals a deck of cards to 4 people; it also calls Bingo.
17. Bowling Scorekeeper **17-01**
 Tired of keeping score and missing the game? Here's your answer for up to 10 bowlers.

18. Biorhythms **18-01**
Calculates cycle values for any date, and tells which of the next 33 days are critical, maximum or minimum days.
19. Timer **19-01**
Offers 2 visible timers, a count-up and count-down timer, and allows splits to be taken.
Program Listings **L00-01**
Appendix A: Magnetic Card Symbols and Conventions **A-1**

A WORD ABOUT PROGRAM USAGE

Each program in this pac is represented by one or more magnetic cards and a section in this manual. The manual provides a description of the program, a set of instructions for using the program, and one or more example problems, each of which includes a list of the actual keystrokes required for its solution. Program listings for all the programs in the pac appear at the back of this manual. Explanatory comments have been incorporated in the listings to facilitate your understanding of the actual working of each program. Thorough study of a commented listing can help you to expand your programming repertoire since interesting techniques can often be found in this way.

On the face of each magnetic card are various mnemonic symbols which provide shorthand instructions to the use of the program. You should first familiarize yourself with a program by running it once or twice while following the complete User Instructions in the manual. Thereafter, the mnemonics on the cards themselves should provide the necessary instructions, including what variables are to be input, which user-definable keys are to be pressed, and what values will be output. A full explanation of the mnemonic symbols for magnetic cards may be found in Appendix A.

This application pac has been designed for both the HP-97 Programmable Printing Calculator and the HP-67 Programmable Pocket Calculator. The most significant difference between the HP-67 and the HP-97 calculators is the printing capability of the HP-97. The two calculators also differ in a few minor ways.

Most of the computed results in this pac are output by PRINT statements: either by the statement PRINTx or by the command PRINT STACK. On the HP-97 these results will be output on the printer. On the HP-67 each PRINT command will be interpreted as a PAUSE: the program will halt, display the result for up to five seconds, then continue execution. The term "PRINT/PAUSE" is used to describe this output condition.

The lists of keystrokes required to solve example problems indicate the resulting outputs. Those outputs indicated by *** are printed by the HP-97 with the printer in MANUAL mode. These *** outputs are shown by PAUSE on the HP-67. Outputs without stars are displayed on both the HP-97 and HP-67.

If you own an HP-67, you may want more time to copy down the number displayed by a PRINT/PAUSE. All you need to do is press any key on the keyboard. If the command being executed is PRINTx (eight rapid blinks of the decimal point), pressing a key will cause the program to halt. If the command being executed is PRINT STACK (two slow blinks of the decimal per value), the number in the display will remain there until the depressed key is released;


then the next register in the stack will be displayed, and so on. After display of all four registers, the program will halt execution if a key was pressed at any time during the display of the stack contents. In both cases execution of the halted program may be re-initiated by pressing R/S.

HP-97 users may also want to keep a permanent record of the values input to a certain program. A convenient way to do this is to set the Print Mode switch to NORMAL before running the program. In this mode all input values and their corresponding user-definable keys will be listed on the printer, thus providing a record of the entire operation of the program.

Another area that could reflect differences between the HP-67 and the HP-97 is in the keystroke solutions to example problems. It is sometimes necessary in these solutions to include operations that involve prefix keys, namely, f on the HP-97 and f, g, and h on the HP-67. For example, the operation 10^x is performed on the HP-97 as f 10^x and on the HP-67 as g 10^x. In such cases, the keystroke solution omits the prefix key and indicates only the operation (as here, 10^x). As you work through the example problems, take care to press appropriate prefix keys (if any) for your calculator.

If you have already worked through a few programs in the Standard Pac, you will understand how to load a program and how to interpret the User Instructions form. If these procedures are not clear to you, take a few minutes to review the sections, Loading a Program and Format of User Instructions, in your Standard Pac.

Game of 21 (Blackjack)





You make your bet, and the calculator, as dealer, deals two cards to you and two to itself. You see the dealer's first card face up, then his second face down (the calculator shows 0). Your two cards are then shown face up, one at a time. Next, you see a number in the form XXX.YY, where XXX is your bet and YY is the number of points in your hand.

You and the dealer may draw additional cards. Your goal is to finish with a hand whose total count is 21 or below, but closer to 21 than the dealer's. If your hand totals over 21, you lose (you're "busted").

The King is indicated by 13, the Queen by 12, and the Jack by 11, but all count 10 points each. The other cards always count their face values except the Ace. The Ace counts 1 unless you decide to change it to an 11 (press **D**). (If you have chosen 11 for an Ace, and want it counted 1, press **E**). If the next card you draw makes your score over 21, the calculator will automatically check for an Ace and make it count 1 if you have chosen 11 for its value. Note that an Ace always counts 1 for the dealer, except for a blackjack. A blackjack is a 2 card hand totalling 21, made up of a 10, Jack, Queen, or King plus an Ace with a value of 11. Your best win is a blackjack, since you win 1.5 times your bet rather than the bet itself. If both you and the dealer get blackjack, you neither win nor lose, it's a "push."

After the initial deal, and provided neither you nor the dealer have blackjack, you may ask the dealer to give you another card ("hit") by pressing **B**. If you don't want to draw, you may "stand" by pressing **C**. The calculator will then show the dealer's two cards. If the dealer's (calculator's) hand counts 16 or less, it draws. It continues to draw until its hand totals 17 or more, then it stands.

The calculator then determines if you've won or lost, and blinks your winnings (XXX) or losses (–XXX) and your final score (YY) in the form XXX.YY.

Next it shows your total account (the sum of your winnings and losses for all the games you've played this session).

Terms for HP-67/97 Game of 21 (Blackjack)

1. BLACKJACK: Any Ace (1) with 10, Jack (11), Queen (12) or King (13).
2. BUST: When your points are 22 or more.
3. HIT: Signify that you wish another card by pressing B.
4. STAND: You wish no more cards. Press C.
5. PUSH: You have the same points as HP-67/97. Blinking 0.000000000 when both have blackjack; blinking 0.00 for ordinary push.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load sides 1 and 2.			
2	Shuffle cards.		f A	
3	Stop shuffle and cut deck.		R/S	Ignore output
4	Input your bet (whole *even*			
	dollars only—no cents nor odd			
	dollars). Please do not bet over			
	$100,000,000.	Bet	A	Dealer's
				cards;
				your cards;
				Bet.points
5	Hit (draw a card).		B	Bet.points
6	Repeat step 5 until you are			
	busted or you want to stand.			
7	If you want your Ace scored			
	as 11:		D	Bet.points
8	If you want your Ace changed			
	from 11 to 1:		E	Bet.points
9	Stand.		C	Win or loss
10	If you had not chosen to stand,			
	what would have been your			
	next card?		f E	Card

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
11	For a new game, go to step 2.			
12	For a new player: Reset			
	account to zero,		f C	0.00
	and go to step 11.			

Example:

Load sides 1 and 2.

Keystrokes: **Outputs:**

f A ——→ Display will not stabilize until R/S is pressed.

Wait 20 or 30 seconds.

R/S ——→ Ignore output.

To reproduce the example below, store .9103987 in register E.

100 A ——→
9. *** Dealer's 1st card
0. *** Dealer's 2nd card (face down)
12. *** Your 1st card is a Queen, worth 10 points.
7. *** Your 2nd card
100.17 100 is your bet, 17 is your score.

B ——→
4. *** Your 3rd card
100.21 Bet. Score

C ——→
9. *** Dealer's 1st card
7. *** Dealer's 2nd card
12. *** Dealer's 3rd card

	100.21	Your win. score Display blinks to indicate end of game. Positive number means you win.
	100.00	Your account
100 A →	6. ***	Dealer's 1st card
	0. ***	Dealer's 2nd card
	1. ***	Your 1st card
	7. ***	Your 2nd card
	100.08	Your bet. score
D →	100.18	Your bet. score


Your Ace is now counted as 11.
You decide to stand.


C →	6. ***	Dealer's 1st card
	12. ***	Dealer's 2nd card
	4. ***	Dealer's 3rd card
	−100.18	Your loss. score
	0.00	Your account

Dealer's 20 beats your 18, so you lose the $100 you won the first game. Care to try your luck again?

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Dice





There are many games that can be played with dice. One of the most popular of these games is "CRAPS."

Two dice are used. One player, by general consent, becomes the first "shooter."

A bet is placed. The shooter then throws the dice. If on the first roll the total is a 7 or 11, this is called a "natural" and the shooter wins. If the throw is a 2, 3, or 12, it is a "crap" and all that is bet is lost.

If any other number appears, it is called a "point." The shooter then continues to throw the dice until the point is matched, in which case all that is bet is won; but if a 7 appears first, all that is bet is lost. Another player then becomes the shooter.


To play craps using this program, a seed (any number between 0 and 100) is input to key **A**. Then a bet is placed (key **B**). The program will then display generated rolls of the dice until the shooter wins or loses. The shooter's winnings are updated and appear on the display. If another player is to become the shooter, press key **C**.

Another feature of this program is as a dice roller. A seed (any number between 0 and 100) is input to key **A**. The roll of the dice is then generated by pressing key **D**. After each roll the result is displayed. This process can be repeated as many times as you like.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 only.			
2	Key in seed (any number			
	between 0 and 100).		A	0.00
3	For dice roll, go to step 6.			
	For craps, go to step 4.			
	CRAPS			
4	Input bet, and roll dice until			
	you win or lose.		B	Display*
5	For new player, reset;			
	then go to step 4.		C	0.00
	DICE ROLL			
6	Roll dice.		D	x.y zz†
7	Repeat step 6 as often as			
	you wish.			
	*Each roll of the dice is			
	displayed in succession as			
	x.y zz†. When the player			
	wins or loses, his updated			
	winnings (or losses) are then			
	displayed. A minus sign is used			
	for losses.			
	†x = value of first die.			
	y = value of second die.			
	zz = sum of both dice.			

Example 1:


Load sides 1 and 2.

Keystrokes:	**Outputs:**	
Set seed.		
9 A →	0.00	
Place bet.		
10 B →	5.1 06	 = 6
	6.3 09	= 9
	3.6 09	
	1.4 05	
	6.4 10	
	6.6 12	
	2.6 08	
	2.4 06	
	10.00	WIN!
Place bet.		
10 B →	3.2 05	
	3.2 05	
	20.00	WIN!
Place bet.		
10 B →	6.6 12	
	10.00	LOSE!
Place bet.		
10 B →	5.6 11	
	20.00	WIN!
Place bet.		
10 B →	1.4 05	
	3.3 06	
	4.5 09	
	6.6 12	
	3.1 04	
	5.2 07	
	10.00	LOSE!
Another shooter		
C →	0.00	

Example 2:

Keystrokes:	**Outputs:**
Set seed.	
1 A →	0.00
Roll dice.	
D →	5.3 08
D →	1.2 03
D →	1.1 02
D →	3.1 04
D →	2.6 08
etc.	

Slot Machine





This electronic slot machine deducts one dollar from your bank account with each "spin" and pays up to one hundred dollars for a jackpot. To begin, input a seed consisting of a decimal point followed by a string of digits using the E key.* Then merely press the A key time-after-time to spin the wheels. Your bank account may be seen at any time by pressing B.

Any combination of three digits may be seen in the display in the format $0.D_1D_2D_3$. Only the following combinations, however, result in a payoff:

COMBINATIONS	PAYOFF
0.1XY	$ 2.00
0.11X	$ 5.00
0.ZZZ (Z ≥ 2)	$ 10.00
0.ZZ0 (Z ≥ 2)	$ 10.00
0.000	$100.00

Good luck!

*The string of digits should be long and should contain an assortment of values.

Reference:

This program is based on an HP-65 Users' Library program by Craig A. Pearce.


STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1.			
2	Enter seed (a many digit			
	number between 0 and 1).	Seed	E	0.
3	Play.		A	Combination
	Winning combinations:			
	0.1XY $ 2.00			
	0.11X $ 5.00			
	0.ZZZ $10.00			
	(where Z is 2 or more)			
	0.ZZ0 $10.00			
	(where Z is 2 or more)			
	0.000 $100.00			
4	Recall winnings or losses at			
	any time (optional).		B	Winnings
5	Repeat step 3 any number			
	of times.			
6	To start over, go to step 2.			

Example:

Load side 1.

Keystrokes:		**Outputs:**	
.963258741 E	→	0.	
A	→	0.450	
A	→	0.001	
A	→	0.000	JACKPOT!
B	→	97.00	
A	→	0.173	A $2 WINNER
B	→	98.00	
A	→	0.991	
A	→	0.026	
A	→	0.902	
A	→	0.999	A $10 WINNER
B	→	104.00	

Submarine Hunt



Using your destroyer, you try to locate the position of the enemy submarine in a 10 × 10 grid, and then destroy it with a depth charge.

You input a seed (1–100) and the calculator will position the submarine in the center of one of the 100 squares (R, C), where R = row and C = column, and where R and C can each be 0, 1, 2, ..., 9.

You make guesses as to where you think the submarine is hiding by taking sonar readings. Input the location of your destroyer (R, C) and press **B**. If the submarine is in one of the 8 adjacent squares (or directly under your destroyer), the calculator will display "1." Otherwise, a "0" will be shown.

When you think you've located the submarine, move your destroyer directly over it (move to the same square) and drop a depth charge. Blinking "1's" indicate a hit, while a "0" shows a miss. If you miss, the submarine will move randomly to one of the 4 adjacent squares in the same row or column.

You can make the hunt easier or more difficult. For an easier game, press **D**. This increases the sensitivity of your sonar, allowing you to detect the submarine as far away as 2 squares in any direction (you cover a square region of the ocean 5 squares on a side). **D** is a toggle switch—you can switch from 1 to 2 square sensitivity or from 2 to 1 square sensitivity as often as you like during the game.

To make a more challenging game, press **C** immediately after inputting the seed. This allows the submarine to move after each sonar echo as well as after each depth charge miss. The submarine always moves randomly to an adjacent square in the same row or column.

A depth charge has a range of 0.9. When you position your destroyer for a depth charge drop, you may move anywhere on the board, not just to the center of a square. For instance, a depth charge dropped from a (2.5, 6.5) location would destroy any submarine in the center of squares (2, 6) (2, 7) (3, 6) and (3, 7).

Try to destroy the submarine using no more than 10 sonar readings and 1 depth charge, playing a regular game with regular sensitivity. You can check your status any time the display is steady by pressing **f** **E**.


Status format is XX.YY

where: XX = Number of depth charges fired.
YY = Number of sonar readings.

Reference:

This program is based on an HP-65 Users' Library program written by Moshe Breiner.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load sides 1 and 2.			
2	Input seed (any number			
	between 0 and 100).		E	0.
3	For regular game, go to			
	step 5.			
4	Select difficult game (sub-			
	marine always moving).		C	1.
5	To change sonar sensitivity:		D	2. or 1.
	"2" means sensitivity			
	distance is 2 squares.			
	"1" means sensitivity			
	distance is 1 square.			
6	**SONAR**	Row	ENTER↑	
	"0" means no echo.	Col.	B	0. or 1.
	"1" means echo received.			
	or			
	DEPTH CHARGE	Row	ENTER↑	
	"0" means miss.	Col.	A	0. or
	Blinking "1's" means **HIT!**			blink
7	Repeat step 6 until sub-			
	marine is hit.			
8	To review status at any time:		f E	XX.YY
	XX = number of depth			
	charges fired.			
	YY = number of sonar			
	readings.			
9	For a new game, go to step 2.			



Playing boards for Submarine Hunt and Space War.
You might wish to use copies of this page for your games.

Example 1:

Load sides 1 and 2.

Keystrokes: **Outputs:**

58 E ⟶ 0.

First move:

2 ENTER↕ 1 B ⟶ 1. Echo

You now know your enemy is in one of the "x" squares below.

	0	1	2	3	4	5	6	7	8	9	
9											9
8											8
7											7
6											6
5											5
4											4
3	x	x	x								3
2	x	x	x								2
1	x	x	x								1
0											0
	0	1	2	3	4	5	6	7	8	9	

Diagram of 1st move

Second move:

1 ENTER↕ 2 B ⟶ 0. No echo

The submarine cannot be in the ⊗ squares below.

	0	1	2	3	4	5	6	7	8	9	
9											9
8											8
7											7
6											6
5											5
4											4
3	x	x	x								3
2	x	⊗	⊗								2
1	x	⊗	⊗								1
0											0
	0	1	2	3	4	5	6	7	8	9	

Diagram of 2nd move

Third move:

3 ENTER 0 B ⟶ 0. No echo

You've narrowed down the submarine's location to just 2 squares, those containing an "x" with no circle.

	0	1	2	3	4	5	6	7	8	9	
9											9
8											8
7											7
6											6
5											5
4											4
3	⊗	⊗	x								3
2	⊗	⊗	⊗								2
1	x	⊗	⊗								1
0											0
	0	1	2	3	4	5	6	7	8	9	

Diagram of 3rd move

Fourth move:

1 ENTER 0 B ⟶ 1. Echo

This eliminates (3, 2) as a submarine location, so you've found it!

	0	1	2	3	4	5	6	7	8	9	
9											9
8											8
7											7
6											6
5											5
4											4
3	⊗	⊗	⊗								3
2	⊗	⊗	⊗								2
1	⊗	⊗	⊗								1
0											0
	0	1	2	3	4	5	6	7	8	9	

Diagram of 4th move

Fifth move:

1 ENTER 0 A ⟶

0.111
0.11111
0.1111111
0.111111111
0.111111111 A hit!

Example 2:


Keystrokes:	**Outputs:**
60 E ⟶	0.
C ⟶	1.

Submarine will now move on sonar echos as well as on depth charge misses.

First move:

7 ENTER 4 B ⟶ 1. Echo

The submarine is in one of the "x" squares in the left diagram below. But the submarine moves, so now it could be in any of the "x" squares in the right diagram below.




Diagrams of 1st move

Second move:

8 ENTER 4 B ⟶ 0. No echo

You've eliminated some positions (left diagram: ⊗), but new possible positions have been created by the enemy's random move (right diagram).




Diagrams of 2nd move

Third move:

7 ENTER 5 B ⟶ 1. Echo

This eliminates many possible positions (left diagram), but again, new ones are created (right diagram).



Diagrams of 3rd move


Fourth move: You try a depth charge.

7.5 ENTER↑ 4.5 A ⟶

0.111
0.11111
0.1111111
0.111111111
0.111111111 A hit!

It pays to be lucky.

The submarine used to be in one of these 4 squares:



Artillery



This program simulates the firing of an artillery round at a moving target whose initial position has been randomly selected. Feedback to the gunner is via a spotter plane weaving in and out of clouds over the battle area.


(1) Initial display for each new battle is one of the 8 main compass directions: 0 (North), 45, 90 (East), 135, 180 (South), 225, 270 (West), or 315. The target lies in that *general* direction from the hidden gun and is 5 to 10 kilometers away.

(2) The gunner fires by bearing and elevation parameters. A spotter (poor to perfect) relays information by displaying hh.DDDD :

hh (0 to 12) = the shell hit as an hour position on a relative clock face with the target at center and 6 o'clock in line with the gun.

DDDD = the *estimated* range from target to shell hit.

Thus: 8.0950 = shell was a bit short, left, and 950m away.
12.1230 = shell passed over target and hit 1230m beyond.



(3) If shell lands within KILL range of target, the gunner wins. If not destroyed, and target has closed within 500 meters, target blasts gun to pieces—player loses!

Win is indicated by PRINT/PAUSE display of stack:

T = spotter rating
Z = maximum axial movement of target (SPEED)
Y = KILL range
X = proximity of shell hit to target

Loss is indicated by flashing 500.0.

(4) Between one-minute shots, target randomly moves (up to maximum SPEED both N-S and E-W) but usually closes toward gun. Accurate information on where target *was* when last shell was fired can be obtained via C in format bbb.DDDD (true bearing and distance from gun).

(5) After loading program, initialization (f A) sets the following parameters:

a) Maximum gun range = 10,000 meters. (Thus, the formula for any shell's range = 10,000 × Sin (2 × elevation).)

b) Target KILL range = 100 meters.

c) Target SPEED = 500 meters/minute (along each axis).

d) Spotter rating = 3.0 (1 = poor, 4 = perfect).

e) Random number seed = 0.5284163

Remarks:

Remember, information from a less than perfect spotter may be incorrect by as much as 3 hours in either circular direction and as much as ±60% of the "miss" distance. A perfect (4.0) spotter will report to the nearest hour and within 10 meters. Target movement along axes (SPEED), spotter rating (SPOTR), and lethal radius of a shell blast (KILL) may all be altered by the player even during a battle. Distinguished indeed will be the first player to win a battle under the following conditions: SPEED = 1000, SPOTR = 1.0, and KILL = 0!

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load sides 1 and 2 of card.			
2	Initialize parameters:		f A	10000.00
	(Random seed = 0.5284163)			
	(Axial movement of target,			
	SPEED = 500)			
	(Spotter rating, SPOTR = 3.0)			
	(KILL range = 100)			
	(Maximum gun range			
	= 10,000)			
3	Optional—			
	Set target SPEED.	Speed	f B	Speed
	Set spotter rating (1 = poor,			
	4 = perfect).	Spot	f C	Spot
	Set KILL range (1000 = easy,			
	10 = tough).	Kill	f D	Kill
4	Reset target for new battle.		A	BBB.*
5	FIRE!	Bearing	ENTER↑	
		Elevation	E	
	or	*or*	f E	hh.DDDD*
6	Repeat step 5 until decision:			
	WIN—Stack is output.			
	LOSS—Flashing 500.0			
7	Display bearing & distance to			
	last target (Opt).		C	bbb.DDDD*
8	Recall rounds fired.		RCL I	Rounds

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
9	Go to step 3.			
	*Outputs:			
	BBB: Bearing in			
	degrees.			
	hh.DDDD:			
	hh = Estimate of hour			
	position of hit relative to			
	target. 6 is nearest gun.			
	DDDD = Estimate of dis-			
	tance from hit to target.			
	bbb.DDDD = Correct			
	bearing and distance to			
	last target position.			

Example 1:

Load sides 1 and 2.

Keystrokes: **Outputs:**

f A ——————→ 10000.00

(This initialization need be done only on a freshly loaded program. SPEED = 500, SPOTR = 3.0, and KILL = 100 meters.)

A (Starts the battle) ——————→ 180. (Approximate target bearing)

201 ENTER↑ 33 E ——————→ 201.0000000 ***
33.0 ***
11.0130 ***

(Spotter has reported that round landed left, long and missed by 130m.)

201.5 ENTER↑ 32 E ——————→ 201.5000000 ***
32.0 ***
2.0670 ***

199 ENTER↑ 30 f E →	199.0000000 ***	
	30.0 ***	
	1.0570 ***	
196 ENTER↑ 27 E	196.0000000 ***	
	27.0 ***	
Target destroyed!		
	3.0 ***	T Spotter rating
	500.0 ***	Z Target max. movement
	100.0 ***	Y Kill range
	79.1 ***	X "Miss" distance

Example 2:

Select SPEED = 100, SPOTR = 4.0 (perfect), and KILL = 20.

100 f B →	100.0	
4 f C →	4.0	
20 f D →	20.0	
A →	315.	Approximate target bearing
315 ENTER↑ 30 E →	315.0000000 ***	
	30.0 ***	
	3.3230 ***	
295 ENTER↑ 25 E →	295.0000000 ***	
	25.0 ***	
	1.0530 ***	
293 ENTER↑ 22.5 f E →	293.0000000 ***	
	22.5 ***	
	4.0050 ***	
292.5 ENTER↑ 22.2 E →	292.5000000 ***	
	22.2 ***	
Gotcha!		
	4.0 ***	T Spotter rating
	100.0 ***	Z Target max. movement
	20.0 ***	Y Kill range
	10.4 ***	X "Miss" distance


Example 3:

Select 1000 meter SPEED and KILL range.

1000.0 f B f D →	1000.0
A →	90.
90 ENTER↑ 30 E →	90.0000000 ***
	30.0 ***
	1.2400 ***
85 ENTER↑ 20 E →	85.0000000 ***
	20.0 ***
Ridiculously easy!	4.0 *** T
	1000.0 *** Z
	1000.0 *** Y
	881.0 *** X

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Space War



You are the commander of the Nuclear Powered Reconnoiterer (NPR) Kittyhawk. The NPR Kittyhawk is the sole guardian of justice in a vast galaxy that measures 10 quadrants by 10 quadrants. Within the galaxy somewhere, anchored among the blazing stars, lie three agents of evil: the vile Alglogs, known throughout space as interstellar thieves and creators of cosmic mischief. Your mission as commander of the NPR Kittyhawk is to search out and destroy the fearsome Alglogs within 18 stardays.

Also within the galaxy somewhere is a Base, a haven to which your ship may return in order to resupply itself. The weapons carried by the Kittyhawk are torpedos, which are fired in a straight line, and phasers, which send out an omnidirectional burst of energy. In addition, your starship is equipped with short- and long-range sensors which can detect the presence of Alglogs or the Base in nearby space. One starday is used whenever the Kittyhawk changes its position, i.e., when a move is made. Details of the operation of the NPR Kittyhawk are given below.

POWER ON (Card 1)

The Kittyhawk is started by supplying a seed s ($0 \leq s \leq 1$) to the routine START (Card 1). This routine positions the three Alglogs, the Base, and the Kittyhawk randomly in the galaxy. For best results, the seed s should contain all the digits but 0 and end in a 1, 3, 7, or 9. Remember that the galaxy is a 10×10 grid of quadrants; within each quadrant is a 10×10 grid of smaller areas called sectors. The quadrants are numbered 00 through 99, as are the sectors. The position of an object, then, may be specified by giving its quadrant and sector (QQ.SS). Examples of allowable positions are 23.68, 10.99, 7.01, and 85.00. No two objects may occupy the same position. At the end of the routine START, the calculator displays the starting position of the NPR Kittyhawk.

LONG-RANGE SCAN (Card 1)

The long-range scan covers all quadrants adjacent to and including that of the Kittyhawk itself. This scan will detect and report the presence of Alglogs or the Base in those quadrants. Suppose objects are located in the quadrants as below.

62	63	64 B	65 A
52 A	53 KH	54	55
42	43	44	45

The long-range scan would include the quadrants adjacent to quadrant 53 (Q53). The output of the scan would be three lines as follows:


63.00400401
53.10400400
43.00400400

The first line shows the contents of quadrants 62, 63, and 64. Two digits are allocated to each quadrant, with the "4's" merely indicating separation of the quadrants. The Base would appear in the right-hand of the two digits, an Alglog in the left-hand digit. Notice that the Base appears in the top line (Q64) and an Alglog in the second line (Q52). The Alglog in quadrant 65 is beyond the range of the sensors and does not show up. The numbers 63, 53, and 43 refer to the middle quadrant of each line.

The contents of nine squares are displayed with each long-range scan. If the Kittyhawk is at or near the edge of the galaxy, some of this information may be meaningless.

MOVE (Card 1)

If the Kittyhawk were in the position shown in the long-range scan above, a logical move would be to go to quadrant 52 to attack the Alglog. To make a move, one specifies the angle θ and distance r to be covered. Orientation of angles is shown in the diagram below. Angles must be input in degrees.



The distance is specified in terms of quadrants. To move exactly one quadrant's width, specify an r of 1. To move from Q53 to Q52, then, select $\theta = 180°$ and r = 1. Suppose one wished to move from Q53 to Q64. This would require an angle of 45° and a distance of $\sqrt{2}$. The output at the end of the move routine is the Kittyhawk's new position.

Each move uses 1 starday. If a move is taken when no stardays remain, the display will flash zeros to indicate that the mission has failed.

Caution must be observed near the edges of the galaxy. Moving beyond an edge can result in the Kittyhawk's being lost in space.

SHORT-RANGE SCAN (Card 2)

The short-range scan gives a detailed picture of the quadrant the Kittyhawk is presently in. The output is 10 lines of information output by PRINTx commands, each line representing a row of the quadrant. The rows are output in the order 9, 8, 7, ..., 0. Each line consists of 10 digits that represent the ten sectors in the row. A "0" in a line means that that sector is unoccupied; a "3" marks the location of the Kittyhawk, a "4" an Alglog, and a "7" the Base. Suppose the output of a short-range scan were as shown below:

Row 9	0.000000000
Row 8	0.040000000
Row 7	0.000000000
Row 6	0.000000000
Row 5	0.000000003
Row 4	0.000000000
Row 3	0.000000000
Row 2	7.000000000
Row 1	0.000000000
Row 0	0.000400000

This scan indicates the presence of Alglogs in sectors 04 and 82, the Kittyhawk in sector 59, and the Base in sector 20.

TORPEDO (Card 2)

The Kittyhawk begins its mission with 3 torpedos. A torpedo may be fired at an Alglog within the same quadrant. If the torpedo passes within 1° of the Alglog, the Alglog is destroyed and the torpedo is spent. To fire a torpedo, simply specify the angle of fire in degrees.

If no torpedos remain and you attempt to fire a torpedo, the display will show "Error."

PHASERS (Card 2)

At the start of the mission, 1000 units of energy are available for firing phasers. Unlike torpedos, phasers fire equally in all directions and can destroy as many Alglogs as are within range. Only Alglogs within the same quadrant as the Kittyhawk may be fired on. The closer the Alglog, the less energy is required to destroy it. A minimum of 105 units and a maximum of 275 units may be needed to destroy an Alglog. To fire phasers, simply specify the amount of energy to be used.

Whenever an Alglog is fired on with phasers, there is a danger that the fire will be returned. Accordingly, the Kittyhawk uses another 100 units of energy to maintain shields against each Alglog within the quadrant.

If more energy is needed than is available, flashing zeros will be displayed to indicate that the mission has failed.

DOCK (Card 2)

The Kittyhawk may dock at the Base by moving into a sector adjacent to that of the base and executing the routine DOCK. If the docking is successful, the Kittyhawk's supply of torpedos and energy are replenished to their initial level: 3 torpedos, 1000 units of energy. The display at the end of this routine shows the current supply of energy and torpedos.

STATUS

Two routines are available for providing information on the status of the mission. Either of these routines may be executed at any time.

The first, on card 1, shows the number of days remaining in the mission. Simply press f A and the number of days will be displayed.

The second, on card 2, shows the remaining energy and torpedos. Both values are output in a single display as Energy.Torpedos. For example, a supply of 500 energy units and 2 torpedos would be displayed as 500.2. This information is available by pressing f A on card 2.

MAP OF GALAXY

A map of the galaxy (playing board) is located on page 04-03 in the game of Submarine Hunt.

Reference:

This program is based on an HP-65 Users' Library program written by Lee Gregory, Jr.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2 of			
	Space War 1.			
2	To initialize, key in a seed s			
	($0 \leq s \leq 1$). Output is the			
	starting position of Kittyhawk.	s	A	QQ.SS
3	You have 18 stardays. Your			
	options are outlined below.			
	Be sure the appropriate card			
	is loaded for each option.			
	LONG RANGE SCAN (Card 1)			
4	Output 3 lines of scan. KH is			
	in center. QQ refers to middle			
	quadrant of each line. Digits			
	AB refer to Alglogs and Base.		C	QQ.AB4AB4AB
	MOVE (Card 1)			
5	Key in direction and distance			
	(in quadrants) of desired			
	move; output new position of			
	Kittyhawk. (Flashing zeros			
	means all stardays used;			
	mission failed.)	θ	ENTER↑	
		r	E	QQ.SS
	SHORT RANGE SCAN (Card 2)			
6	Output 10 rows of present			
	quadrant in order 9, 8, ..., 0.			
	Kittyhawk = 3, Alglog = 4,			
	Base = 7.		A	x.xxxxxxxxx
	TORPEDO (Card 2)			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
7	To fire a torpedo, key in angle			
	or fire; output number of			
	Alglogs remaining. ("Error "			
	means no torpedos remain;			
	use phasers.)	θ	C	# Alglogs
	PHASER (Card 2)			
8	To fire phasers, key in units			
	of energy expended in fire;			
	output number of Alglogs			
	remaining. (Flashing zeros			
	mean all energy used; mis-			
	ion failed.)	Energy	D	# Alglogs
	DOCK (Card 2)			
9	You may dock from any			
	square adjacent to Base.			
	Output is present			
	Energy.Torpedos.		E	En.Torp
	STATUS			
10	With Card 1, display number			
	of days remaining.	(Card 1)	f A	Days
11	With card 2, display present			
	Energy. Torpedos.	(Card 2)	f A	En.Torp

Example:

From the log of the NPR Kittyhawk:

Load side 1 and side 2 of Space War 1.

Keystrokes:

.63154897 A →

C →

Outputs:


50.53 (KH position)

60.00400400 ***

50.00400400 *** (Long scan)

40.00400400 ***

Current map of galaxy:



Dots indicate quadrants known to contain neither Alglogs nor Base.

Move in direction −45°.


45 CHS ENTER↑ 5.5 E ⟶ 14.62 (New position)

C ⟶ 24.00400400 ***

14.00400401 *** (Long scan)

4.00400410 ***

Current map of galaxy:



Move to Q05 to attack.


45 CHS ENTER↑ 2 √x E ⟶ 5.62 (Now in Q05)

Load side 1 and side 2 of Space War 2.

A ⟶

0.000000000 *** (Short scan)
0.000000000 ***
0.000000000 ***
0.030000000 *** (KH in S62)
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.004000000 *** (Alglog in S03)

Current map of galaxy:



Quadrants **Sectors**

Fire a torpedo in direction −80°.

80 CHS C ⟶ 2.000000000 (2 Alglogs left)

Return to Base and dock.

Load side 1 and side 2 of SW1.


90 ENTER↑ 1 E ⟶ 15.62 (New position)

Load side 1 and side 2 of SW2.

A ⟶

0.000000000 ***
0.000000000 ***
0.000000000 ***
0.030000007 *** (KH in S62, Base in S69)
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***

Current map of galaxy:




Move to S68.

Load side 1 and side 2 of SW1.

0 ENTER↑ .6 E ⟶ 15.68

Current map of galaxy:



Dock.


Load side 1 and side 2 of SW2.

E ⟶ 1000.3 (Energy, torpedos replenished)

Load side 1 and side 2 of SW1.

90 ENTER↑ 5 E ⟶ 65.68 (New position)

Current map of galaxy:




C ⟶ 75.00400400 ***
65.00410400 *** (Note Alglog in Q65)
55.00400400 ***

Load side 1 and side 2 of SW2.

A ⟶ 0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000030 *** (KH in S68)
0.000000000 ***
0.004000000 *** (Alglog in S43)
0.000000000 ***
0.000000000 ***
0.000000000 ***
0.000000000 ***

Current map of galaxy:



Use phasers. Try 200 energy units.

200 D ⟶ 1.000000000 (1 Alglog left)

The rest of the mission will be left as an exercise for the cadet.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Notes

Super Bagels

2 ? 7 ? 4 ? 1 5 3 ? ? 9 ? 8 ?



The object of the game of Super Bagels is for the player to guess an integer number which the calculator has chosen. Clues are given after each guess to tell the player how close his guess is to the hidden number. To make the game more interesting, the hidden number can be specified by the user to be from 1 to 8 digits, where each digit can range from zero to a maximum specified by the user. When the proper number is finally entered, the number of guesses required to discover the hidden number is displayed.

Play begins by first keying in a seed (any number) and pressing **A**. The display will return with a 2-digit code as shown: 4.5. This output shows the type of number which the machine will pick for the player to guess unless requested otherwise. The 4.5 game is a game of moderate difficulty where the number is a 4 digit number with each digit having any value from 0 to 5. Thus the minimum possible number is 0000, and the maximum 5555.

After the game has been started by pressing **A**, the number to be guessed can be changed by pressing **B** or **C**. To change the number of digits in the hidden number, key in the number of digits and press **B**. The number of digits must be at least 1 and not greater than 8. To change the maximum digit found in the hidden number, the maximum digit is keyed in and **C** is pressed. The range of legal maximum digits is from 0 to 9. After **B** or **C** is pressed, the display returns with a display in the same format as after pressing **A**. This makes sure the user knows the type of number he is trying to guess.

Once the hidden number has been specified, the game begins with the player entering his first guess and pressing **E**. The returned output is of the form CW.Guess where C is the number of digits of the guess that exactly match digits in the hidden number both in value and location. W is the number of digits of the guess that match digits of the hidden number in value, but not in location. Digits are not counted twice; that is, digits counted as C digits are not counted again as W digits. If C is 0 there will be a blank in place of C.

For example, if the hidden number is 12251, a guess of 12345 would yield 21.12345, meaning that 2 numbers (the 1 and 2) match exactly the hidden number, but that 1 number (5) is out of place.

A guess of 21125 would give 5.21125 meaning all of the digits of the guess are in the hidden number, but none of them are in the right place.

When the guess finally matches the hidden number, the number of guesses used is output. At any time during the game, the current number of guesses taken can be displayed by pressing D.

To play again, enter a new seed and press A. Super Bagels is written to run as fast as possible, but when numbers with many digits are selected, the time to analyze a guess will be significantly slower than with a simpler number. For those who want to discover the hidden number in some manner other than by using the clues given, you are invited to try. Super Bagels has been written to hide the number as much as possible. Good Luck.

Reference:

This game was inspired by the popular game *Mastermind*.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	To start game, key in a seed			
	(any number); output is in the			
	form D.M.*	Seed	A	4.5
3	To change number of digits to			
	be guessed in the number,			
	key in the number ($1 \leq D \leq 8$).	D	B	D.M*
4	To change the maximum digit			
	found in the number to be			
	guessed, key in the number			
	($0 \leq M \leq 9$).	M	C	D.M *
5	To display current number of			
	guesses already taken		D	Guesses
6	Guess a number containing D			
	digits with the maximum			
	digit $\leq$ M. The output returns			
	the guess and also codes C			
	and W which signify the			
	number of digits of the guess			
	correct and in the right location			
	(C), and the number of other			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	digits of the guess correct but			
	in the wrong location (W).	Guess	E	CW.Guess
7	Repeat step 6 until a match is			
	made between the guess and			
	the number stored in the			
	machine. The output shows the			
	number of guesses required			
	to make the match.			no. of guesses
8	To play again return to 2.			
	*D = number of digits in			
	hidden number.			
	M = maximum allowed value			
	of any digit in hidden			
	number.			

Example 1:

Play a game with 4 digits, each in the range 0-5.

Load sides 1 and 2.


Keystrokes:	**Outputs:**
1.23456987 EEX CHS 12 A →	4.5
3214 E →	11.3214 *** (1 right, 1 in right place)
3015 E →	2.3015 *** (2 right)
5234 E →	21.5234 *** (1 right, 2 in right place)
5203 E →	30.5203 *** (3 in right place)
5223 E →	30.5223 ***
5253 E →	40.5253 *** (Correct)!
	6. *** (6 guesses)

Example 2:

The original game of Bagels uses a hidden number of 3 digits, each in the range of 0-9. Play a game of Bagels.

Keystrokes:	**Outputs:**
1.23456987 A →	4.5
3 B →	3.5
9 C →	3.9
512 E →	1.512 ***
702 E →	1.702 ***
217 E →	10.217 ***
236 E →	20.236 ***
235 E →	20.235 ***
239 E →	20.239 ***
238 E →	30.238 ***
	7. *** (Number of guesses)

***Shown by PRINT on HP-97 and by PAUSE on HP-67.



According to Martin Gardner, one of the oldest and most engaging of all two person mathematical games is known today as Nim. The game, perhaps Chinese in origin, is played with counters (often pennies) arranged in piles, and two players alternate in removing one or more objects from one pile at a time. The player taking the last counter or counters wins or loses according to the mode of play.

Nim_k is a generalization of this Nim, first proposed by Prof. E. H. Moore of the University of Chicago in 1910. Nimb is an abbreviated version of Nim provided for the HP-65 and HP-25.

A number of objects or counters (from one to nine) is placed in a desired number of separate piles (from one to nine). You and the calculator take turns removing any number of counters (but at least one) from up to k piles. You choose whether the player taking the last counter wins (W mode) or loses (L mode).

The number k may be from one to eight. It is set at the beginning of the game and does not change during the game. You select both k and the initial arrangement of counters and piles.

To illustrate, choose k = 1 and let 2, 4, 5, and 6 counters be placed in pile numbers 1, 2, 3, 4 as shown below:

k = 1

Pile number: 1 2 3 4

Number of counters in each pile: 2 4 5 6

This will be shown in the calculator display as

1.2456

After the calculator's move, the display

1.2453

tells how many piles you may reduce and how many counters remain. The left-most digit keeps track of how many piles may yet be reduced.

You respond with a pile number, and the number of counters to be removed. Your response is displayed as:

3.1

That is, from pile 3 take 1 counter. The display then shows 0.2443, the zero indicating your move is finished (there are no more piles left from which to remove counters until your next move).

The moves continue back and forth until the last counter or counters are taken by the winner, or in the L mode of play, by the loser.

The game's complete mathematical analysis for k = 1 was first published by C.L. Bouton in 1901. In 1910 E.H. Moore described this generalization which he named Nim_k. As Moore described it, for n piles containing respectively

$$c_1, c_2, \ldots, c_n \text{ counters,}$$

represent these numbers

$$c_i \ (i = 1, \ldots, n)$$

in the binary scale of notation with

$$c_{ij} \begin{pmatrix} i = 1, \ldots, n \\ j = 0, 1, \ldots \end{pmatrix} \text{each 0 or 1}$$

where $c_i = c_{i0} + c_{i1}\, 2^1 + c_{i2}\, 2^2 + \ldots + c_{ij}\, 2^j$

$$(i = 1, 2, \ldots, n).$$

The combination is safe when

$$\sum_{i=1}^{n} c_{ij} = 0 \pmod{k+1} \qquad (j = 0, 1, 2, \ldots).$$

That is, for every place j the sum of the n digits c_{ij} (i = 1, ..., n) is exactly divisible by k + 1. The L mode in which the player taking the last counter or counters loses, requires a change in strategy toward the end of the game. When the number of piles with two or more counters is from 1 to k inclusive, make

$$\sum_{i=1}^{n} c_{i0} = 1 \pmod{k+1} \text{ and } \sum_{i=1}^{n} c_{ij} = 0 \pmod{k+1} \ (j = 1, 2, \ldots).$$

This strategy is continued till the end of the game. A lengthy execution time is required to implement the above expressions.

The present game can be used as a teaching device to achieve an intuitive grasp of the strategy of play since at any time the play can be turned over to the calculator to reveal how it would play. For example, it is clear that if there are fewer than k + 1 piles, your opponent can win by taking all the counters. Such an arrangement is an "unsafe" combination (according to the

W mode of play). A ''safe'' combination would be k + 1 piles of one counter each. At least one counter must be taken by the calculator. That leaves k counters that you can take and win. If instead, k counters had been taken there would still be one left for you to take and win. Similarly, for all other options it is a safe situation for you.

References:

Bouton, Charles L., ''Nim, a Game with a Complete Mathematical Theory.'', *Annals of Mathematics,* Series 2, Vol. 3, pages 35-39, 1901.

Moore, Eliakim H., ''A Generalization of the Game called Nim.'', *Annals of Mathematics,* Series 2, Vol. 11, pages 93-94, 1910.

Redheffer, Raymond M., ''A Machine for Playing Generalized Nim.'', B.S. Thesis in Mathematics, 1943, Massachusetts Institute of Technology.

Gardner, Martin, *Mathematical Puzzles & Diversions,* Simon and Schuster, 1959.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2 of			
	card.			
2	Input choice of k followed by			
	the number of objects in each			
	pile.	$k.p_1p_2p_3...$	E	$k.p_1p_2p_3...$
3	Choose either W or L mode			
	of play:			
	W: player taking last object			
	wins.		C	32.
	L: player taking last object			
	loses.		A	–32.
	Pressing C or A also gen-			
	erates calculator's move.			$k.p_1p_2p_3...$
4	Input choice of pile and number			
	of objects to be removed.	pile.#	D	pile.#
	m = the number of piles yet			$m.p_1p_2p_3...$
	available to choose objects			
	from this turn.			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
5	Repeat step 4 until k piles			
	have been chosen—(or less			
	than k piles if desired) then			
	go to step 3 for calculator's			
	turn.			
6	Continue playing till the last			
	object or objects are taken by			
	the winner (or loser if in L			
	mode).			k.000...
7	For another game, go to			
	step 2.			
8	To learn good move habits,			
	have the calculator play			
	itself. After step 2, repeat			
	step 3 until all piles are empty.			

Example 1:

Load sides 1 and 2.

Keystrokes: **Outputs:**

7.478379895 E ⟶ 7.478379895 ***

You have chosen 9 piles, where counters from up to 7 piles may be removed each turn. The number of counters in each pile is:

Pile number:	1	2	3	4	5	6	7	8	9
Number of counters:	4	7	8	3	7	9	8	9	5

C ⟶ 32. ***

You've chosen the W mode, where the player taking the last counter wins.

7.455155555 ***

After the calculator moves (unfortunately for you, it does a lot of thinking), it leaves the above pile arrangement .

You choose to take 4 counters from pile 2:

2.4 D → 2.4 ***
6.415155555 ***

You can still remove counters from 6 more piles this move. You elect to remove counters from all 6 as follows:

3.4 D → 3.4 ***
5.411155555 ***

5.4 D → 5.4 ***
4.411115555 ***

6.4 D → 6.4 ***
3.411111555 ***

7.4 D → 7.4 ***
2.411111155 ***

8.4 D → 8.4 ***
1.411111115 ***

9.4 D → 9.4 ***
0.411111111 ***

Now it's the calculator's turn.

C → 32. ***
7.011111111 ***

The handwriting is on the wall, but you gamely continue:

9.1 D → 9.1 ***
6.011111110 ***

It's all over but the last move:

C → 32. ***
7.000000000 ***

The calculator won this one, but maybe if you chose the L mode, you'd do better. Why don't you try?

***Shown by PRINT on HP-97 and by PAUSE on HP-67.


Notes

Queen Board



This game is based on the moves of a chess queen. A queen will be allowed to move only to the left, down, or diagonally to the left. The object of the game is to be the first player to move the queen to the lower left-hand corner of the chess board (square 158), by alternating moves between you and the calculator. You start by placing the queen on any square on the top row or right-hand column. This is your first move. The play then alternates.

The playing board is numbered as follows:



You tell the calculator your moves by keying in the number of the square you start on or move to. Press **A** and the calculator responds with the square it moves to. Square 158 is the winning square.

The program does not check for illegal moves. If you win (by moving to square 158), the program will respond with 168 (the calculator acknowledges the loss by displaying a nonexistent square).

The magnetic card was recorded in DSP 0 mode, so only integers will be displayed.

Reference:

This program is based on an HP-65 Users' Library program by Jacob R. Jacobs.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1.			
2	Key in your starting position			
	(first move).	Move	A	Calculator's
				move
3	Repeat step 2 until someone			
	wins.			

Example:

Load side 1.

Keystrokes: **Outputs:**

55 A ——————→ 75.

(You start on 55, and the calculator, after deep and careful thought, moves to 75).

97 A ——————→ 127.

(You respond with 97, and the calculator, showing no mercy, moves to 127).

148 A ——————→ 158.

(You try 148, hoping the calculator's batteries run down before it can respond, but no luck—it wins by moving to 158).

Hexapawn



Hexapawn is a game which is programmed to learn from its mistakes. The game is played with chess pawns on a 3 × 3 board. Pawns may advance one square at a time or capture the opponent's pawns by moving diagonally one square. The game starts with the pawns positioned as follows:




Figure 1. Starting position of pawns

The two allowed opening moves for the first player (in this example, white) are A and B:




Figure 2. Opening moves

Since position C is a mirror image of A, it is not used. Black's three possible responses to white's A move are D, E and F.




Figure 3. Black's responses to white's A move

Black can move diagonally and capture white (D), or he can move either **b** or **c** straight ahead one square. Black pawn at **a** is blocked. Note that the only way a pawn can move to an open square is straight ahead. Also, the only way a pawn can capture is by moving diagonally.

The game is won by advancing a pawn to the third row, capturing all of the opponent's pawns, or creating a position in which the opponent cannot move.

Moves are made by keying in a board position selected from the set of board positions (shown in Figure 4 or Figure 5). The numbered arrows in each diagram indicate the possible choices the machine has for its replies. A reply of "0.00" indicates that the calculator has decided to forfeit the game. The machine selects its move at random, but whenever it is punished, it forgets the previous move. Thus, if the machine makes a poor move and is punished, it will not repeat the mistake.*

Since it is not easy for a human to visualize the changing game board, it is suggested that you follow your game on the playing board on page 10-03. You might use silver colored coins for white and pennies for black.


*Similarly, if you punish the machine for making good moves, it will eventually lose consistently—the calculator is your slave.

Reference:

This program was published in *65 Notes,* Vol. 2, No. 3. The HP-65 version was written by John R. Rausch.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Initialize:			
	Human moves first		f C	
	or Calculator moves first.		C	
	Then, after waiting a few			
	seconds, stop the random			
	number generator.		R/S	
3	Input the board position which			
	exists after your move.	Position	A	Response
4	Update your own board and			
	repeat step 3 until the game			
	is over.			
5	If the machine lost, punish it.		B	

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
6	To play another game:			
	a) If the same player plays			
	first, go to step 3.			
	b) If the other player plays			
	first, go to step 2.			



Playing Board for Hexapawn

Board Positions and Responses

You move *first:* You are white (○)




Figure 4

Board Positions and Responses

You move *second:* You are white (○)




Figure 5

Example 1:

Load sides 1 and 2.

Keystrokes: **Outputs:**


You move first.

f C (Wait a few seconds.)

R/S → Ignore display.


If you store .70879 in register 6, the game will proceed as follows:
You start by moving your left pawn, giving board position 1. The calculator responds with move 1.

1 A →



Board position 1


1.00



Board after calculator's response


You capture, resulting in board position 13. In response, the calculator makes the only possible move.

13 A →



Board position 13

1.00




Board after calculator's response

You can't move, so the calculator wins.


Example 2:

You start again by making the same opening move (board position 1). This time the calculator chooses move 2.

1 A ——————→ 2.00




Board position 1



Board after calculator's response

You move your right pawn forward, making it impossible for the calculator to move. You win.



Your winning board position

Since the calculator's move was a foolish one, you punish it.

B ——————→ Ignore output.

Now the calculator will not respond to board position 1 with move 2, unless you scramble its brain by removing the Hexapawn program from its memory and then reloading it.


By continuing to punish the calculator for unwise moves, it will soon play without error. Then be prepared for some tough games.

Notes

Tic-Tac-Toe




The game of tic-tac-toe hardly needs any introduction. In this one, you play versus the calculator. Moves are entered by keying in the appropriate position number selected from the diagram shown below. The calculator moves first at (2) so you will have a better chance to draw.



If you make any bad moves, the calculator will win; otherwise, the game will end in a tie.

You can use copies of the playing board below to follow your games.



Reference:

This program is based on an HP-65 Users' Library submittal by Delmer D. Hinrichs.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Initialize.		f A	0.000000000
3	To start a game		A	Board*
4	Repeat step 5 until the end of			
	the game.			
5	Your turn. Enter position			
	number (see diagram above).	$1 \leq x \leq 9$	R/S	
	The calculator will move,			
	and the resulting position will			
	be output.			Board*
6	To start a new game, go to			
	step 3.			
	*For instance, this PRINT/			
	PAUSE output: 4.121, 4.112,			
	4.212, 7.212112121 cor-			
	responds to this board			
	position:			
	1 2 1 1 1 2 2 1 2			
	Your moves are shown by 2's,			
	the calculator's moves are			
	shown by 1's. The 4. in each			
	PAUSE display means you have			
	finished your 4th move.			
	The 7 means the calculator has			
	just moved into position 7			
	(see diagram above).			


Example:

Load sides 1 and 2.

Keystrokes:	**Outputs:**
f A →	0.000000000

The calculator starts by making the move it will always make when a new game begins:

A →	0.000 ***
	0.000 ***
	0.010 ***
	0.010000000




Board position 1A
Calculator's opening move

You put your "2" in square 3, and the calculator responds with square 5.

3 R/S →	1.000 ***
	1.010 ***
	1.012 ***
	5.012010000



Board position 1B
You move to square 3



Board position 2A
The calculator moves to square 5

8 R/S →

2.021 ***
2.010 ***
2.012 ***
9.012010021

	2	
	1	
	1	2

Board position 2B
You move to square 8

	2	1
	1	
	1	2

Board position 3A
The calculator moves to square 9

1 R/S →

3.021 ***
3.110 ***
3.212 ***
4.212110021

	2	1
	1	
2	1	2

Board position 3B
You move to square 1

	2	1
1	1	
2	1	2

Board position 4A
The calculator moves to square 4

6 R/S →

4.121 ***
4.112 ***
4.212 ***
7.212112121

	2	1
1	1	2
2	1	2

Board position 4B
You move to square 6

1	2	1
1	1	2
2	1	2

Board position 5A
The calculator moves to square 7

You've battled the calculator to a tie, which gives you a moral victory.

Flushed with success, you decide to play another game:


A →	0.000 ***
	0.000 ***
	0.010 ***
	0.010000000
5 R/S →	1.000 ***
	1.020 ***
	1.110 ***
	1.110020000

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

You might wish to continue this game. The calculator is a very good Tic-Tac-Toe player, so be careful!


Notes

Wari



Wari* is a board game which has been played for at least several centuries in various forms throughout Africa. The game is played on a board containing (generally) twelve small pits or bins, and two large pits. Forty-eight beads, seeds, or other counters are moved and captured according to certain rules.

The Wari board is shown here set up to begin a game.



Wari Board at start of game

Bin 1	4.04	Bin 1
	4.04	
Player 1	4.04	Player 2
	4.04	
	4.04	
Bin 6	4.04	Bin 6

HP-97 Wari Printout at start of game**

Each player in turn removes all the counters from one bin on his side and distributes them one-at-a-time into successive bins moving counterclockwise, skipping the two bins which are for storing captured counters. If the last counter drops into an opponent's hole containing one or two counters, the contents of that hole are captured and placed in the player's scoring pit. Counters in an unbroken sequence of two- and three-counter bins on the opponent's side clockwise from the captured bin are also captured. If a bin contains twelve counters or more, that bin is skipped when the counters from that bin are distributed.

The above rules are implemented in the calculator program. Special rules, such as prohibiting moves which remove all of the opponent's counters, were deemed to be variations of the basic game and were not programmed. It is possible to come to a situation where a few counters will circulate forever. In this case each player claims the counters on his side.

* Also known as Man-Kalah, Awari, and many other names.

**The HP-67 displays this information in PRINT/PAUSE mode.

To make a play on the calculator Wari board, the player specifies the bin he wants to move by keying in a number from 1 to 6 and then pushing either A or E. The machine then moves the counters from the specified bin according to the rules, prints the resulting position and displays the updated score. If you play this game on an HP-67, you must copy down the position as it is print/paused. To review the position, press B. To redisplay the score, press D.

An elementary strategy is also implemented in this program so that a player may match his wits against the machine. The machine is able to make obvious, though not brilliant, captures. The machine does not attempt to avoid having its counters captured, so it is a relatively poor opponent.

A special situation exists (covered by the Example) when one side (say side 1) has no counters. If player 1 is a human, he or she passes until consecutive moves by player 2 puts counters on side 1. If player 2 is the calculator, player 1 presses f E to cause the calculator to move.

If the calculator is playing the side that is temporarily without counters, move your counters in the usual way (Move A), and then press R/S anytime after the board is print/paused. Next, make your next move (Move A), and so on until the board shows a counter on the calculator's side. At that time, let the calculator make its move.

References:

Zaslavski, Claudia, *Africa Counts–Number and Pattern In African Culture,* Prindle, Weber & Schmidt, Inc., Boston, 1973.

Rules for Man-Kalah!, Skor-Mor Corp., 1970.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Start.		C	Board**, 0.00
3	Player 1: Select move (choose			
	bin number from 1 to 6).	Move	A	Board, score
4	If 2 humans are playing, go			
	to step 5.			
	If a human is playing the cal-			
	culator, go to step 9.			
	**See text and example.			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
5	Player 2: Select move.	Move	E	Board, Score
6	If one player cannot move (no			
	counters), he skips his turn			
	and the other player plays			
	again.			
7	Repeat steps 3, 5 and 6 until			
	the game is finished.			
8	For another game, go to			
	step 2.			
9	Human: Tell calculator to be			
	your opponent, and instruct it			
	to move automatically after			
	each of your moves.			
	For HP-67:		h CF	
			0 f	
			E	Move,
				Board,
				Score
	For HP-97:		f CLF	
			0 f	
			E	Move,
				Board,
				Score
10	Select move (choose bin			
	number from 1 to 6).	Move	A	Board,
				Move,
				Board,
				Score

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
11	If you cannot move (no			
	counters), tell calculator to			
	move again.		f E	Board,
				Score
12	If the calculator cannot move			
	(no counters), stop calculator's			
	automatic move.		R/S	
	And move your counter(s)			
	again.	Move	A	
13	Repeat steps 10, 11 and 12			
	until the game is finished.			
14	For another human/calculator			
	game, press START,		C	
	and go to step 10.			
15	For a human/human game,			
	tell calculator politely that it is			
	no longer playing:			
	For HP-67		h SF	
			0	
	For HP-97		f STF	
			0	
	and go to step 2.			
16	To review position		B	Board
17	To review score		D	Score

Example:

You have decided to challenge the calculator.

Load sides 1 and 2. To reproduce this example, completely clear all registers.

Keystrokes: **Outputs:**

C →

4.04 ***
4.04 ***
4.04 ***
4.04 ***
4.04 ***
4.04 *** } Starting board
0.00 Score

Move 1:

You choose to move your counters out of bin 2:

2 A →

4.04 ***
0.04 ***
5.04 ***
5.04 ***
5.04 ***
5.04 *** } Board after your 1st move
0.00 Score

For HP-67: h CF 0 f E
For HP-97: f CLF 0 f E

3.00 *** Calculators 1st move

5.05 ***
1.05 ***
5.00 ***
5.04 ***
5.04 ***
5.04 *** } Board after Cal's 1st move
0.00 Score

After you dropped each of your 4 counters from your bin 2 into your bins 3, 4, 5 and 6 (moving counterclockwise), the calculator decided to move its counters from its bin 3. Note that bins are numbered from top to bottom for both sides and that both sides move counterclockwise.

Move 2:

5 A →

5.05 ***
1.05 ***
5.01 ***
5.05 ***
0.05 ***
6.05 *** } Board after your 2nd move
4.00 *** Cal's 2nd move

6.06 ***
0.06 ***
5.02 ***
5.00 ***
0.05 ***
6.05 *** } Board after Cal's 2nd move
0.02 Score

The calculator has struck the first blow. The 5 counters from its bin 4 went to its bins 3, 2, 1 and your bins 1 and 2. Since the last bin reached (your bin 2) contained only one lonely counter, both your counter and the attacking counter were removed, making the score 0 to 2, the calculator leading. If your bin 2 had contained 2 counters, they would have been captured, and the score would have been 0 to 3. Had your bin 2 contained 3 or more counters, you would have been safe.

You and the calculator continue moving as follows:

Move no.	Your move	Cal's move	Score
3	6	5	0-2
4	4	6	3-4

Here's the board after Cal's move 4:

8.09 ***
0.09 ***
5.05 ***
0.01 ***
1.02 ***
1.00 ***
3.04 Score

Move 5:

1 A ——————→

0.09 ***
1.09 ***
6.05 ***
1.00 *** } Board after your 5th move
2.00 ***
2.01 ***
6.00 *** Cal's 5th move

0.09 ***
1.09 ***
6.05 *** } Board after Cal's
1.00 *** } 5th move
2.01 ***
2.00 ***
8.04 Score

You moved the 8 counters from your bin 1 around the board counterclockwise, ending up in Cal's bin 4. Looking clockwise from Cal's bin 4, note that Cal's bin 5 has only 2 counters. So you take the single counter in 4 (plus your counter) and the 2 counters in 5 (plus your counter), giving you a take of 5 counters. If Cal's bin 6 had contained 1 or 2 counters (before you added yours), you would have added another 2 or 3 to your score.

The game continues:

Move no.	Your move	Cal's move	Score
6	6	3	10-4
7	5	2	12-4
8	6	1	16-4
9	6	4	18-4
10	3	5	18-4
11	6	3	20-4
12	4	1	20-4
13	5	2	27-4
14	1	1	27-4
15	1	6	27-4
16	3	5	27-4
17	6	6	29-4
18	2	5	29-4
19	6	2	31-4
20	1	3	31-4
21	2	1	31-4
22	3	4	31-4
23	1	3	31-4
24	2	2	31-4
25	1	1	31-4

After Cal's 25th move, the board looks like this:

```
1.00 ***
2.00 ***
1.00 ***   } Board
5.00 ***
4.00 ***
0.00 ***
31.04      Score
```

Move 26:

3 [A] ⟶

```
1.00 ***
2.00 ***
0.00 ***
6.00 ***
4.00 ***
0.00 ***
```

Since there are no counters on the calculator's side, it cannot move. You therefore stop its otherwise endless search for the nonexistent counter for it to move.

[R/S] ⟶ Hold key until display stabilizes. Ignore output.

You then move again (5 [A]), and the game then proceeds normally. The calculator's succeeding moves depend on how long you wait before pressing [R/S], since the program's random number generator runs during the calculator's search for a counter. Therefore, the rest of this example shows one of several possible outcomes.

Move no.	Your move	Cal's move	Score
27	5	5	31-4
28	6	4	33-4
29	4	5	35-4
30	6	4	37-4
31	1	2	37-4
32	1	1	37-4
33	1	3	37-4
34	2	6	37-4
35	3	5	37-4
36	5	4	37-4
37	4	3	37-4
38	6	4	37-4
39	5	5	37-4
40	6	4	40-4

The board looks like this after Cal's half of the 40th move:

0.00 ***
0.02 ***
0.02 ***
0.00 ***
0.00 ***
0.00 ***

You have no counters and cannot move. So you ask the calculator to move again:

Move 41:

f E ——————→ 3.00 *** Cal's move

0.01 ***
0.03 ***
0.00 ***
0.00 ***
0.00 ***
0.00 ***

} Board after Cal's 41st move

Ruthless in victory, you seek even more victims:

Move no.	Your move	Cal's move	Score
42	No move	2	40-4
43	2	1	40-4
44	1	No move	40-4
45	2	No move	40-4
46	4	No move	40-4
47	3	No move	40-4
48	5	6	40-4
49	6	6	42-4

This is the final board following Cal's last move:

0.00 ***
0.00 ***
0.00 ***
1.00 ***
0.01 ***
0.00 ***

Since these two counters would chase each other forever, the game is called. Each remaining counter is counted for the side in whose bin it lies, making the final score:

Human: 43
Machine: 5

The machines have not taken over yet, but don't underestimate this opponent. It can give you trouble.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Racetrack



This program is based on a pencil-and-paper game published in Martin Gardner's "Mathematical Games" column in *Scientific American* (May, 1973). Up to five contestants race on a superelliptical track. Players take turns inputting acceleration (direction and magnitude) and the machine updates the velocity and position of each racer and checks for collision, shown by flashing the ID number(s) of the other racer(s) involved. Racers are considered to have collided if they approach within 2 units of each other. All racers involved in a collision are penalized by having their velocities reduced to zero. A racer that leaves the track or is off the track is similarly penalized. Thus, a racer leaving the track at high velocity might require several moves to get back on—so watch out!

The track is bounded by two superellipses:

outer boundary


$$\left(\frac{x}{80}\right)^{5/2} + \left(\frac{y}{100}\right)^{5/2} = 1$$

inner boundary


$$\left(\frac{x}{50}\right)^{5/2} + \left(\frac{x}{70}\right)^{5/2} = 1$$

At the start, the five racers are located as shown on the racetrack at the points (55, 0), (60, 0), (65, 0), (70, 0), and (75, 0). Moves are made by placing direction in the y-register, acceleration in the x-register, and pressing A, B, C, D, or E as appropriate for the desired racer. The direction convention used is shown on the racetrack. To simulate frictional effects, the maximum acceleration is 9 units per second per second.

It is convenient to keep track of the progress of the race by plotting the positions of the racers on a copy of the accompanying racetrack. By observing the changing positions of the racers, it is easier to determine what the next move should be.



Race between snail and turtle



Racetrack
Shows grid and starting positions

Reference:

This program was first programmed for the HP-65 Users' Library by Delmer D. Hinrichs.

The superellipse is described in the following article:

Gardner, Martin, "The Superellipse: a Curve that lies between the Ellipse and the Rectangle," *Scientific American,* Sept. 1965, 222-234.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Start.		f C	Ignore output.
3	Move racers in turn.			
	Car: Input angle	θ	ENTER↑	
	and acceleration.	a	A	1, stack*
	Turtle: Input angle	θ	ENTER↑	
	and acceleration.	a	B	2, stack*
	Snail: Input angle	θ	ENTER↑	
	and acceleration.	a	C	3, stack*
	Wagon: Input angle	θ	ENTER↑	
	and acceleration.	a	D	4, stack*
	Rabbit: Input angle	θ	ENTER↑	
	and acceleration.	a	E	5, stack*
4	To check the position of any			
	racer, input ID.	$1 \leq ID \leq 5$	f A	ID y, x
	*The contents of the the			
	stack are			
	angle of velocity T			
	velocity Z			
	y-coordinate Y			
	x-coordinate X			

Example:

A race is proposed between the turtle and the snail. They decide to race around the first turn to the finish line shown. By watching how they race, we might learn some tricks.

Load sides 1 and 2.

Keystrokes:	**Outputs:**
Initialize.	
f C ⟶	-3.00 (Ignore this display.)

The racers start by accelerating in the directions 110 and 90 at the maximum acceleration.

110 ENTER↑ 9 B ⟶	2.00 *** Turtle's I.D.
	110.00 *** T Direction of Turtle
	9.00 *** Z Speed of Turtle
	4.32 *** Y y-position of Turtle
	58.46 *** X x-position of Turtle
90 ENTER↑ 9 C ⟶	3.00 *** Snail's I.D.
	90.00 *** T Direction of Snail
	9.00 *** Z Speed of Snail
	4.50 *** Y y-position of Snail
	65.00 *** X x-position of Snail

Turtle now speeds on in the same direction and Snail begins a slow left turn.

110 ENTER↑ 9 B ⟶	2.00 *** Turtle's I.D.
	110.00 *** Direction of Turtle
	18.00 *** Speed of Turtle
	16.91 *** y-position of Turtle
	53.84 *** x-position of Turtle
100 ENTER↑ 9 C ⟶	3.00 *** Snail's I.D.
	95.00 *** Direction of Snail
	17.93 *** Speed of Snail
	17.93 *** y-position of Snail
	64.22 *** x-position of Snail

100 ENTER↑ 9 B →

```
  2.00 *** Turtle
106.67 *** Direction
 26.91 *** Speed
 38.26 *** y
 46.91 *** x
```

100 ENTER↑ 9 C →

```
  3.00 *** Snail
 96.67 *** Direction
 26.91 *** Speed
 40.23 *** y
 61.87 *** x
```

Turtle now begins to turn left a little more…

225 ENTER↑ 5 B →

```
  2.00 *** Turtle
116.84 *** Direction
 24.93 *** Speed
 62.27 *** y
 37.42 *** x
```

… and so does Snail.

180 ENTER↑ 9 C →

```
  3.00 *** Snail
114.40 *** Direction
 29.35 *** Speed
 66.95 *** y
 54.25 *** x
```

250 ENTER↑ 9 B →

```
  2.00 *** Turtle
136.12 *** Direction
 19.89 *** Speed
 80.28 *** y
 24.63 *** x
```

260 ENTER↑ 9 C →

```
  3.00 *** Snail
127.46 *** Direction
 22.50 *** Speed
 89.25 *** y
 41.34 *** x
```

250 ENTER↑ 9 B →

```
  2.00 *** Turtle
162.99 *** Direction
 18.21 *** Speed
 89.84 *** y
  8.75 *** x
```

Snail realizes he is going too fast and he turns sharply left, but...

270 ENTER↑ 9 C ⟶

```
  3.00 *** Snail
  0.00 *** OOPS! Snail
  0.00 *** crashes
102.61 *** through the fence.
 27.65 ***
```

Turtle roars across the finish line.

220 ENTER↑ 9 B ⟶

```
  2.00 *** Turtle
-178.92 *** Direction
 24.31 *** Speed
 92.28 *** y
-12.11 *** x is less than -10,
           so Turtle has won.
```

Even though he has lost, Snail would like to try to get back on the track and finish the race.

250 ENTER↑ 9 C ⟶

```
  3.00 *** Snail
  0.00 *** Still off the track,
  0.00 *** but closer
 98.38 *** y
 26.11 *** x
```

180 ENTER↑ 9 C ⟶

```
  3.00 *** Snail
180.00 *** Hooray! Snail
  9.00 *** made it back to the
 98.38 *** racetrack.
 21.61 ***
```

190 ENTER↑ 9 C ⟶

```
  3.00 *** Snail
-175.00 *** Direction
 17.93 *** Speed
 97.60 *** y
  8.18 *** x
```

Now Snail should be able to cross the finish line only three moves after Turtle.

250 ENTER↑ 9 C ⟶

3.00	***	Snail
2.00		(flashing) Snail crashed into Turtle!
0.00	***	Direction
0.00	***	Speed
91.81	***	y
−11.22	***	x

Well, folks, that's it from the HP racetrack: Snail came in second and Turtle was next to last.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Teaser



The object of this game is to convert the pattern

```
0 0 0
0 1 0
0 0 0
```

To the pattern

```
1 1 1
1 0 1
1 1 1
```



by changing 1's to 0's. The only legal move is changing a 1 to a 0. Consequently, the only allowable opening move is changing the 1 in the center of the board to a 0. When a 1 is changed to a 0, certain other 1's and 0's also change according to these rules:

1. A move in a corner causes all 1's and 0's in a 2 × 2 box containing the corner to change state.

```
1 0 1                    1 0 1
1 1 0                    1 0 1
0 0 1 <-- a move here yields:   0 1 0
```

2. A move in the center of an edge causes all 1's and 0's on that edge to change state.

```
1 0 0                    1 0 1
1 0 1 <-- a move here yields:   1 0 0
1 0 0                    1 0 1
```

3. A move in the center causes all 1's and 0's in a "+" to change state.

```
1 0 0                    1 1 0
0 1 1 <-- a move here yields:   1 0 0
1 0 0                    1 1 0
```

References:

Nico, Willard I., "Shooting Stars," *Byte,* May, 1976, pp. 42-48.

People's Computer Center, *What To Do After You Hit Return,* People's Computer Company, Menlo Park, 1975, p.54.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Initialize.		C	Board*
3	Move.	1 ≤ moves ≤ 9	A	Board
4	Repeat step 3 until the pattern			
	1 1 1			
	1 0 1			
	1 1 1			
	is reached.			
5	To suppress printing		E	0**
6	To reinstate printing		E	1**
	*The board is both print/paused			
	in the form			
	0.789			
	0.456			
	0.123			
	and displayed as			
	9.123456789 xx			
	where xx is the number of			
	moves you've completed.			
	**If you don't get the desired			
	output, press E again.			

Example:

Load sides 1 and 2.

Keystrokes:	**Outputs:**
C →	0.000 ***
	0.010 ***
	0.000 ***
	9.000010000 00
5 A →	0.010 ***
This is the only possible move.	0.101 ***
	0.010 ***
	9.010101010 01
6 A →	0.011 ***
	0.100 ***
	0.011 ***
	9.011100011 02

The game continues. We pick up the action several moves later.

4 A →	0.100 ***
	0.011 ***
	0.100 ***
	9.100011100 09
6 A →	0.101 ***
	0.010 ***
	0.101 ***
	9.101010101 10
5 A →	0.111 ***
	0.101 ***
	0.111 ***
	9.111101111 11

All you have to do is fill in the missing moves and you've got the solution.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Notes

Golf




You choose your handicap, design your course, select and swing your club, and hope your ball escapes the woods. One or two people can play.

After you design each hole (actually, your HP-67/97 designs each hole for you), the hole number, hole yardage, par, and distance to the woods are output. After each shot, you are given the distance the ball was hit, the angle the ball was hit relative to the hole's direction, the coordinates of the ball's position, the remaining distance to the hole, and the angle between the ball-hole line and the direction from tee to hole.

The woods are called the deep woods, because that's the kind of trouble you may be in if your ball lands there. If such bad luck befalls you, you have the option of taking a penalty stroke and hitting a second ball from the same spot, or slashing your way through the brambles to find and hit your ball where it lies. The woods are not only thick, but also magic. You can see the flag from every position in the woods, and consequently you always aim directly for the flag. However, if your aim is less than excellent, your ball will hit from one to many trees. Your distance will be sharply reduced, and you may even find yourself moving away from the flag rather than towards it.

Think twice before following your ball into the woods and hitting it from there, since if you do, you have no choice but to club your way out. The example with two players shows what can happen.



General Hole Layout

All clubs may be swung with a full swing or less, allowing you to adjust your swing according to the distance to the hole.

The distance and angle achieved with each hit varies randomly about a mean value. The ball is always aimed directly at the hole, and the deviation from this direction tends to get worse as your handicap increases. The maximum possible distance with each club is independent of handicap, but the means and minimum possible distances decrease as handicap increases. When using a particular club, the number of yards between maximum and minimum possible yardage remains the same, regardless of whether full or partial swing is used. It is generally wise, therefore, to use a full swing whenever possible.

Table 1 gives the mean distances achieved with each club for a 0 handicap player:

TABLE I

Club	Mean Distance	Club	Swing Factor	Mean Distance
1 Wood	260 yds.	10 Iron	1	100
2 Wood	240 yds.	10 Iron	.5	50
3 Wood	220 yds.	11 Iron	1	90
4 Wood	200 yds.	11 Iron	.5	45
1 Iron	190 yds.	Putter	1	10
2 Iron	180 yds.	Putter	.5	5
3 Iron	170 yds.			
4 Iron	160 yds.			
5 Iron	150 yds.			
6 Iron	140 yds.			
7 Iron	130 yds.			
8 Iron	120 yds.			
9 Iron	110 yds.			

The course near each green is treacherous. Tall grass, traps, and other undefined problems will reduce your chipping accuracy. The greens are also challenging. Only the best golfers can do well.

In spite of the championship nature of this course, a duffer can beat the best because of the method of scoring. After each hole is completed, the player's adjusted score is given. This compares the total strokes less handicap against total par for the number of holes completed. While an 18 handicapper may have more trouble with woods, approach shots and green, his score is reduced by 1 stroke per hole before being compared against par. A negative adjusted score means you're beating par.

When playing 2 person golf, it is easy to keep track of whose storage register bank is active (Did I press f P≷S or didn't I?). One way is to recall R7 and see whose handicap is displayed. Another way is to use R6 in each bank to hold an identifying number (such as 1 or 2) for each player. Recalling R6 could then display the player number whose bank was active.

If you want to simplify the game by moving the woods further away for all holes (or make it more difficult by moving the woods closer), change the woods constant as follows:

1. Choose minimum and maximum woods distances ($W_{max} = 3W_{min}$). The standard range is from 60 to 20 yards from the fairway centerline.
2. Determine the midpoint of this range (must be a 2 digit integer). This is your new woods constant.
3. Press GTO .018.
4. Switch to PRGM. The display will show 018 00.
5. Remove old woods constant by pressing DEL two times. The display will show 016–55 (HP-97) or 016 61 (HP-67).
6. Key in new woods constant. This must be a 2 digit integer, such as 70 or 55. The display will show 018 OX (where X is the second digit of your new constant).
7. Switch to RUN.

When you've inserted your woods constant into program memory, you might wish to preserve the revised program by recording it on a magnetic card.

TABLE II

Symbols

u_0	Initial random number seed.
H	18 hole handicap.
h	Hole number.
Y_h	Hole yardage.
W	Distance from centerline of fairway to right and left woods.
C#	Club number.
Y_c	Distance ball hit (club yardage).
θ_c	Angle ball hit relative to hole direction. A 0° angle means the ball is hit directly towards the hole.
y	y coordinate of ball's position after hit.
x	x coordinate of ball's position after hit.
D_h	Distance from ball to hole after hit.
ϕ_h	Direction to hole after hit. If $\phi = 0°$, the ball lies on the fairway's centerline, the line between tee and hole.
S	Adjusted score. This equals the sum of pars for the holes played subtracted from total strokes reduced by adjusted handicap (adjusted for number of holes played).

In symbols:

$$S = \left(\text{Total strokes} - \frac{hH}{18}\right) - \Sigma \text{ par}$$

A negative S means you're beating par.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Clear registers.		f CL REG	
			f P≠S	
			f CL REG	
3	Choose and store a six			
	digit random number seed			
	u_0, between 0 and 1 such as			
	.345762. To change the		STO A	
	character of each game, store			
	a different random number.			
4	For one person golf, go to			
	step 5. For two people golf, go			
	to step 13.			
	ONE PERSON GOLF			
5	Store your 18 hole handicap			
.	(handicap may not be negative).	H	STO 7	H
6	Design hole.		A	h, Y_h, Par, W*
7	Choose club and enter club			
	number:			
	Either:			
	Wood (Club #1, 2, 3 or 4),	C#	B	0
	or:			
	Iron (Club #1, 2, 3, 4, ..., 10			
	or 11),	C#	C	0
	or:			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	Putter (use only if hole dis-			
	tance (D_h) is 10 yds or less).		D	0
8	Choose and enter swing			
	factor s, where s is from			
	0 to 1.	s	R/S	See below
				for output.
9	If you want to take a penalty			
	stroke and hit another ball from			
	the same place, go to step 29.			
	Otherwise, go to step 10.			
10	Repeat steps 7, 8 and 9 until			
	ball is holed.			
11	When ball is holed, start next			
	hole at step 6.			
12	For new game, start at step 2			
	(you may omit step 3).			
	TWO PEOPLE GOLF			
13	Store 18 hole handicaps (must			
	be zero or positive).			
	Player 1:	H_1	STO 7	
			f P≷S	H_1
	Player 2:	H_2	STO 7	
			f P≷S	H_2
14	Design hole.		A	h, Y_h Par, W*
15	Player 1, make your mark.	1	SPACE	
			PRINT X	1†*
16	Player 1, choose club and			
	enter club number:			
	Either:			
	Wood (Club #1, 2, 3 or 4),	C#	B	0
	or:			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	Iron (Club #1, 2, 3, ..., 10			
	or 11),	C#	C	0
	or:			
	Putter (use only if hole dis-			
	tance (D_h) is 10 yds or less).		D	0
17	Player 1, choose and enter			
	swing factor s, where s is			
	from 0 to 1.	s	R/S	See below
				for output.
18	Player 1, if you want to take a			
	penalty stroke and hit another			
	ball from the same place, go to			
	step 29. Otherwise, go to			
	step 19.			
19	Player 1, has player 2 finished			
	this hole?			
	Yes: Repeat steps 16, 17 and			
	18 until you finish this			
	hole. Then go to step 14.			
	No: Allow player 2 to hit his ball.		f P%S	
	Note: Steps 20, 21, 22 and 23			
	are identical to steps 15, 16, 17			
	and 18, except player 2 is			
	playing instead of player 1.			
20	Player 2, make your mark.	2	SPACE	
			PRINT X	2†*
21	Player 2, choose club and			
	enter club number:			
	Either:			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	Wood (Club #1, 2, 3 or 4),	C#	B	0
	or:			
	Iron (Club #1, 2, 3, ..., 10			
	or 11),	C#	C	0
	or:			
	Putter (Use only if D_h = 10 yds			
	or less).		D	0
22	Player 2, choose and enter			
	swing factor s, where s is from			
	0 to 1.	s	R/S	See below for
				output.
23	Player 2, if you want to take a			
	penalty stroke and hit another			
	ball from the same place, go to			
	step 29. Otherwise, go to			
	step 24.			
24	Player 2, has player 1 finished			
	this hole?			
	Yes: Repeat steps 21-23 until			
	ball is holed. Then go to			
	step 26.			
	No: Allow player 1 to hit his			
	ball.		f P↕S	
25	Player 1, go to step 15.			
26	Player 2, allow player 1 to hit			
	his tee shot.		f P↕S	
27	Player 1, go to step 14.			
28	For new game, go to step 2			
	(you may omit step 3).			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
29	To take penalty stroke:		1 STO	
			+ 1	
		previous y	STO 2	
		previous x	STO 3	
		previous D_h	STO 4	
		previous ϕ_h	STO 5	
	Then go to next step (10, 19			
	or 24).			
	Output: After choosing and			
	inputting club number and			
	swing factor, the following			
	output is provided:			
	Either:			
	If ball is not sunk in hole:			Y_c, θ_c,
				y, x,
				D_h, ϕ_h*
	Note: A six decimal output for			
	D_h and ϕ_h show that ball has			
	landed in woods.			
	Or:			
	If ball is holed:			0.000000000,
				S*
	*After obtaining this output,			
	player may review his situation			
	as follows:			
	18 hole handicap		RCL 7	H
	Total strokes (not reduced			
	by handicap)		RCL 1	S′

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	Total par of holes played or			
	started		RCL 9	Σ par
	†These steps are optional.			

Example 1:

One player game.

This records the first hole fortune of Ken Brambles, a moderately accomplished Sunday afternoon golfer carrying an 18 hole handicap of 18.

Load side 1 and side 2.


Keystrokes:	**Outputs:**
f CL REG f P≷S f CL REG	
.637914 STO A →	1. u_0 Seed

Since the program is run in DSP 0 format, numbers are rounded to the nearest whole number.

18 STO 7 →	18.
A →	1. *** h Hole no.
	241. *** Y_h Hole yd.
	4. *** Par
	20. *** W Woods dist.
2 B →	0.
1 R/S →	229. *** Y_c Club yd.
	10. *** θ_c Club angle
	−15. *** y } Ball location
	40. *** x }
	42.981363 *** D_h Hole dist.
	−69.671474 *** ϕ_h Hole angle

A six decimal place output for D_h and ϕ_h shows ball has landed in woods.

Ken's tee shot covered 229 yards with a very acceptable 10° slice. His ball is now located as follows:



Ken, a cautious man, elects to take a penalty stroke rather than fight the woods, especially since he's 20 yards from the fairway at the nearest point. Note that −229 and 0 are input as previous y and x, since these are the coordinates of the tee (see drawing on page 15-02).

1 STO + 1 229 CHS STO 2	
0 STO 3 229 STO 4 0	
STO 5 2 B →	0.
1 R/S →	211. *** Y_c Club yd.
	−2. *** θ_c Club angle
	−19. *** y −6. *** x } Ball location
	19. *** D_h Hole dist.
	18. *** ϕ_h Hole angle
11 C →	0.
.2 R/S →	4. *** Y_c Club yd.
	−11. *** θ_c Club angle
	−15. *** y −5. *** x } Ball location
	16. *** D_h Hole dist.
	20. *** ϕ_h Hole angle

11 C →
.2 R/S →

0.
20. *** Y_c Club yd.
1. *** θ_c Club angle
4. *** y
2. *** x } Ball location
5. *** D_h Hole dist.
−154. *** ϕ_h Hole angle

Since D_h is less than 10 yards, the distance from the edge of the green to the hole, Ken has made the green. A D_h of 10 yards also means "on the green."

D →
.6 R/S →

0.
5. *** Y_c Club yd.
−3. *** θ_c Club angle
−1.613743000−02 *** y
2.725378030−01 *** x } Ball location

In DSP 0 format, a number smaller than .5 is presented by the 67/97 in scientific notation. Look for these scientific notation numbers. They mean your hit has excellent directional accuracy, or (as here) you're very close to the hole, or you're very near the center of the fairway.

2.730151474−01 *** D_h Hole dist.
−87. *** ϕ_h Hole angle

D →
.1 R/S →

0.
0.000000000 *** Holed!
2. *** S Score

Because of bad luck, Ken is 2 over par, even including his 1 stroke/hole handicap.

A →

2. *** h Hole no.
130. *** Y_h Hole yd.
3. *** Par
33. *** W Woods dist.

A poor start, but perhaps if we stop looking over Ken's shoulder, he'll do better.

Example 2:

Two player game.

This match pits D.C. Divot against Janet Birdie, one of the leading lady golfers of our time. Janet carries a 0 handicap, while D.C. stumbles around the course under a 34. As you will see, however, D.C.'s spirit is as high as his handicap. He is a charger and a scrambler.

Load side 1 and side 2.

Keystrokes:		Outputs:	
f CL REG f P≷S f CL REG			
.385246 STO A	→	3.852460000–01	u_0 Seed
0 STO 7 f P≷S	→	0.	Janet's handicap
34 STO 7 f P≷S	→	34.	D.C.'s handicap
A	→	1. ***	h Hole no.
		571. ***	Y_h Hole yd.
		5. ***	Par
		24. ***	W Woods dist.
1 f SPACE PRINT X	→	1.	Janet's I.D. no.

This step is optional.

1 B	→	0.	
1 R/S	→	246. ***	Y_c Club yd.
		2. ***	θ_c Club angle
		−325. *** y	Ball location
		11. *** x	Ball location
		325. ***	D_h Hole dist.
		−2. ***	ϕ_h Hole angle

f P≷S			
2 f SPACE PRINT X	→	2.	D.C.'s I.D. no.
1 B	→	0.	
1 R/S	→	204. ***	Y_c Club yd.
		−8. ***	θ_c Club angle
		−369. *** y	Ball location
		−29. *** x	Ball location
		370.509734 ***	D_h Hole dist.
		4.455967 ***	ϕ_h Hole angle

f P≷S

Janet outdrove D.C. by 42 yards, and she has a good fairway lie compared to D.C.'s 5 yard penetration of the left woods.

1 f SPACE PRINT X	→	1.	Janet
1 B	→	0.	
1 R/S	→	276. ***	Y_c Club yd.
		1. ***	θ_c Club angle
		−49. *** y	Ball location
		9. *** x	Ball location
		50. ***	D_h Hole dist.
		−10. ***	ϕ_h Hole angle

f P≷S

2 f SPACE PRINT x → 2. D.C.

1 B → 0.

1 R/S → 25. *** Y_c Club yd.

−65. *** θ_c Club angle

−357. *** y } Ball location

−51. *** x }

360.811319 *** D_h Hole dist.

8.046678 *** ϕ_h Hole angle

f P≷S

Since D.C. could see the flag from his lie in the woods, he decided to make a try for it rather than take a penalty shot. The window out of the woods proved too narrow, however, and D.C.'s gutsy #1 wood shot hit many trees, and finally came to rest only 10 yards closer to the hole and 22 yards further into the woods.

1 f SPACE PRINT x → 1. Janet

10 C → 0.

.5 R/S → 48. *** Y_c Club yd.

1. *** θ_c Club angle

−1. *** y } Ball location

1. *** x }

2. *** D_h Hole dist.

−52. *** ϕ_h Hole angle

f P≷S

Janet now finds herself only 2 yards from the hole. An excellent approach shot from 50 yards out.

2 f SPACE PRINT x → 2. D.C.

1 B → 0.

1 R/S → 30. *** Y_c } Result of

−53. *** θ_c } Result of

−337. *** y } D.C.'s swing

−72. *** x } D.C.'s swing

344.037744 *** D_h } Hole location

12.002730 *** ϕ_h } Hole location from ball

f P≷S

D.C. gained another 16 yards on the hole, but he's now buried 48 yards into the woods.

1 f SPACE PRINT x →	1.	Janet
D →	0.	
.3 R/S →	3. *** Y_c	Result of Janet's swing
	−7. *** θ_c	
	1. *** y	
	−1. *** x	
	1. *** D_h	Hole location from ball
	114. *** ϕ_h	

f P≷S

Too bad, Janet missed a good birdie chance.

2 f SPACE PRINT x →	2.	D.C.
1 B →	0.	
1 R/S →	32. *** Y_c	
	100. *** θ_c	
	−348. *** y	
	−42. *** x	
	350.755487 *** D_h	
	6.898699 *** ϕ_h	

f P≷S

1 f SPACE PRINT x →	1.	Janet
D →	0.	
.2 R/S →	0.000000000 ***	
	0.	S

f P≷S

Janet made her par.

2 f SPACE PRINT x →	2.	D.C.
1 B →	0.	
1 R/S →	246. *** Y_c	
	−1.803671685−01 *** θ_c	
	−104. *** y	
	−13. *** x	
	105. *** D_h	
	7. *** ϕ_h	

The rewards of try, try again. D.C. found the window.

9 C →	0.	
1 R/S →	98.	*** Y_c
	1.	*** θ_c
	−7.	*** y
	1.	*** x
	7.	*** D_h
	−10.	*** ϕ_h

D.C. is on the green.

D →	0.	
.8 R/S →	8.	*** Y_c
	−12.	*** θ_c
	2.430006000−03	*** y
	−2.	*** x
	2.	*** D_h
	90.	*** ϕ_h
D →	0.	
.3 R/S →	0.000000000	***
	1.	S

f P≷S

D.C.'s struggles in the woods gave him an 8 on this hole, but considering his nearly 2 strokes/hole handicap, he stands only 1 over par, 1 stroke behind Janet. It looks like a close match.

A →	2.	*** h
	399.	*** Y_h } Hole no. 2
	4.	*** Par } layout
	22.	*** W

You might wish to continue to see who wins.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Notes

The Dealer





The Dealer is capable of drawing from a numerical deck or bin without replacement. That is, once a card or number has been selected, it will not be selected again until a shuffle is performed.

If the "Cards" mode is selected, numerical cards of 4 suits, containing 13 cards each, are dealt as follows:

S.	CC
Digit position	Exponent position

In this display format, S is the suit (digit from 1-4) and CC is the card of the indicated suit (digit from 1-13). The following convention is used for a standard deck of 52 cards:

Suit Convention	Card Convention
Spade = 1.	Ace = 01
Heart = 2.	2-10 = 02-10
Diamond = 3.	Jack = 11
Club = 4.	Queen = 12
	King = 13

The bingo mode simply selects numbers between 1. and 75. without replacement.

In both card mode and bingo mode, it is possible to draw one value at a time using A or many values automatically using C. To use the automatic feature, key in the number of values wanted before pressing C.

A shuffle may be performed at any time by pressing f C. An automatic shuffle is performed after all cards or numbers have been dealt.

The Dealer will start the same sequence of cards or numbers each time the card or bingo mode is selected unless the seed used to start the sequence is keyed in by the player(s). A seed is any number between 0 and 1. The seed must be keyed in after selecting card or bingo mode and R/S is used to store it. A fair way to select a seed in a multiplayer game is to have the dealer key a decimal point and the first digit and have each player key in a subsequent digit until the display is full. Press R/S to store the seed.

Remarks:

It is possible to modify the dealer to deal up to 100 numbers in bingo mode. Steps 109 and 110 control the number of objects dealt. If you wish to deal 85 numbers instead of 75 numbers replace the 23 (steps 109 and 110) with 33 (23 + (85 − 75)). Similarly a joker could be added to the card dealer by replacing the 51 at steps 112-113 with 52. The Joker would be displayed as the first card of the fifth suit.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	For bingo-type dealer (deals			
	numbers without repetition),			
	go to step 10.			
3	Select card dealer.		f A	0.
4	Optional: input seed			
	(0 < seed < 1).	seed	R/S	seed
5	Deal one card,		A	"suit. card"
	or deal a specified number			
	of cards.	n	C	"suit. card"
6	Optional: Review cards dealt.		E	"suit. card"
7	Go back to step 5 for more			
	cards or go to step 8 for shuffle.			
8	Shuffle.		f C	0. 00
9	Go to step 5 and deal cards.			
10	Select bingo dealer.		f E	0.
11	Optional: input seed			
	(0 < seed < 1).	seed	R/S	seed

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
12	Draw one number		A	"#."
	or draw a specified number			
	of numbers.	n	C	"#."
13	Optional: Review numbers			
	drawn.		E	"#."
14	Go back to step 12 for more			
	numbers or go to step 15 for			
	a new game.			
15	Shuffle.		f C	0.
16	Go to step 12 for more			
	numbers.			

Example 1:

Deal two poker hands of five cards. First use the program's seed, then use a seed of .896348.

Load sides 1 and 2.

Keystrokes:

f A →

5 C →

5 C →

Outputs:

0.

4. 04 *** (4C)
3. 02 *** (2D)
2. 01 *** (AH)
1. 02 *** (2S)
1. 10 *** (10S)
0. 00

3. 09 *** (9D)
3. 12 *** (QD)
4. 03 *** (3C)
3. 04 *** (4D)
3. 01 *** (AD)
0. 00

f A →	0. 00
.896348 R/S →	9. -01
5 C →	3. 08 ***
	4. 10 ***
	1. 10 ***
	1. 01 ***
	1. 06 ***
	0. 00
5 C →	1. 03 ***
	2. 11 ***
	2. 02 ***
	1. 11 ***
	2. 13 ***
	0. 00

Example 2:

Generate 10 bingo numbers, one at a time and then review the numbers automatically. Then shuffle, and deal 10 more numbers automatically.

Keystrokes:	**Outputs:**
f E →	0. 00
A →	62.
A →	41.
A →	20.
A →	3.
A →	14.
A →	52.
A →	57.
A →	64.
A →	45.
A →	74.
E →	62. ***
	41. ***
	20. ***
	3. ***
	14. ***
	52. ***

	57. ***
	64. ***
	45. ***
	74. ***
f C →	0.
10 C →	17. ***
	54. ***
	36. ***
	55. ***
	6. ***
	21. ***
	33. ***
	3. ***
	61. ***
	64. ***
	0.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Notes

Bowling Scorekeeper





This program keeps score for up to 10 bowlers. Each bowler is identified by a number (ID). Using his identification number, a player may input the pin count for each ball, and access his score.

To score a frame, key in the bowler's ID number, a decimal point, and a one digit pin count (P) for each ball. For instance, if bowler 6 knocked down three pins on the first ball and 5 pins on the second ball, the keystrokes would be as follows:

6.3 A
6.5 A.

A strike for player 3 (10 pins on the first ball) is indicated by:

3 C.

Similarly, if player 4 knocked down 9 pins on the first ball and then picked up the spare, the score would be indicated by:

4 B.

The score is displayed after each player's pin count is input. The format is shown below:

S.FS NF
or
−S.FS NF

where:

− (if present) = bowl another ball this frame.

S = Score calculated through frame FS.

FS = Frame number containing most recent score (frames scored).

NF = Frame in which next ball will be bowled (next frame).

By pressing DSP 6, the pin count (PC) for the last ball is displayed in the last 2 digits:

S.FS NF PC

A player's score may be displayed at any time by keying in the player's ID number and pressing D.

Remarks:

Players need not bowl in order. It is not necessary to complete a particular bowler's frame before input of another bowler's score. This allows two lanes to be scored simultaneously.

Other variables used in listing (pages L17-01, -02)

SSS = Score

CS = Current sum within a frame.

S1 = Strike one frame earlier.

S2 = Strike two frames earlier.


PS = Spare previous frame.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	Initialize.		f A	0.0000
3	Input each ball's score:			
	a) For frame's first ball (no			
	strike), key in player's ID			
	number, decimal point, and			
	single digit pin count.	ID.P	A	-S.FSNF*
	b) For frame's second ball			
	leaving open frame	ID.P	A	S.FSNF
	c) For spare	ID	B	S.FSNF
	d) For strike	ID	C	S.FSNF
4	For next ball or another			
	bowler, go to step 3.			
5	Display score (at any time).	ID	D	
6	Optional: Increase display to			
	show pin count of last ball.			
	Step 3 output will become			
	S.FSNFPC (PC = last ball pin			
	count).		DSP 6	

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
7	For a new game, go to step 2.			
	*S = Score			
	FS = Frame associated with			
	score			
	NF = Frame in which next			
	ball will be bowled			
	Minus sign means a second			
	ball should be bowled this			
	frame.			

Example:

Score the games below using the calculator.



Load sides 1 and 2.

Keystrokes: **Outputs:**

f A ——→ 0.0000

1.8 A ——→ –0.0001 ***

The minus sign means a second ball should be bowled this frame. There is no score, and the next ball will be bowled in frame 1.

1 B ——→ 0.0002 ***

Player 1's next ball will be in frame 2.

2.7 A ——→ –0.0001 ***

2.1 A ——→ 8.0102 ***

Player 2's score is 8 in frame 1, and his next ball will be bowled in frame 2.

1.7 A → −17.0102 ***

Player 1's score in frame 1 is 17, and he has another ball to bowl in frame 2.

1.2 A → 26.0203 ***

Since frame 2 is open, player 1's score (26) can be calculated up to the current frame (2). His next ball will be in frame 3.

2 C → 8.0103 ***
1 C → 26.0204 ***
2 C → 8.0104 ***
1 C → 26.0205 ***
2 C → 38.0205 ***

The strike in frame 2 can now be scored, since two more balls have been bowled.

1.8 A → −54.0305 ***
1.1 A → 82.0506 ***
2 C → 68.0306 ***
1 C → 82.0507 ***
2.9 A → −97.0406 ***
2 B → 117.0507 ***

Recall score of player 1.

1 D → 82.0507
1.8 A → −82.0507 ***
1 B → 102.0608 ***
2 C → 137.0608 ***
1 C → 122.0709 ***
2.6 A → −137.0608 ***
2.2 A → 163.0809 ***
1.7 A → −122.0709 ***
1.1 A → 148.0910 ***
2.8 A → −163.0809 ***
2 B → 163.0810 ***

The players would like to have each ball's pin count displayed:

DSP 6 → 163.081010

For a spare and a strike, the pin count is shown as 10.

1 C ⟶ 148.091110

Here, the "11" (xxx.xx11xx) means another ball should be bowled in the 10th frame.

1.8 A ⟶ −148.091108

Now a minus sign calls for the 3rd 10th frame ball.

1 B ⟶ 168.100000 ***

Player 1's final score

2.9 A ⟶ −182.091009 ***


2.0 A ⟶ 191.100000 ***

Player 2 wins easily.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Notes


Biorhythms



From the ancient of days, philosophers and sages have taught that human happiness lies in the harmonious integration of body, mind, and heart. Now a twentieth-century theory claims to be able to quantitatively gauge the functioning of these three aspects of ourselves: the physical, sensitive, and cognitive.

The biorhythm theory is based on the assumption that the human body has inner clocks or metabolic rhythms with constant cycle times. Currently, three cycles starting at birth in a positive direction are postulated. The 23-day or physical cycle relates with physical vitality, endurance and energy. The 28-day or sensitivity cycle relates with sensitivity, intuition and cheerfulness. The 33-day or cognitive cycle relates with mental alterness and judgement.

For each cycle a day is considered either high, low, or critical. The high ($0 < x \leq 1$) times are regarded as energetic times, you are your most dynamic in the cycle. The low ($-1 \leq x < 0$) times are regarded as the recuperative periods. The critical days ($x = 0$) are regarded as your accident prone days especially for the physical and sensitivity cycles.



Operating Limits and Warnings:

The birthdate and biodate must occur between January 1, 1901 and December 31, 2099.

The date format for input is MM.DDYYYY (March 3, 1976 is keyed in as 3.031976). The program does not check input data. Thus, if an improper format or an invalid date (e.g., February 30) is keyed in, erroneous answers will result.

Reference:

This program is based on an HP-65 Users' Library program by Grant Munsey.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
2	(Optional) To cancel PRINT/			
	PAUSE mode		f E	0*
	Later for automatic output of			
	results set PRINT/PAUSE			
	mode.		f E	1*
3	Key in the following:			
	Birthdate	MM.DDYYYY	A	
	Biodate	MM.DDYYYY	B	P**
				S**
				C**
4	To calculate the cycles for			
	Biodate + 1, 2, ...		C	P (day+1)
				S (day+1)
				C (day+1)
				P (day+2)
				S (day+2)
				C (day+2)
	To stop cycle		R/S	

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
5	To calculate which of the next			
	33 days after biodate are			
	critical days		E	# days P
				# days S
				# days C
6	To calculate which of the next			
	33 days after biodate are			
	max days		f D	# days P
				# days S
				# days C
7	To calculate which of the next			
	33 days after biodate are min			
	days		D	# days P
				# days S
				# days C
	*If you don't get the desired			
	output, press f E again.			
	**Physical, Sensitivity,			
	Cognitive			

Example:

Calculate the Bio values for the month of June 1976 if birthdate is June 7, 1948.

Load sides 1 and 2.

Keystrokes: **Outputs:**

6.071948 A ⟶ 6.07

By using May 31 for biodate (5.311976 B), instruction steps 5, 6 and 7 give correct day numbers for month of June.

5.311976 B ⟶ 0.82 *** P

0.00 *** S

−0.95 *** C

These are the values of the three cycles for May 31, 1976.

C →

0.63 *** P
0.22 *** S
-0.99 *** C
} June 1

0.40 *** P
0.43 *** S
-1.00 *** C
} June 2

0.14 *** P
0.62 *** S
-0.97 *** C
} June 3

-0.14 *** P
0.78 *** S
-0.91 *** C
} June 4

-0.40 *** P
0.90 *** S
-0.81 *** C
} June 5

-0.63 *** P
0.97 *** S
-0.69 *** C
} June 6

R/S → Ignore output

Listing stops.

f D →

20.75 *** P

7.00 *** S

18.25 *** C

The one maximum for the physical cycle during June (and the first 3 days of July) is June 20. Similarly, the sensitivity and cognitive cycles have one maximum each in this period, June 7 and June 18.

E →

3.50 ***
15.00 ***
26.50 ***
} P

14.00 ***
28.00 *** } S

10.00 ***
26.50 *** } C

There are 3 critical days in June for the physical cycle, June 3, 15, and 26. The other two cycles have 2 critical days each.

D ⟶

9.25 ***
32.25 *** } P

21.00 *** S


1.75 *** C

Only the physical cycle has more than one minimum day during this 33 day period.

***Shown by PRINT on HP-97 and by PAUSE on HP-67.


Notes

Timer



This program contains five different timers:

1. Five-second interval visible timer
2. Minimum interval visible timer
3. Count-Up timer
4. Count-Down timer
5. Splits



Calibration routines are also included to accomodate differences between calculators and different environments. The clock circuits in the HP-67 and HP-97 are designed for calculator use, not for accurate time keeping. Consequently, highly stable performance should not be expected.

In addition to the primary calibration constants whose adjustments are covered below, a secondary constant K_a, is also used for the 5 second timer. This determines how fast the calibration routine ''zeros in'' on the best value for the 5 second primary constant. K_a generally should require no user adjustment. These constants are named in Table I and are indicated in the listings.

TABLE I

CALIBRATION CONSTANTS

C_a	Primary for 5-Second Timer
C_b	Primary for Minimum Interval Timer
C_c	Primary for Count-Up Timer
C_d	Primary for Count-Down Timer
C_e	Primary for Splits Timer
K_a	Secondary for 5-Second Timer

A split is a time measurement which is preserved without stopping the clock. The split routine allows up to 16 splits to be taken during one continuous running of the count-up timer. If the count-up timer is properly calibrated, 10 splits taken over a few minutes should introduce no more than a few seconds error.

CALIBRATION ROUTINES

5-Second Timer

1. Initialize (A), and note sweep second hand time R/S is pressed.
2. When timer reaches chosen time T_p (program time), note sweep second hand finish time.

3. Stop timer (RTN), and enter sweep second hand finish time (H.MS ENTER↑).
4. Enter sweep second hand start time (H.MS ENTER↑).
5. Key in T_p and calculate new C_a (H.MS f A).
6. Enter the displayed C_a into program as follows:
 a. Press GTO .016.
 b. Switch to PRGM. Display should show 016 0X (X = last digit of old C_a).
 c. Remove old C_a by pressing DEL 6 times. Display should show 010 35 15 (HP-97) or 010 33 15 (HP-67).
 d. Key in new C_a. Display should show 016 0X (X = last digit of new C_a).
 e. Switch to RUN.
7. Repeat steps 1-2 to check calibration, and if necessary, repeat steps 3-7.

Minimum Interval Timer

1. Initialize (B), and note sweep second hand time R/S is pressed.
2. When timer reaches chosen time T_p (program time), note sweep second hand finish time and SIMULTANEOUSLY stop timer (RTN). Timer will not stop unless display is steady when RTN is pressed.
3. Enter sweep second hand finish time (H.MS ENTER↑).
4. Enter sweep second hand start time (H.MS ENTER↑).
5. Key in T_p and calculate new C_b (H.MS f B).
6. Enter the displayed C_b into program as follows:
 a. Press GTO .008.
 b. Switch to PRGM. Display should show 008 0X (X = last digit of old C_b).
 c. Remove old C_b by pressing DEL 4 times. Display should show 004 16–53 (HP-97) or 004 31 43 (HP-67).
 d. Key in integer portion (4 digits) of new C_b. Display should show 008 0X (X = last digit of new C_b).
 e. Switch to RUN.
7. Repeat steps 1-2 to check calibration, and if necessary, repeat steps 3-7.

Count-Up Timer

1. Initialize (C), and note sweep second hand time R/S is pressed.

2. When sweep second hand reaches desired finish time, stop timer by pressing any key until display stabilizes.
3. Enter sweep second hand finish time (H.MS ENTER↑).
4. Key in sweep second hand start time and display elapsed time T_p (program time) measured by count-up timer (H.MS f D).
5. Calculate new C_c (R/S).
6. Enter the displayed C_c into program as follows:
 a. Press GTO .027.
 b. Switch to PRGM. Display should show 027 0X (X = last digit of old C_c).
 c. Remove old C_c by pressing DEL 4 times. Display should show 023 35 13 (HP-97) or 023 33 13 (HP-67).
 d. Key in integer portion (4 digits) of new C_c. Display should now show 027 0X (X = last digit of new C_c).
 e. Switch to RUN.
7. Repeat steps 1-4 to check calibration, and if necessary, repeat steps 5-7.

Count-Down Timer

1. After initialization (D), enter start time, which equals elapsed time T_p (program time) as measured by timer (H.MS R/S).
2. Start timer, and note sweep second hand time R/S is pressed.
3. Note sweep second hand finish time the instant timer displays 0.0000.
4. Enter sweep second hand finish time (H.MS ENTER↑).
5. Key in sweep second hand start time and calculate new C_d (H.MS f E).
6. Enter displayed C_d into program as follows:
 a. Press GTO .033.
 b. Switch to PRGM. Display should show 033 0X (X = last digit of old C_d).
 c. Remove old C_d by pressing DEL 4 times. Display should show 029 35 14 (HP-97) or 029 33 14 (HP-67).
 d. Key in integer portion (4 digits) of new C_d. Display should now read 033 0X (X = last digit of new C_d).
 e. Switch to RUN.
7. Repeat steps 1-3 to check calibration, and if necessary, repeat steps 4-7.

Splits

1. The following procedure should be followed only after the count-up calibration constant has been adjusted to give acceptable timer performance.
2. Initialize (C), and note sweep second hand time R/S is pressed.
3. At chosen sweep second hand time intervals, take a series of from 10 to 16 splits (E E —see instruction steps 19 and 20).
4. When sweep second hand reaches desired finish time, stop timer by pressing any key until display stabilizes.
5. Display and note total elapsed time (f C).
6. Display and note splits (press R/S repeatedly).
7. Program steps 158, 159, 160 and 161 contain the split calibration constant, whose form is X.XX. If the split times are too small, this constant is too small, and visa versa. Key a new split constant into program memory and repeat steps 2-6. Increasing the split constant 0.10 will increase the displayed time after 16 splits roughly one second or so.

 Normally, several runs through this calibration procedure should allow you to "zero in" on a value for this constant which gives an accuracy over 16 splits of one or two seconds (plus whatever error might be introduced by the count-up timer itself over the total time interval measured).

After you have entered your new calibration constants into program memory, you may wish to record the timer program on a different card to preserve your new constants.

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Load side 1 and side 2.			
	For 5-second interval visible			
	timer:			
	Go to step 2.			
	For minimum interval			
	visible timer:			
	Go to step 6.			
	For count-up timer:			
	Go to step 10.			
	For count-down timer:			
	Go to step 14.			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
	For splits:			
	Go to step 17.			
	5-SECOND VISIBLE TIMER			
2	Initialize.		A	0.0000
3	If you want timer to start at a			
	time other than zero, key in			
	time.	H.MMSS		H.MMSS
4	Start 5-second timer.		R/S	H.MMSS
	Each PAUSE begins at the			
	time displayed.			
5	Stop 5-second timer. Press			
	RTN during time display.		RTN	H.MMSS
	MINIMUM INTERVAL VISIBLE			
	TIMER			
6	Initialize.		B	0.0000
7	If you want timer to start at a			
	time other than zero, key in			
	time.	H.MMSS		H.MMSS
8	Start minimum interval			
	timer.		R/S	H.MMSS
	Even when accurately cali-			
	brated, displayed time can			
	vary ±1 second from correct			
	time.			
9	Stop minimum interval timer.			
	Press RTN during time display.		RTN	H.MMSS
	COUNT-UP TIMER			
10	Initialize.		C	0.0000
11	Start count-up timer.		R/S	
12	Stop count-up timer: Depress			
	any key until display stabilizes.			

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
13	Display elapsed time.		f C	H.MMSS
	COUNT-DOWN TIMER			
14	Initialize.		D	0.0000
15	Enter starting time.	t_s H.MMSS	R/S	t_s H.MMSS
16	Start count-down timer.		R/S	
	When starting time interval			
	has elapsed, flashing display			
	is replaced by 0.0000.			
	SPLITS			
17	Initialize.		C	0.0000
18	Start count-up timer.		R/S	
19	Take a split: For HP-97, press			
	E twice, in rapid succession.			
	For HP-67, press E and hold			
	it down just long enough to			
	obtain a steady display. Then			
	press E again quickly.			
20	Take another split: Repeat			
	step 19. Up to 16 splits may			
	be taken. At least 4 seconds			
	must separate adjacent splits.			
21	Stop count-up timer:			
	Depress any key until display			
	stabilizes.			
22	Display total elapsed time.		f C	H.MMSS
23	Display last split.		R/S	H.MMSS
24	Display next-to-last split.		R/S	H.MMSS
25	Display each earlier split in			
	turn:			
	Repeatedly press		R/S	H.MMSS

Example 1:

Operate the 5-second interval visible timer.

Load side 1 and side 2.

Keystrokes:	**Outputs:**	
A →	0.0000	
R/S →	0.0000	
	0.0005	H.MS
	0.0010	
	0.0015	
	⋮	
	0.0055	
	0.0100	
RTN →	0.0100	

Example 2:

Calibrate the 5-second timer. (You'll probably generate a different calibration constant C_a with your calculator.)

Keystrokes:	**Outputs:**	
A →	0.0000	
R/S →	0.0000	
Start time t_s = 9:28:45.	0.0005	H.MS
	⋮	
	0.0155	
Finish time t_f = 9:30:48.	0.0200	
RTN →	0.0200	
9.3048 ENTER↑ 9.2845 ENTER↑		
.02 f A →	4.4347 ***	C_a
GTO .016		
Switch to PRGM. →	016 00	
DEL DEL DEL DEL DEL DEL →	010 35 15	(HP-97)
	010 33 15	(HP-67)
4.4347 →	016 07	
Switch to RUN. →	4.4347	
A →	0.0000	
R/S →	0.0000	

Start time t_s = 9:36:35. ⟶	0.0005	H.MS
	⋮	
	0.0155	
Finish time t_f = 9:38:34. ⟶	0.0200	
RTN ⟶	0.0200	

***Shown by PRINT on HP-97 and by PAUSE on HP-67.

Example 3:

Take 6 splits, 10 seconds apart, and stop the count-up timer at 70 seconds.

Keystrokes:	**Outputs:**	
C ⟶	0.0000	
Start count-up timer.		
R/S		
On 10 second mark: E E		
On 20 second mark: E E		
⋮		
On 60 second mark: E E		
On 70 second mark: f ⟶		Ignore display.
f C ⟶	0.0110	Elapsed time, H.MS
R/S ⟶	0.0100	Last split
R/S ⟶	0.0050	Previous split
⋮	⋮	
R/S ⟶	0.0010	First split
R/S ⟶	0.0000	

PROGRAM LISTINGS

The following listings are included for your reference. A table of keycodes and keystrokes corresponding to the symbols used in the listings can be found in Appendix E of your Owner's Handbook.

Program		Page
1.	Game of 21	L01-01
2.	Dice	L02-01
3.	Slot Machine	L03-01
4.	Submarine Hunt	L04-01
5.	Artillery Game	L05-01
6.	Space War	L06-01
7.	Super Bagels	L07-01
8.	Nim_k	L08-01
9.	Queen Board	L09-01
10.	Hexapawn	L10-01
11.	Tic-Tac-Toe	L11-01
12.	Wari	L12-01
13.	Racetrack	L13-01
14.	Teaser	L14-01
15.	Golf	L15-01
16.	The Dealer	L16-01
17.	Bowling Scorekeeper	L17-01
18.	Biorhythms	L18-01
19.	Timer	L19-01

Game of 21

001	*LBLA	
002	SFC	
003	SFC	
004	CF0	
005	CF1	
006	STOA	
007	1	
008	STOI	
009	GSB0	
010	STOB	
011	GSB5	
012	GSB9	
013	STO1	Bet,
014	STO3	
015	1	New game
016	STOI	
017	GSB0	
018	STOC	
019	GSB9	
020	STO2	
021	ST+3	
022	0	
023	GSB5	
024	SFC	
025	GSBe	
026	STO5	
027	STO7	
028	GSBe	
029	STO6	
030	ST+7	
031	RCL5	
032	×	
033	RCL7	
034	+	
035	2	
036	1	
037	STO0	
038	X=Y?	
039	GTO2	
040	RCL7	
041	GSB3	
042	R/S	----------
043	*LBLB	
044	GSBe	
045	ST+7	
046	RCL7	
047	RCL0	
048	X≠Y	Hit
049	X>Y?	
050	GTO4	
051	X≤Y?	
052	GSB3	
053	R/S	----------
054	*LBLD	
055	SF0	
056	1	
057	0	
058	ST+7	11 for Ace
059	RCL7	
060	GSB3	
061	RTN	----------
062	*LBLE	
063	CF0	
064	1	
065	0	
066	ST-7	1 for Ace
067	RCL7	
068	GSB3	
069	RTN	----------
070	*LBL4	
071	F0?	
072	GTOE	
073	RCLA	
074	CHS	
075	ST+9	player lose
076	RCL7	
077	EEX	
078	2	
079	÷	
080	-	
081	GTO6	----------
082	*LBL2	
083	RCL1	
084	RCL2	
085	×	
086	RCL3	HP BJ?
087	+	
088	RCL0	
089	X=Y?	
090	GTO7	
091	F1?	
092	RTN	----------
093	*LBL8	
094	.	
095	2	
096	1	
097	RCLA	player BJ!
098	1	
099	.	
100	5	
101	×	
102	STOA	
103	ST+9	
104	+	----------
105	*LBL6	
106	PSE	
107	PSE	
108	PSE	
109	PSE	Display with blinks.
110	RCL9	
111	DSP2	
112	F1?	

REGISTERS

0 21	1 1st D.	2 2nd D.	3 ΣD.	4	5 1st P.	6 2nd P.	7 ΣP.	8	9 Σ Bet
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A Bet	B 1st D.	C 2nd D.	D last K_i	E u_i	I Index				

```
113   R/S
114   RTN
115  *LBL7
116   F1?
117   GTO4
118     0
119   DSP9
120   GTO6
121  *LBL9
122     1
123     0
124   X=Y
125   X≤Y?
126   RTN
127   X=Y
128   RTN
129  *LBL3
130   EEX
131     2
132     ÷
133   RCLA
134     +
135   RTN
136  *LBL5
137   DSP0
138   FRTX
139   DSP2
140   RTN
141  *LBLa
142     0
143   STOI
144     .
145     5
146     2
147     8
148     1
149     1
150     6
151     3
152   STOE
153  *LBL0
154   RCLE
155     9
156     9
157     7
158     ×
159   FRC
160   STOE
161     1
162     3
163     ×
164   INT
165     1
166     +
167   STOD
168   DSZI
```

HP BJ!

10 for J, Q, K

Display

Bet.point

print

Shuffle

```
169   GTO0
170   RTN
171  *LBLC
172   CF0
173   SPC
174   RCLB
175   GSB5
176   RCLC
177   GSB5
178   SF1
179   GSB2
180   CF1
181   RCL3
182  *LBL6
183     1
184     7
185   X≤Y?
186   GTOd
187   GSBe
188   ST+3
189   RCL3
190     2
191     2
192   X≤Y?
193   GTO1
194   RCL3
195   GTO6
196  *LBLd
197   RCL7
198   RCL3
199     -
200   X=0?
201   GTO6
202   X<0?
203   GTO4
204  *LBL1
205   RCLA
206   ST+9
207   RCL7
208   GSB3
209   GTO6
210  *LBLe
211     1
212   STOI
213   GSB0
214   GSB5
215   GSB9
216   RTN
217  *LBLc
218     0
219   STO9
220   RTN
```

Stand and

HP takes cards.

Next card

New player

LABELS					FLAGS	SET STATUS		
[A] Bet	[B] Hit	[C] Stand	[D] 11 for Ace	[E] 1 for Ace	[0] 11 for Ace	FLAGS ON OFF	TRIG	DISP
[a] Shuffle	[b] Dealer	[c] New P.	[d] Used	[e] Next card	[1] HP BJ	0 ☐ ☒	DEG ☒	FIX ☒
[0] R. No.	[1] P. Win	[2] HP BJ?	[3] Display	[4] P. lose	[2]	1 ☐ ☒	GRAD ☐	SCI ☐
[5] Print	[6] blinks	[7] HP BJ!	[8] P. BJ!	[9] 10 for J,Q,K	[3]	2 ☐ ☒	RAD ☐	ENG ☐
						3 ☐ ☒		n 2

Dice


001	*LBLA	Input seed.
002	EEX	
003	CHS	
004	7	
005	X	
006	.	
007	5	
008	2	
009	8	
010	4	
011	1	
012	6	
013	+	
014	STO9	Store in R_9.
015	*LBLC	Reset Winnings (WIN) to 0.
016	0	
017	STO8	
018	*LBL1	Display Winnings (WIN).
019	DSP2	
020	FIX	
021	SF2	Set 1st Roll Flag.
022	RTN	
023	*LBLB	Store Bet in R_7.
024	STO7	
025	*LBL2	Get Dice Roll.
026	GSB0	
027	FSE	1st Roll?
028	F29	
029	GTO4	Yes.
030	GTO5	No.
031	*LBLD	Dice Roll Routine
032	GSB3	1st die (1 DIE).
033	STO6	Sum of 2 dice (2 DIE).
034	STO5	
035	GSB3	
036	ST+5	
037	1	
038	0	
039	÷	
040	RCL6	
041	+	
042	RCL5	
043	10^x	
044	X	
045	DSP1	
046	SCI	
047	RTN	
048	*LBL3	Random Number Generator.
049	3	
050	RCL9	
051	9	
052	9	
053	7	
054	X	
055	FRC	
056	STO9	

057	6	
058	X	
059	1	
060	+	
061	INT	
062	RTN	
063	*LBL4	1st Roll Routine
064	3	Lose on 2, 3, 12.
065	RCL5	
066	X=Y?	
067	GTO7	
068	2	
069	X=Y?	
070	GTO7	
071	R↓	
072	1	
073	2	
074	X=Y?	
075	GTO7	
076	R↓	Win 7, 11.
077	7	
078	X=Y?	
079	GTO6	
080	R↓	
081	1	
082	1	
083	X=Y?	
084	GTO6	
085	R↓	Current Roll (C ROLL).
086	STO4	
087	GTO2	Not 1st Roll.
088	*LBL5	
089	RCL5	Craps?
090	7	
091	X=Y?	
092	GTO7	YES
093	R↓	
094	RCL4	
095	X≠Y?	Match
096	GTO2	No
097	*LBL6	Win!
098	RCL7	
099	RCL8	Increment Winnings (WIN).
100	+	
101	STO8	
102	GTO1	
103	*LBL7	Lose!
104	RCL8	
105	RCL7	
106	-	Decrement Winnings (WIN).
107	STO8	
108	GTO1	

REGISTERS

0	1	2	3	4 C ROLL	5 2 DIE	6 1 DIE	7 BET	8 WIN	9 SEED
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I



LABELS					FLAGS
A SEED	B BET	C RESET	D ROLL	E	0
a	b	c	d	e	1
0	1 DISPLAY	2 GET DIE	3 RANDOM	4 1 ROLL	2 1ST ROLL
5 ≠ 1 ROLL	6 WIN	7 LOSE	8	9	3

SET STATUS		
FLAGS	TRIG	DISP
ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☒ ☐ 3 ☒ ☐	DEG ☒ GRAD ☐ RAD ☐	FIX ☐ SCI ☒ ENG ☐ n ____

Slot Machine

```
001  *LBLB
002   DSP2
003   RCL0
004    RTN
005  *LBLE
006   CLRG
007   STOE
008    CLX
009   DSP0
010    RTN
011  *LBLA
012   DSP3
013      1
014   ST-0
015   RCLE
016    EEX
017      3
018    ×
019    COS
020    ABS
021   STOE
022    EEX
023      6
024    +
025   LSTX
026    -
027    FRC
028   STO4
029      1
030      0
031   STO5
032    ×
033    INT
034   STO1
035    CHS
036   LSTX
037    +
038   RCL5
039    ×
040    INT
041   STO2
042    CHS
043   LSTX
044    +
045   RCL5
046    ×
047    INT
048   STO3
049      1
050   RCL1
051   X=Y?
052   GTO1
053   RCL2
054   X≠Y?
055   GTO9
056   RCL3
057   X≠0?
058   GTO2
059      1
060      0
061   ST+0
062   RCL2
063   X≠0?
064   GTO9
065      9
066      0
067   GTO8
068  *LBL2
069   RCL2
070   RCL3
071   X≠Y?
072   GTO9
073      1
074      0
075   GTO8
076  *LBL1
077      2
078   ST+0
079      1
080      0
081   RCL2
082   X≠Y?
083   GTO9
084      3
085  *LBL8
086   ST+0
087  *LBL9
088   RCL1
089      1
090      0
091    ÷
092   DSP1
093    PSE
094   RCL2
095      1
096      0
097      0
098    ÷
099    +
100   DSP2
101    PSE
102   RCL3
103    EEX
104      3
105    ÷
106    +
107   DSP3
108    RTN
```

Recalls winnings

Sets up new machine conditions.

Play:
Removes dollar played from winnings.

Sets up wheels.

Determine winnings.

Adds $10 for XX0.

Adds additional $90 for 000.

Adds $10 for XXX,


Adds $2 for 1XY.

Adds additional $3 for 11X.

REGISTERS

0	1	2	3	4	5	6	7	8	9
Winnings	Wheel 1	Wheel 2	Wheel 3	Comb.	10				
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I



LABELS					FLAGS
A Play	B Winnings	C	D	E Set up	0
a	b	c	d	e	1
0	1 Cherry loop	2 Used	3	4	2
5	6	7	8 Adds	9 End of play	3

SET STATUS			
FLAGS		TRIG	DISP
	ON OFF		
0	☐ ☒	DEG ☒	FIX ☒
1	☐ ☒	GRAD ☐	SCI ☐
2	☐ ☒	RAD ☐	ENG ☐
3	☒ ☐		n 3

Submarine Hunt

```
001  *LBLC
002     1
003   STOC
004    SF8
005   RTN
006  *LBLD
007   RCLD
008     1
009   X=Y?
010     +
011   STOD
012   RTN
013  *LBLE
014   CLRG
015    CF8
016     .
017     5
018     2
019     8
020     4
021     1
022     6
023     X
024   STO8
025   GSBd
026   STO1
027   GSBd
028   STO2
029   DSP0
030     1
031   STOD
032    CLX
033   RTN
034  *LBLA
035     1
036   ST+7
037    R↓
038    SF1
039   GSBc
040   X≠0?
041   GTO8
042     1
043   STO5
044   GSBa
045   RTN
046  *LBL8
047     9
048    1/X
049   DSP3
050    PSE
051   DSP5
052    PSE
053   DSP7
054    PSE
055   DSP9
056    PSE
```

Sets movement flag. 1 unit after sonar.

Sensitivity toggle switch 1.9→2.9→1.9 etc.

Start

Determine initial position using input seed.

Fire Depth Charge

Move Submarine

Display Hit!

```
057   RTN
058  *LBLB
059     1
060   ST+8
061    R↓
062   DSP0
063    CF1
064   GSBc
065   RCLC
066   STO5
067    F8?
068   GSBa
069   RCL3
070   RTN
071  *LBLa
072   GSBd
073     4
074   X≠Y
075   X>Y?
076   GTO8
077   RCL5
078   CHS
079   GTO1
080  *LBL8
081   RCL5
082  *LBL1
083   STO6
084   GSBd
085     5
086   X>Y?
087   GTO8
088    SF2
089   RCL1
090   GTO1
091  *LBL8
092   RCL2
093  *LBL1
094   RCL6
095     +
096   X<0?
097   GTO8
098     9
099   X≠Y
100   X≤Y?
101   GTO1
102  *LBL8
103   RCL6
104     2
105     x
106     -
107  *LBL1
108    F2?
109   GTO8
110   STO2
111   GTO1
112  *LBL8
```

Sonar Reading

Submarine Move Routine

REGISTERS

0 Seed	1 P_1	2 P_2	3 Response	4 d	5 Used	6 Used	7 Used	8 Used	9
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
		0, 1	1 or 2		

```
113   STO1
114  *LBL1
115    RCL3
116    DSP0
117     RTN
118  *LBLc
119    RCL2
120     -
121     X≠Y
122    RCL1
123     -
124     →P
125    STO4
126     F1?
127    GTO8
128    RCLD
129     -
130  *LBL0
131     .
132     9
133     -
134    X<0?
135    GTO0
136     0
137    GTO1
138  *LBL8
139     1
140  *LBL1
141    STO3
142     RTN
143  *LBLd
144    RCL0
145     9
146     9
147     7
148     ×
149     FRC
150    STO0
151     1
152     0
153     ×
154     INT
155     RTN
156  *LBLe
157    DSP2
158    RCL7
159    RCL8
160     1
161     0
162     0
163     ÷
164     +
165     RTN
```

Determine Response and Calculate Distance.

Random Number Generator

Check Status

LABELS					FLAGS	SET STATUS		
A Depth charge	B Sonar	C Option	D Dist	E Start	0 Motion?	FLAGS	TRIG	DISP
a Move sub	b	c d	d random ≠	e	1 Depth charge	ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☑ GRAD ☐ RAD ☐	FIX ☒ SCI ☐ ENG ☐ n 2
0	1	2	3	4	2 P_1?			
5	6	7	8	9	3			

Artillery

001	*LBLa	INITIALIZATION	057	EEX	
002	FIX		058	4	
003	DSP2		059	÷	
004	.		060	X≠Y	
005	5		061	X>0?	
006	2		062	GTO2	
007	8		063	3	
008	4		064	6	
009	1		065	0	
010	6		066	+	
011	3		067	*LBL2	
012	STO0	R_0←seed = .5284163	068	DSP0	
013	3		069	RND	
014	STOC	R_C←spot rating = 3	070	+	
015	5		071	DSP4	Display brg. range.
016	0		072	RTN	
017	0		073	*LBLb	- - - - - - - - - - -
018	STOB	R_B←speed = 500	074	STOB	Set new SPEED.
019	EEX		075	RTN	
020	2		076	*LBLc	- - - - - - - - - - -
021	STOD	R_D←kill range = 100	077	STOC	Set new spotter rating.
022	X²		078	RTN	
023	STO9	Max. gun range = 10000	079	*LBLd	- - - - - - - - - - -
024	RTN		080	STOD	Set new KILL range.
025	*LBLA	- - - - - - - - - - -	081	RTN	
026	SPC	START NEW BATTLE	082	*LBL1	- - - - - - - - - - -
027	0		083	CF0	Routine to calc. move-
028	STOI	Rounds = 0	084	X<0?	ment of target in N–S and
029	RCL9		085	SF0	E–W directions.
030	2		086	RCLB	
031	÷		087	GSB0	
032	ENT↑		088	F0?	
033	GSB0		089	CHS	
034	+	Generate target range.	090	-	
035	3		091	RTN	
036	6		092	*LBLe	- - - - - - - - - - -
037	0		093	*LBLE	FIRE! Routine - - -
038	GSB0		094	ISZI	
039	STO8	Generate target bearing.	095	X≠Y	
040	R↑		096	DSP7	
041	→R		097	PRTX	Output bearing.
042	STO1	Save target N–S.	098	X≠Y	
043	X≠Y		099	DSP1	
044	STO2	Save target E–W.	100	PRTX	Output elevation.
045	4		101	ENT↑	
046	5		102	+	
047	ST÷8		103	SIN	
048	RCL8		104	RCL9	
049	DSP0	Display target 45° sector.	105	×	
050	RND		106	→R	
051	X-		107	STO3	Save round's N–S.
052	RTN		108	X≠Y	
053	*LBLC	- - - - - - - - - - -	109	STO4	Save round's E–W.
054	RCL2	Routine to generate and	110	RCL1	
055	RCL1	display target's last position.	111	GSB1	
056	→P		112	STO1	Move target N–S.

REGISTERS

0 Seed	1 Targ N–S	2 Targ E–W	3 Shell N–S	4 Shell E–W	5	6	7 Used	8 Used	9 Gun Range
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B SPEED	C Spot Rating	D KILL Range	E	I Rounds Fired

```
113  RCL2
114  GSB1
115  STO2          Move target E-W.
116  CHS
117  RCL4
118  +
119  RCL3          Generate "miss" data.
120  RCL1
121  -
122  →P
123  STO7          R7←miss
124  RCL0
125  X≷Y           Test if round hit within
126  X>Y?          KILL range.
127  GTO7
128  RCLC
129  RCLB
130  R↓
131  R↓
132  PRST          WIN! Print stack.
133  R/S
134  *LBL7
135  R↓
136  R↓
137  RCL2          Otherwise, test if target has
138  RCL1          closed within 500 meters.
139  →P
140  5
141  0
142  0
143  *LBL8         LOSE! So flash "500.0"
144  PSE           repeatedly.
145  X>Y?
146  GTO8
147  R↓
148  R↓            If no decision, generate
149  -             spotter's estimate of hour
150  3             angle to shell hit.
151  0
152  ÷
153  4
154  RCLC
155  -
156  GSB9
157  *LBL5
158  X<0?
159  GTO6
160  DSP0
161  RND
162  STO8          R8←hour angle.
163  RCL7
164  .
165  2             Generate up to 20% range
166  ENT↑          error for each level of
167  4             spotter incompetence.
168  RCLC
169  -
170  X
171  X
172  X=0?
173  GTO3
174  GSB9
175  RCL0
176  *LBL3
177  X≤Y?
178  X≷Y
179  RCL9
180  ÷
181  DSP3
182  RND
183  RCL8
184  +
185  DSP4          Display and print
186  PRTX          hh.DDDD feedback to
187  RTN           gunner.
188  *LBL6
189  1             Patch to bring hour angle
190  2             within clock numbers.
191  +
192  GTO5
193  *LBL9
194  -             Routine to generate
195  LSTX          spotter's estimate of
196  ENT↑          "miss" data.
197  +
198  GSB0
199  +
200  RTN
201  *LBL0         Random number
202  RCL0          generator.
203  9
204  9
205  7
206  X
207  FRC
208  STO0
209  X
210  RTN
```

LABELS					FLAGS	SET STATUS		
A START	B	C →TARGET	D	E FIRE!	0 Switch	FLAGS	TRIG	DISP
a INIT.	b New speed	c New spot	d New kill	e FIRE!	1	ON OFF 0 ☐ ☒ 1 ☐ ☒	DEG ☒ GRAD ☐	FIX ☒ SCI ☐
0 Ran. Gen.	1 ΔTarget	2 Tgt brg.rng	3 Used	4	2	2 ☐ ☒ 3 ☐ ☒	RAD ☐	ENG ☐ n 4
5 Used	6 Patch	7 Tests	8 LOSS!	9 Err. Gen.	3			

Space War

```
001  *LBLA
002   CLRG
003   X=0?
004    Pi
005   STO9
006     1
007     0
008   STO4
009     2
010     0
011   STOI
012  *LBL9
013   GSB1
014   GSB8
015    F2?
016   GTO9
017   STOi
018   ISZI
019   RCLI
020     2
021     5
022   X≠Y?
023   GTO9
024    EEX
025     3
026   STO6
027     3
028   STO7
029   STO9
030     1
031     8
032   STO8
033   RCLE
034    RTN
035  *LBL1
036   RCL9
037     9
038     9
039     7
040     x
041    FRC
042   STO9
043    EEX
044     4
045     x
046    INT
047   GSB5
048   GSB5
049    RTN
050  *LBL8
051   RCLA
052   X=Y?
053    SF2
054    CLX
055   RCLE
056   X=Y?
```

Initialize.
If seed = 0, use π.

Point to R_A and prepare to compute random starting positions.

Compute a position. Check not occupied.

Store position.

Exit loop after filling R_E.

Energy = 1000.

Torpedoes = 3.

Days = 18
Display position of Kittyhawk.

Generate one starting position of the form QQ.SS, where QQ is quadrant, SS is sector.

Routine tests to see if position in X-register is already occupied.

```
057    SF2
058    CLX
059   RCLC
060   X=Y?
061    SF2
062    CLX
063   RCLD
064   X=Y?
065    SF2
066     R↓
067    RTN
068  *LBLC
069     4
070    FIX
071     9
072     9
073     9
074     ÷
075   STO2
076   DSP8
077    SPC
078   RCLE
079    INT
080   STO0
081   RCL4
082     +
083   GSB3
084   RCL0
085   GSB3
086   RCL0
087   RCL4
088     -
089   GSB3
090    RTN
091  *LBL3
092   RCL2
093   STO1
094     R↓
095   STO3
096   ST+1
097     1
098     -
099   GSB0
100   GSB5
101   GSB5
102   ST+1
103   RCL3
104   GSB0
105    EEX
106     5
107     ÷
108   ST+1
109   RCL3
110     1
111     +
112   GSB0
```

Set flag 2 if position occupied.

Long Scan.

Store constant 0.00400400

Scan line above KH.

Scan line with KH.

Scan line below KH.

Routine scans one line, i.e., 3 quadrants.

$R_I \leftarrow$QQ.00400400, where QQ refers to middle quadrant.

First quadrant.

Middle quadrant.

REGISTERS

0	1	2	3	4	5	6	7	8	9
Used	Used	Used	Used	10	Used	Energy	Torpedoes	Days	Alglogs
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
Alglog 1	Alglog 2	Alglog 3	Base	Kittyhawk	Pointer

113	EEX	
114	8	Last quadrant.
115	÷	
116	ST+1	
117	RCL1	
118	PRTX	Print line.
119	RTN	
120	*LBL0	Routine checks one quadrant for presence of Alglogs or Base.
121	0	
122	STO5	
123	R↓	
124	RCLA	
125	INT	Forms a two-digit number AB, where A is no. of Alglogs, B no. of Bases in quadrant.
126	X=Y?	
127	GSB1	
128	CLX	
129	RCLB	
130	INT	
131	X=Y?	
132	GSB1	
133	CLX	
134	RCLC	
135	INT	
136	X=Y?	
137	GSB1	
138	CLX	
139	RCLD	
140	INT	
141	X=Y?	
142	GSB2	
143	RCL5	
144	RTN	
145	*LBL1	Alglog detected—add 10 to R_5.
146	RCL4	
147	ST+5	
148	RTN	
149	*LBL2	Base found—add 1 to R_5.
150	1	
151	ST+5	
152	RTN	
153	*LBLE	Move. Convert (r, θ) to $(\Delta x, \Delta y)$.
154	→R	
155	FIX	
156	DSP1	
157	RND	
158	STO0	$\Delta Q_x.\Delta S_x$
159	X≠Y	
160	RND	$\Delta Q_y.\Delta S_y$
161	DSP2	
162	RCLE	
163	GSB5	
164	STO3	
165	INT	
166	RCLE	
167	GSB4	
168	STO2	
169	INT	
170	GSB5	
171	FRC	
172	+	$Q_y.S_y$
173	+	$(Q_y + \Delta Q_y).(S_y + \Delta S_y)$
174	FRC	
175	LSTX	
176	INT	
177	GSB4	
178	+	$Q_y\ O.S_y$ (new Y-position)
179	RCL2	
180	FRC	
181	RCL3	
182	FRC	
183	GSB4	
184	INT	
185	+	$Q_x.S_x$
186	RCL0	
187	+	$(Q_x + \Delta Q_x).(S_x + \Delta S_x)$
188	INT	
189	LSTX	
190	FRC	
191	GSB5	
192	+	$Q_x.OS_x$
193	*LBL7	$Q_yQ_x.S_yS_x$ (QQ.SS) Test not occupied.
194	+	
195	GSB8	
196	F2?	
197	GTO0	
198	STOE	
199	1	
200	ST-8	Decrement no. days remaining.
201	RCL8	
202	X<0?	If negative, game over.
203	GTO6	Otherwise display new
204	RCLE	position.
205	RTN	
206	*LBL6	Ran out of days—flash
207	CLX	zeros.
208	PSE	
209	GTO6	
210	*LBL4	
211	RCL4	Multiply by 10.
212	x	
213	RTN	
214	*LBL5	
215	RCL4	
216	÷	Divide by 10.
217	RTN	
218	*LBL0	
219	.	Position occupied—add
220	1	0.1 and try again.
221	GTO7	
222	*LBLa	
223	RCL8	Display remaining days.
224	RTN	

LABELS

A Start	B	C Long Scan	D	E Move	0
a →Days	b	c	d	e	1
0 Used	1 Used	2 Used	3 Scan line	4 10x	2 Occupied
5 10÷	6 Flash zeros	7 Exit move	8 Occupied?	9 Start loop	3

FLAGS

SET STATUS

FLAGS	ON	OFF
0	☐	☒
1	☐	☒
2	☐	☒
3	☐	☒

TRIG	
DEG	☒
GRAD	☐
RAD	☐

DISP	
FIX	☒
SCI	☐
ENG	☐
n	2

L06-03

```
001 *LBLA
002   FIX
003   DSP9
004   SPC
005   P≠S
006     9
007   STOI
008     0
009 *LBL9
010   STOi
011   DSZI
012   GTO9
013   STO0
014     3
015   RCLE
016   GSB0
017     4
018   RCLA
019   GSB0
020     4
021   RCLB
022   GSB0
023     4
024   RCLC
025   GSB0
026     7
027   RCLD
028   GSB0
029     9
030   STOI
031 *LBL8
032   RCLi
033   PRTX
034   DSZI
035   GTO8
036   RCL0
037   PRTX
038   P≠S
039   RTN
040 *LBL0
041   ENT↑
042   INT
043   RCLE
044   INT
045   X≠Y?
046   RTN
047   R↓
048   R↓
049   FRC
050   GSB5
051   INT
052   STOI
053   CLX
054   LSTX
055   FRC
056   GSB5
```

Short Scan.

A "3" marks KH,
"4" marks Alglog,
"7" marks Base.

Clear $R_{s0} - R_{s9}$ to hold scans of rows 0 thru 9, respectively.

Locate KH in quadrant.

Check Alglog 1.

Check Alglog 2.

Check Alglog 3.

Check for Base.

Print R_{s9}, R_{s8}, ..., R_{s0} as rows 9, 8, ..., 0.

Routine tests whether an object is in KH's quadrant.

If not, return.

If so, locate 3, 4, or 7 in proper sector of proper row, represented by R_{s0}–R_{s9}.

```
057   CHS
058   10^x
059   X
060   ST+i
061   RTN
062 *LBLC
063   CF0
064   STO0
065   RCL7
066     1
067   X>Y?
068   GTOB
069     -
070   STO7
071     1
072     9
073   STOI
074   GSB1
075   GSB1
076   GSB1
077   RCL9
078   CF0
079   RTN
080 *LBL1
081   ISZI
082   F0?
083   RTN
084   RCLi
085   INT
086   RCLE
087   INT
088   X≠Y?
089   RTN
090   GSB7
091   CLX
092   RCL0
093     -
094   ABS
095     1
096   X≤Y?
097   RTN
098     1
099   CHS
100   STOi
101   SF0
102     1
103   ST-9
104   RTN
105 *LBL7
106   RCLi
107   FRC
108   GSB5
109   STO1
110   INT
111   RCLE
112   FRC
```

3, 4, or 7 times $10^{(-S_x)}$ Add to register S_y.

Torpedo.

Save angle.

If no torpedoes remain, display "Error". Otherwise subtract one from no. torpedoes.

Check if Alglogs 1, 2, and 3 are in the path of the torpedo.
Display no. Alglogs left.

Routine tests if Alglog will be hit by torpedo.
If F0 set, an Alglog has been hit—return.
If Alglog not in same quadrant as KH, return.

Find angle to Alglog.

Compare to angle of fire.

If Alglog 1° or more away, no hit.

If hit, store –1 as Alglog's position.

F0 set to indicate torpedo is spent.
Decrement no. Alglogs.

Routine finds angle and distance from KH to Alglog.

REGISTERS

0 Used	1 Used	2	3	4 10	5	6 Energy	7 Torpedos	8 Days	9 Alglogs
S0 Row 0	S1 Row 1	S2 Row 2	S3 Row 3	S4 Row 4	S5 Row 5	S6 Row 6	S7 Row 7	S8 Row 8	S9 Row 9

A Alglog 1	B Alglog 2	C Alglog 3	D Base	E Kittyhawk	I Pointer

```
117  GSB5
114   INT
115    -
116  RCL1
117   FRC
118  RCLE
119  GSB5
120   FRC
121    -
122  GSB5
123    →P          Return r in X, θ in Y.
124   RTN          ------------
125  *LBL0         Phaser.
126   STO0         Save energy and subtract
127   ST-6         from total.
128     1
129     9
130   STOI
131   GSB4         Check if Alglogs 1, 2, and
132   GSB4         3 are in range.
133   GSB4
134   RCL9         Display no. Alglogs left.
135   RTN          ------------
136  *LBL4         Test if Alglog hit by phaser.
137   RCL6
138   X<0?         If energy < 0, exit.
139   GTO6
140   ISZI
141   RCL i
142    INT         If Alglog not in KH's
143   RCLE         quadrant, return.
144    INT
145   X≠Y?
146    RTN
147    EEX         Deduct 100 for shields.
148      2
149   ST-6
150   GSB7         Find distance r to Alglog.
151     X²
152    EEX         Energy input must be
153      2         greater than r² + 100.
154     +
155   RCL0
156   X≤Y?
157    RTN
158     1          If hit, store -1 as Alglog's
159    CHS         position.
160   STOi
161     1
162   ST-9         Decrement no. Alglogs.
163    RTN
164  *LBL6         ------------
165    CLX         Out of energy—flash zeros.
166    PSE
167   GTO6         ------------
168  *LBLE         Dock.
```

```
169   RCLD
170    INT         If Base and KH not in
171   RCLE         same quadrant, display
172    INT         same En.Torp.
173   X≠Y?
174   GTOa
175   RCLD
176    FRC
177   GSB5
178   STO0
179    INT
180   RCLE
181    FRC
182   GSB5
183   STO1
184    INT
185     -           KH must be within 1
186    ABS          sector of Base in
187      2          Y-direction.
188   X≤Y?
189   GTOa
190   RCL0
191    FRC
192   GSB5
193   RCL1
194    FRC
195   GSB5
196     -
197    ABS          Also must be within
198      2          1 sector of Base in
199   X≤Y?          X-direction.
200   GTOa
201    EEX          If successful, get 1000
202      3          units energy and 3
203   STO6          torpedoes.
204      3
205   STO7
206   GTO0
207  *LBLa          ------------
208   RCL6          If failed, display old
209   RCL7          energy and torpedoes.
210  *LBL0          ------------
211     1
212     0           Form display
213     ÷           Energy.Torpedoes.
214    X≷Y
215    INT
216     +
217    FIX
218   DSP1
219    RTN
220  *LBL5          ------------
221     1           Multiply by 10.
222     0
223     x
224    RTN
```

LABELS					FLAGS	SET STATUS		
A Short scan	B	C Torpedo	D Phaser	E Dock	0 Torpedo	FLAGS (ON / OFF)	TRIG	DISP
a →En.torp	b	c	d	e	1	0 ☐ ☒	DEG ☒	FIX ☒
0 Used	1 Torp hit?	2	3	4 Phaser hit?	2	1 ☐ ☒	GRAD ☐	SCI ☐
5 10x	6 Flash zeros	7 KH to Alglog	8 Print reg.	9 Clear reg.	3	2 ☐ ☒	RAD ☐	ENG ☐
						3 ☐ ☒		n 2

Super Bagels

```
001 *LBLB
002   INT
003   X=0?
004   GTO6
005     8
006   X≠Y
007   X>Y?
008   GTO6
009   RCLB
010   FRC
011   +
012   GTO0
013 *LBLC
014   INT
015     9
016   X≠Y
017   X>Y?
018   GTO6
019   RCLA
020   ÷
021   RCLB
022   INT
023   +
024   GTO0
025 *LBLD
026   RCLC
027   RTN
028 *LBLA
029   SPC
030   CF0
031   CLRG
032   X=0?
033   Pi
034   STOE
035     1
036     0
037   STOA
038     4
039     .
040     5
041 *LBL0
042   STOB
043   FIX
044   DSP1
045   RTN
046 *LBLE
047   CF2
048   F0?
049   GTOa
050   ENT↑
051   SF0
052   RCLE
053   RCLB
054   x
055   x
056   X=0?
057   LSTX
058   LN
059   EEX
060     7
061   x
062   ABS
063   D+R
064   1/X
065   STOE
066   R↓
067 *LBLa
068   INT
069   STOD
070   RCLE
071   1/X
072   R↑D
073   SF1
074   GSB1
075   CLX
076   STO9
077   STO0
078   P≠S
079   RCLD
080   CF1
081   GSB1
082   RCLB
083   STOI
084 *LBL3
085   RCLi
086   P≠S
087   RCLi
088   X≠Y?
089   GTO0
090   CHS
091   X≠Y
092   CHS
093   X≠Y
094   RCLA
095   ST+9
096   R↓
097 *LBL0
098   STOi
099   X≠Y
100   P≠S
101   STOi
102   DSZI
103   GTO3
104   RCLB
105   STOE
106 *LBL9
107   RCL0
108   STOI
109   RCLi
110   P≠S
111   X<0?
112   GTO5
```

Number of digits.

Maximum digit.

Number of guesses.

Input seed.

Input guess.

Compare for equality.

Check for digits out of position.

REGISTERS

0	1 Used	2 Used	3 Used	4 Used	5 Used	6 Used	7 Used	8 Used	9
S0 Used	S1 Used	S2 Used	S3 Used	S4 Used	S5 Used	S6 Used	S7 Used	S8 Used	S9 Used
A Used	B Used	C Used	D Used	E Used	I Used				

```
113   SF2
114   RCLB
115   STOI
116  *LBL6
117   CLX
118   RCLi
119   X=Y?
120   GT00
121   DSZI
122   GT07
123   GT05
124  *LBL7
125   CLX
126   RCLi
127   X=Y?
128   GT06
129   DSZI
130   GT08
131   GT05
132  *LBL8
133   CLX
134   RCLi
135   X=Y?
136   GT00
137   DSZI
138   GT06
139   GT05
140  *LBL0
141   CHS
142   STOI
143   RCLA
144   ST+0
145  *LBL5
146   P≠S
147   CLX
148   STOI
149   DSZi
150   GT09
151   P≠S
152   RCLD
153   RCLB
154   INT
155   10ˣ
156   ÷
157   FRC
158   RCL0
159   RCLA
160   ÷
161   +
162   RCL9
163   +
164   RCLB
165   STOI
166   CLX
167   GSBe
168   CLX
```

Mark digits used.

Prepare output for user.

```
169   RCLC
170   1
171   +
172   STOC
173   DSPi
174   X≠Y
175   PRTX
176   F2?
177   RTN
178   X≠Y
179   DSP0
180   PRTX
181   RTN
182  *LBL1
183   RCLB
184   FRC
185   RCLA
186   1/X
187   +
188   STO0
189   CLX
190   RCLB
191   STOI
192   INT
193   10ˣ
194   ÷
195   ABS
196   STO9
197  *LBL2
198   RCLS
199   FRC
200   RCLA
201   X
202   STO9
203   RCL0
204   X≠Y
205   F1?
206   X
207   1
208   +
209   INT
210   STOi
211   DSZI
212   GT02
213   RTN
214  *LBLe
215   STO1
216   STO2
217   STO3
218   STO4
219   STO5
220   STO6
221   STO7
222   STO8
223   RTN
```

Win?

Output guesses to win.

Decompose number.

Clear registers for next guess.

LABELS					FLAGS	SET STATUS		
A Start	B #digits	C Max digit	D #guesses	E Guess	0 Used	FLAGS	TRIG	DISP
a Used	b	c	d	e Used	1	ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☒ GRAD ☐ RAD ☐	FIX ☒ SCI ☐ ENG ☐
0 Used	1	2 Used	3 Used	4	2			
5 Used	6 Used	7 Used	8 Used	9 Used	3			n ___

Nim$_k$

001	*LBLA	L mode.	057	RCLE	
002	3		058	STOI	Set I to right-most pile.
003	2		059	*LBL6	
004	CHS		060	GSB2	
005	GTO0		061	X≤Y?	Test for binary unit in
006	*LBLD		062	ST+0	designated pile/column.
007	DSP1		063	DSZI	Accumulate Σc_{ij}.
008	PRTX	Print pile.# taken.	064	GTO8	Cycle till zero.
009	STOI		065	2	
010	INT		066	ST×0	Double R0 for Σc_{ij}.
011	CHS		067	RCL0	
012	10^x		068	RCL0	
013	RCLi		069	RCLE	
014	RCLI		070	1	
015	FRC		071	+	
016	1		072	X>Y?	
017	0		073	GTO0	
018	x		074	3	$k < \Sigma c_{ij}$
019	INT		075	RCLC	
020	X>Y?		076	ABS	
021	GTOa	Error, taking more than in	077	X>Y?	
022	X=0?	pile.	078	SF0	Set F0 for Σc_{ij} mod
023	GTOa	Error, taking zero delete #	079	+	(k + 1) = 0.
024	ST-i	from pile.	080	R↓	
025	R↑		081	*LBL0	
026	x	Shift by 10.	082	ENT↑	
027	1		083	R↓	
028	+		084	÷	
029	CHS		085	INT	
030	RCLA		086	R↑	
031	+	Adjust A.	087	x	
032	STOA		088	-	Σc_{ij} mod (k + 1).
033	RCLB		089	STO0	
034	STOI		090	RCLC	
035	DSPi	Readjust display.	091	X<0?	neg. = L mode
036	RCLA		092	F0?	
037	PRTX	Print new combination.	093	GTO0	
038	RTN		094	3	F0 not set.
039	*LBLC		095	RCLC	
040	3		096	ABS	
041	2		097	X>Y?	
042	*LBL0		098	GTO0	
043	DSP0		099	RCL0	
044	PRTX		100	1	
045	STOC	Initialize C to –32, L mode	101	-	
046	CF0	32, W mode.	102	X<0?	Subtract 1 from Σc_{ij}.
047	CF1		103	RCLE	If neg, replace with k.
048	*LBL9		104	STO0	
049	RCLC		105	*LBL0	
050	2		106	RCL0	
051	÷	Get 2^j	107	X=0?	If Σc_{ij} = 0 go to next
052	STOC		108	GTO9	column.
053	ABS		109	1	
054	1		110	0	
055	X=Y?		111	STOE	Initialize pointer to RS0.
056	GTO1	Exit if C = 1.	112	*LBL7	

REGISTERS

0 Σc_{ij}	1 p_1	2 p_2	3 p_3	4 p_4	5 p_5	6 p_6	7 p_7	8 p_8	9 p_9
S0 k_1	S1 k_2	S2 k_3	S3 k_4	S4 k_5	S5 k_6	S6 k_7	S7 k_8	S8 k_9	S9
A $k.p_1p_2p_3...$	B no. of piles	C 2^j	D 10, pointer		E k		I Used		

```
113  STOI
114  RCLB
115  RCLi
116  X=0?
117    X<>Y
118  STOI
119  *LBL6
120  GSB2
121  X>Y?
122  GTO0
123    SF1
124    SF2
125  DSZi
126  GTO6
127  *LBL0
128    F2?
129  GTO0
130  DSZI
131  GTO6
132  *LBL0
133  RCLD
134    X<>I
135  STOi
136  ISZI
137    CLX
138    X<>I
139  STOD
140  DSZi
141  GTO7
142  GTO9
143  *LBL2
144  RCLi
145  RCLC
146    ABS
147    ÷
148    FRC
149    .
150      5
151    RTN
152  *LBLI
153    F1?
154  GTO0
155  RCLB
156  STOI
157  *LBL5
158  RCLi
159  DSZi
160  X>0?
161  GTO0
162  STOi
163  DSZI
164  GTO5
165  *LBL0
166  RCLB
167  RCLA
168  RCLC
```

If pointer empty, use right most pile no.

Test for binary unit.

Set F1, at least one pile decreased.
Set F2, this pile decreased.
Step to next pile.

Recall D to I.

Store pile # in pointer.
Increment I (D).
0 to I.

I to D.
Decrement Σcol by 1.
Go to new pile or new column.
Subroutine.
Objects in pile.

Divided by 2^j.

Compare fractional part to 0.5.

Any pile decreased, exit with no change.

Otherwise decrement right-most pile by 1.

Exit routine.
Recall no. piles.
Display.
2^j

```
169  RCLE
170    P≠S
171  CLRG
172    P≠S
173  STOE
174    R↓
175  STOC
176    R↓
177  STOA
178    R↓
179  STOB
180  STOI
181  DSPi
182      0
183  *LBL4
184  RCLi
185      +
186      1
187      0
188      ÷
189  DSZI
190  GTO4
191  RCLE
192      +
193  STOA
194    SPC
195  PRTX
196    RTN
197  *LBLE
198  CLRG
199    P≠S
200  CLRG
201  STOA
202  ENT↑
203    INT
204  STOE
205      -
206  *LBL3
207  ISZI
208      1
209      0
210      x
211  ENT↑
212    INT
213  STOi
214      -
215  X≠0?
216  GTO3
217  RCLI
218  DSPi
219  STOB
220  RCLA
221  PRTX
222    RTN
```

k

Clear pointer reg's.

Restore E, C, A, B.

Adjust display.

Build display.

Shift by 10.

Recall k.
Add to combination.

Space and print display.

Entry routine.
Clear all registers.

Store input in A.

Input fractional part.

Shift by 10 to get individual pile #'s.

Continue till fractional part = 0.

Set display.

Print input.

LABELS

A L mode	B	C W mode	D Delete	E Enter
a	b	c	d	e
0 Used	1 Used	2 Used	3 Used	4 Used
5 Used	6 Used	7 Used	8 Used	9 Used

FLAGS

0	L/W
1	⩾ 1 pile
2	this pile
3	

SET STATUS

FLAGS	ON	OFF
0	☐	☒
1	☐	☒
2	☐	☒
3	☐	☒

TRIG: DEG ☒ GRAD ☐ RAD ☐

DISP: FIX ☒ SCI ☐ ENG ☐ n 4


Queen Board

001	*LBLA	Current position.	057	1	
002	STO1	R_1	058	-	
003	GSBE		059	X=Y?	127 = R_2?
004	1		060	GTO9	
005	X=Y?		061	1	
006	GTO2		062	-	
007	7		063	X=Y?	126 = R_2?
008	STO1	7→R_1	064	GTO9	
009	*LBL1		065	5	
010	RCL1		066	1	
011	RCL1		067	-	
012	EEX		068	X=Y?	75 = R_2?
013	1		069	GTO9	
014	x		070	2	
015	+		071	-	
016	STO2	10K + R_1→R_2	072	X=Y?	73 = R_2?
017	GSBE	Position good?	073	GTO5	
018	1		074	2	
019	X=Y?		075	9	
020	GTO0	Yes, recall R_2.	076	-	
021	RCL1		077	X=Y?	44 = R_2?
022	ST+2	K + R_2→R_3	078	GTO9	
023	RCL2	Position good?	079	3	
024	GSBE		080	-	
025	1		081	X=Y?	41 = R_2?
026	X=Y?		082	GTO5	
027	GTO0	Yes, recall R_2.	083	RTN	
028	RCL1		084	*LBL5	
029	EEX		085	1	
030	1		086	RTN	
031	x				
032	ST+2	10K + R_2→R_2			
033	RCL2				
034	GSBE	Position good?			
035	1				
036	X=Y?				
037	GTO0	Yes, recall R_2.			
038	DSZI				
039	GTO1				
040	RCL1				
041	*LBL2				
042	EEX				
043	1	Default move.			
044	ST+1	10 + R_1→R_1			
045	RCL1				
046	RTN				
047	*LBL0				
048	RCL2				
049	RTN				
050	*LBLE	Test for good position.			
051	1				
052	5				
053	8				
054	X=Y?	158 = R_2?			
055	GTO9				
056	3				

REGISTERS

0	1	2	3	4	5	6	7	8	9
	Used	Used							
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
					K



LABELS					FLAGS
A Used	B	C	D	E Used	0
a	b	c	d	e	1
0 Used	1 Used	2 Used	3	4	2
5	6	7	8	9 Used	3

SET STATUS		
FLAGS	TRIG	DISP
ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☒ GRAD ☐ RAD ☐	FIX ☒ SCI ☐ ENG ☐ n 0

Hexapawn

```
001  *LBL0          Machine first.-
002      8
003      3
004      8
005      8          Configurations for move 1.
006      6
007      0
008      7
009    STO1
010      3
011      1
012      3          Configurations for move 2.
013      9
014      5
015      8
016      3
017    STO2
018      3
019      4          Configurations for move 3.
020      3
021      1
022      4
023    STO3
024    GTO8         ------------
025  *LBL1          Player first.
026      1
027      6
028      7
029      7          Configurations for move 1.
030      7
031      2
032      1
033      5
034    STO1
035      1
036      6
037      7          Configurations for move 2.
038      5
039      6
040      7
041      3
042      5
043    STO2
044      5
045      2          Configurations for move 3.
046      4
047      4
048      1
049      3
050    STO3
051  *LBL0
052      0
053    STO4
054    STO5
055    STO6
056    STO7
```

```
057  *LBL9
058     Pi
059      +
060    STO6
061    GTO9         ------------
062  *LBLA          Move
063    STO8
064    RCL4
065    STO9
066    RCL5
067    STO7
068      2
069    RCL8
070     Y^x
071    STO5
072      3
073    STO1         ------------
074    RCL6         Generate a random
075     Pi          number between 1 and 3.
076      +
077     X^2
078     FRC
079    STO6
080      3
081      X
082      1
083      +
084     INT
085    STO4         ------------
086  *LBL1          BEGIN loop 1
087      3
088    RCL4
089      1          INCREMENT trial move
090      +
091    X>Y?
092      1
093    STO4
094    X=1
095    RCL1
096    X=V
097    X=I
098     R↓
099    RCL5
100      ÷
101     FRC
102      .
103      5
104    X≠Y?         IF trial move OK
105    GTO4         THEN exit
106    DSZI         IF less than 3 tries
107    GTO1         THEN REPEAT loop 1
108    RCL7         ELSE no move possible.
109    STO5
110    STO4
111     CLX
112     RTN
```

REGISTERS

0	1 Moves #1	2 Moves #2	3 Moves #3	4 Trial move	5 2↑(Config)	6 Random	7 2↑(Last conf)	8 This move	9 Last move
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I

```
113 *LBL4
114  RCL4
115   RTN
116 *LBLB
117  RCL4
118   X≠I
119  RCL5
120     2
121     ÷
122  ST-i
123   R↓
124   X≠I
125   RTN
```

DISPLAY move

PUNISH
Remove last configuration from move list

LABELS					FLAGS
A Move	B Punish	C Mach. 1st	D	E	0
a	b	c Player 1st	d	e	1
0 Used	1 Loop 1	2	3	4 Display	2
5	6	7	8	9 Used	3

SET STATUS

FLAGS			TRIG		DISP	
	ON	OFF				
0	☐	☒	DEG	☒	FIX	☒
1	☐	☒	GRAD	☐	SCI	☐
2	☐	☒	RAD	☐	ENG	☐
3	☐	☒			n 2	

Tic-Tac-Toe

001	*LBLA	Start a new game.	057	STOB	
002	8		058	INT	
003	STOE		059	RTN	
004	1		060	*LBL6	Store to R_A & R_I.
005	CHS		061	STOA	
006	STO8		062	STOI	
007	2		063	RTN	
008	GSB6		064	*LBL8	Increase move number.
009	GSB8		065	1	
010	GSBD		066	ST+0	
011	GSBe		067	RCLA	
012	RCLI		068	RTN	
013	RCLE		069	*LBLd	Store 2 for HP.
014	DSP9		070	RCLI	
015	R/S		071	CHS	
016	GSB6	Check for the 1st move of player.	072	10^x	
017	GSB8		073	2	
018	GSBd		074	x	
019	RCLi		075	RCLE	
020	INT		076	+	
021	RCLi		077	STOE	
022	STOB		078	RCLI	
023	*LBL0		079	RTN	
024	+		080	*LBLe	Decode for printing.
025	GSBB		081	EEX	
026	STOI		082	6	
027	GSBD		083	GSB9	
028	GSBe		084	EEX	
029	RCLI		085	3	
030	DSP9		086	GSB9	
031	RCLE		087	1	
032	+		088	GSB9	
033	R/S		089	SPC	
034	*LBLE	Check for 2, 3, 4th move of player and decide HP's move.	090	RTN	
035	GSB6		091	*LBL9	Print.
036	GSB8		092	DSP3	
037	GSBd		093	RCLE	
038	RCLI		094	x	
039	GSBB		095	FRC	
040	X=Y?		096	RCL0	
041	GSBB		097	+	
042	STOI		098	PRTX	
043	GSBD		099	DSP0	
044	GSBe		100	RTN	
045	RCLI		101	*LBLD	Store 1 for player.
046	DSP9		102	RCLI	
047	RCLE		103	CHS	
048	+		104	10^x	
049	R/S		105	RCLE	
050	GTOE		106	+	
051	*LBLB	Check for next move.	107	STOE	
052	RCLB		108	RCLI	
053	FRC		109	RTN	
054	1		110	*LBLo	Store constants for move sequences.
055	8		111	.	
056	x		112	5	

REGISTERS

0	1	2	3	4	5	6	7	8	9
play no.	.5873649		.5891467	.13598	.1374698	.31578	.13589	.3175964	.31587
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
Temp.	Last X of LBL B			Used	1, 2, ..., 9

113	8			169	3		
114	7			170	1		
115	3			171	5		
116	6			172	8		
117	4			173	7		
118	5			174	STO5		
119	STO1			175	0		
120	.			176	PTN		
121	5						
122	8						
123	9						
124	1						
125	4						
126	6						
127	7						
128	STO3						
129	.						
130	1						
131	3						
132	5						
133	9						
134	8						
135	STO4						
136	.						
137	1						
138	3						
139	7						
140	4						
141	6						
142	9						
143	8						
144	STO5						
145	.						
146	3						
147	1						
148	5						
149	7						
150	8						
151	STO6						
152	.						
153	1						
154	3						
155	5						
156	8						
157	9						
158	STO7						
159	.						
160	3						
161	1						
162	7						
163	5						
164	9						
165	6						
166	4						
167	STO8						
168	.						

LABELS					FLAGS
A New Game	B next move	C	D	E 2nd move	0
a	b St to A, I	c	d 2 for HP	e Decode	1
0 1st move	1	2	3	4	2
5	6	7	8 Increase	9 Print	3

SET STATUS

FLAGS			TRIG	DISP
	ON	OFF		
0	☐	☒	DEG ☒	FIX ☒
1	☐	☒	GRAD ☐	SCI ☐
2	☐	☒	RAD ☐	ENG ☐
3	☐	☒		n 0

Wari

```
001  *LBLA          Move player 1
002    CHS
003      7
004      +
005    SF1
006    STO9
007  *LBLE          Move player 2
008      6
009      +
010    CF1
011  *LBL9          Initialize move loop
012    STOC
013    STOI
014    RCLi
015    X=0?
016      ÷
017    STOD
018      0
019    STOi
020  *LBL1          Begin loop 1
021    DSZI         I←I − 1
022    GTO8         If I = 0
023      1          Then I←12
024      2
025    STOI
026  *LBL8
027    RCLI
028    RCLC
029    X=Y?         If I = original bin
030    GTO1         then skip to next bin
031      1          else
032    ST+i           increment bin
033    RCLD           decrement # seeds
034      1
035      -
036    STOD
037    X=0?         If seeds used up
038    GTO5         then try to capture
039    GTO1         else repeat loop 1
040  *LBLC          ---------- Initialize
041      1
042      2
043    STOI
044      4
045  *LBL0
046    STOi
047    DSZI
048    GTO0
049      0
050    STOA
051    STOB
052  *LBL6          ----------
053    GSBB         Display board
054    F0?
055    GTOD         Display score
056    F1?
057    GTOe
058    GTOD         ----------
059  *LBLB          Display board
060    SPC
061      6          Initialize
062    STOI         I←6
063  *LBL3          Begin loop 3
064    RCLi
065      1
066      3
067    ROLI
068      -
069    STOI
070    CLX
071      +
072    RCLi
073    EEX
074      2
075      ÷
076      +          D = C(I) + C(13 − I) / 100
077    PRTX         Print D
078    RCLI
079      1
080      3
081      -
082    CHS
083    STOI
084    DSZI         I←I − 1
085    GTO3         If I > 0 then repeat loop 3
086    SPC
087    RTN          ----------
088  *LBLD          Display score
089    RCLA
090    RCLB
091    EEX
092      2
093      ÷
094      +
095    RTN          ----------
096  *LBL5          CAPTURE
097    RCLI
098      6
099      ÷
100      5
101      -
102    RCLC
103    LSTX
104      -
105      x
106    X>0?         If start & finish on same
107    GTO6         side
108  *LBL7          Then no capture
109      2          Else begin loop 7
110    RCLi
111    X=Y?         If bin has 2 or 3
112    GTO7         Then increment appro-
```

REGISTERS

0	1 Bin 1	2 Bin 2	3 Bin 3	4 Bin 4	5 Bin 5	6 Bin 6	7 Bin 7	8 Bin 8	9 Bin 9
S0 Bin 10	S1 Bin 11	S2 Bin 12	S3	S4	S5	S6	S7	S8	S9

A Score 1	B Score 2	C Current bin	D # seeds	E Random	I Pointer & Counter

```
113      3
114   X≠Y?
115    GTO6
116  *LBL7
117     FI?
118    GTO9
119    RCLB
120      +
121    STOB
122    GTO7
123  *LBL9
124    RCLA
125      +
126    STOA
127  *LBL7
128      0
129    STOi
130    ISZI
131      7
132    RCLI
133   X=Y?
134    GTO6
135      1
136      3
137   X=Y?
138    GTO6
139    GTO7
140  *LBLe
141      1
142    STOI
143  *LBL2
144    RCLi
145   X=0?
146    GTOb
147      3
148   XⱢY?
149    GTO4
150  *LBLb
151    ISZI
152    RCLI
153      7
154   X≠Y?
155    GTO2
156  *LBLc
157    RCLE
158     Pi
159      +
160      8
161     Y^x
162     FRC
163    STOE
164      6
165      x
166      1
167      +
168     →P
```

priate score,

Else no more capture.

Begin loop 7
If player 1
Then go to 9
Else
 increment score 2

Increment score 1

Remove seeds from bin

Step to next bin
If this is bin 7 or 13
Then done
Else
 Try to capture from this bin

Automatic player 2

I←1
Begin loop 2

If C(I) = 0
Then next I
Else if C(I) = 1 or 2
Then
Search for attacking bin
Else next I
I←I + 1

While I < 7
Repeat loop 2

Move randomly

```
169     INT
170    STO0
171      6
172      +
173    STOI
174    RCLi
175   X=0?
176    GTOc
177    RCL0
178    PRTX
179    GSBE
180     RTN
181  *LBL4
182    RCLI
183    STO6
184      1
185      2
186    STOI
187  *LBLd
188    RCLi
189   X=0?
190    GTO8
191      1
192      1
193      ÷
194     FRC
195      1
196      1
197      x
198    RCLI
199    RCL0
200      -
201   X=Y?
202    GTO9
203  *LBL8
204    DSZI
205    RCLI
206      6
207   X=Y?
208    GTO8
209    GTOd
210  *LBL8
211    RCL0
212    STOI
213    GTOb
214  *LBL9
215    RCLI
216      6
217      -
218    PRTX
219    GSBE
220     RTN
```

If bin is empty
Then try again
Else
 make move

Search for attacking bin

Save pointer from loop 2

Initialize new pointer

If capture is possible
Then go to 9

Decrement pointer

If search is complete
Then go to 8

Restore pointer for loop 2

Capture possible

LABELS

A Player 1	B Display	C Start	D Score	E Player 2	0 P1 vs. P2
a	b Random move	c Random loop	d Loop	e Auto player 2	1 Player 1
0 Loop	1 Loop	2 Loop	3 Loop	4 Used	2
5 Used	6 Used	7 Used	8 Used	9 Used	3

FLAGS

SET STATUS

FLAGS	ON	OFF
0	☒	☐
1	☐	☒
2	☐	☒
3	☐	☒

TRIG	
DEG	☒
GRAD	☐
RAD	☐

DISP	
FIX	☒
SCI	☐
ENG	☐
n	2

Racetrack

```
001  *LBL0
002   CLRG
003    P≠S
004   CLRG
005      1
006      7
007   STOI
008  *LBL9
009   RCLI
010      1
011      -
012      4
013      ÷
014      5
015      ×
016      5
017      5
018      +
019   STOi
020   RCLI
021      4
022      -
023   STOI
024   X>0?
025   GTO9
026    RTN
027  *LBLA
028      1
029   GTO0
030  *LBLB
031      2
032   GTO0
033  *LBLC
034      3
035   GTO0
036  *LBLD
037      4
038   GTO0
039  *LBLE
040      5
041  *LBL0
042   PRTX
043      1
044      -
045      4
046      ×
047      1
048      +
049   STO0
050   STOI
051    R↓
052      9
053   X≤Y?
054    X≠Y
055    R↓
056    →R
057   ISZI
058   ISZI
059   RCLi
060      +
061   STOI
062   GSB2
063   DSZI
064   DSZI
065   RCLi
066      +
067   STOi
068    X≠Y
069   ISZI
070   ISZI
071   ISZI
072   RCLi
073      +
074   STOi
075   GSB2
076   DSZI
077   DSZI
078   RCLi
079      +
080   STOi
081   RCL0
082   STOI
083   RCLi
084   STOB
085   ISZI
086   RCLi
087   STOC
088      1
089      7
090   STOI
091  *LBL8
092   RCL6
093   X=Y?
094   GTO0
095   RCLi
096   RCLB
097      -
098   ISZI
099   RCLi
100   RCLC
101      -
102     →P
103      2
104   X≤Y?
105   DSZI
106   X≤Y?
107   GTO0
108   RCLI
109      2
110      -
111      4
112      ÷
```

START

Initialize loop 9

Compute starting position

Decrement pointer

While pointer is positive, repeat loop 9

Identify cars

Print car ID
Compute a pointer

If |v| exceeds 9
Then use 9 instead

Increment v_x

Increment x

Increment v_y

Increment y

Initialize loop 8

Test for crash

If same car
Then skip test

If distance ≥ 2
Then no crash

REGISTERS

0 Pointer	1	2	3	4	5	6	7	8	9
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B Used	C Used	D	E	I Used

```
113    1
114    +
115    PSE          Display ID of car in crash
116    PSE
117    PSE
118    0            Set v_y and v_x to zero for
119    ISZI         both cars
120    STO;
121    ISZI
122    STO;
123    RCL0         Save pointer
124    X≠I
125    X≠Y
126    ISZI
127    ISZI
128    STO;
129    ISZI
130    STO;
131    X≠Y
132    3
133    -
134    X≠I          Restore pointer
135  *LBL0          ---------
136    RCLI         Decrement pointer
137    4
138    -
139    STOI
140    X>0?         WHILE pointer is positive
141    GTO8         repeat loop 8
142    RCLB         ---------
143    5            CHECK INSIDE FENCE
144    0
145    ÷
146    GSB7
147    RCLC
148    7
149    0
150    ÷
151    GSB7
152    +
153    1
154    X>Y?         If off track
155    GSB5         Then penalize
156    RCLB         ---------
157    8            CHECK OUTSIDE FENCE
158    0
159    ÷
160    GSB7
161    RCLC
162    EEX
163    2
164    ÷
165    GSB7
166    +
167    1
168    X>Y?         If on track
169    GTO6         THEN don't penalize
170  *LBL5          ---------
171    RCL0         PENALIZE
172    2
173    +
174    STOI
175    0            Set v_y and v_x to zero
176    STO;
177    ISZI
178    STO;         ------
179  *LBL6          Set up display
180    RCL0
181    3
182    +
183    STOI
184    RCL;
185    DSZI
186    RCL;
187    DSZI
188    +P
189    RCL;
190    DSZI
191    RCL;
192    PRST
193    RTN          ---------
194  *LBL2          Subroutine to compute
195    LSTX         ΔS
196    +
197    2
198    ÷
199    RTN          ---------
200  *LBL7          Subroutine to compute
201    ABS          y^2.5
202    2
203    .
204    5
205    y^x
206    RTN          ---------
207  *LBL0          Display position
208    PRTX         ID→y,x
209    1
210    -
211    4
212    x
213    2
214    +
215    STOI
216    RCLI
217    PRTX
218    DSZI
219    RCLI
220    PRTX
221    RTN
```

LABELS

A 1	B 2	C 3	D 4	E 5	0
a ID→y,x	b	c START	d	e	1
0 Used	1	2 Subroutine	3	4	2
5 Off track	6 Display	7 Subroutine	8 Crash loop	9 Start loop	3

FLAGS

	ON	OFF
0	☐	☒
1	☐	☒
2	☐	☒
3	☐	☒

SET STATUS

TRIG	DISP
DEG ☒	FIX ☒
GRAD ☐	SCI ☐
RAD ☐	ENG ☐
	n 2

Teaser

00:	*LBLC	Initialize	057	STx9	
002	1		058	GTOD	
003	STO5		059	*LBL7	
004	CHS		060	STx4	
005	STO1		061	STx5	
006	STO2		062	STx7	
007	STO3		063	STx8	
008	STO4		064	GTOD	
009	STO6		065	*LBL8	
010	STO7		066	STx7	
011	STO8		067	STx8	
012	STO9		068	STx9	
013	STOB		069	GTOD	
014	1		070	*LBL9	
015	0		071	STx5	
016	STOA		072	STx6	
017	GTOD		073	STx8	
018	*LBLA	Store move	074	STx9	
019	STOI		075	*LBLD	Set up display
020	RCLi	Generate a negative 1 or display "Error"	076	F0?	
021	X<0?		077	SPC	
022	GTOe		078	FIX	
023	CHS		079	DSP3	
024	GTOi	Go to appropriate routine to change board	080	RCL9	
025	*LBL1		081	X<0?	
026	STx1		082	0	
027	STx2		083	RCLA	
028	STx4		084	÷	
029	STx5		085	RCL8	
030	GTOD		086	X<0?	
031	*LBL2		087	CLX	
032	STx1		088	+	
033	STx2		089	RCLA	
034	STx3		090	÷	
035	GTOD		091	RCL7	
036	*LBL3		092	X<0?	
037	STx2		093	CLX	
038	STx3		094	+	
039	STx5		095	RCLA	
040	STx6		096	÷	
041	GTOD		097	F0?	
042	*LBL4		098	PRTX	
043	STx1		099	EEX	
044	STx4		100	6	
045	STx7		101	÷	
046	GTOD		102	STO0	
047	*LBL5		103	RCL6	
048	STx2		104	X<0?	
049	STx5		105	0	
050	STx8		106	RCLA	
051	STx4		107	÷	
052	STx6		108	RCL5	
053	GTOD		109	X<0?	
054	*LBL6		110	CLX	
055	STx3		111	+	
056	STx6		112	RCLA	

REGISTERS

0	1	2	3	4	5	6	7	8	9
Used	±1	±1	±1	±1	±1	±1	±1	±1	±1
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
10	# of moves				

```
113    ÷
114   RCL4
115   X<0?
116    CLX
117     +
118   RCLA
119     ÷
120    F0?
121   PRTX
122    EEX
123      3
124     ÷
125   ST+0
126   RCL3
127   X<0?
128      0
129   RCLA
130     ÷
131   RCL2
132   X<0?
133    CLX
134     +
135   RCLA
136     ÷
137   RCL1
138   X<0?
139    CLX
140     +
141   RCLA
142     ÷
143    F0?
144   PRTX
145   RCL0
146     +
147      9
148     -
149   RCLB
150      1
151     +
152   STOB
153    10^x
154     x
155    SCI
156   DSP9
157    RTN
158  *LBLE
159    F0?
160   GTOe
161    SF0
162      1
163    RTN
164  *LBLe
165    CF0
166      0
167    RTN
```

If flag 0
then clear flag
else set flag and
display 1

Clear flag
display 0

LABELS					FLAGS	SET STATUS		
A Shoot	B	C Start	D Print	E Print?	0 True/False	FLAGS	TRIG	DISP
a	b	c	d	e	1	ON OFF 0 ☒ ☐ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☒ GRAD ☐ RAD ☐	FIX ☐ SCI ☒ ENG ☐ n 9
0 Used	1 Used	2 Used	3 Used	4 Used	2			
5 Used	6 Used	7 Used	8 Used	9 Used	3			

Golf

001	*LBL b	Random #.	057	RCL 6	Print.
002	RCL A	u_{i+1}	058	RCL D	
003	9		059	R↓	
004	9		060	RCL C	
005	7		061	PRST	Print h, Y_h, Par, W.
006	x		062	RTN	----------
007	FRC		063	*LBL D	Club distance.
008	STO A	u_i	064	1	Putter
009	.		065	9	
010	5		066	GTO C	
011	-	$u_i - .5$	067	*LBL E	Wood
012	RTN	----------	068	4	
013	*LBL A	Woods distance.	069	-	
014	GSB b		070	2	
015	1		071	x	
016	+		072	*LBL C	Iron
017	4		073	1	
018	0		074	ST+1	S' = total strokes.
019	x	W	075	R↓	
020	STO C	----------	076	2	
021	0	Clear registers.	077	0	
022	STO 5		078	-	
023	STO 3		079	1	
024	STO 2		080	0	
025	P≠S		081	x	
026	STO 5		082	CHS	
027	STO 3		083	STO 8	Mean distance m.
028	STO 2		084	0	
029	P≠S	----------	085	R/S	Enter s.
030	GSB b	Hole yardage.	086	STO B	s
031	9		087	2	Calculate Y_c
032	x		088	1/X	
033	7		089	GSB b	
034	+		090	-	
035	5		091	LSTX	.5
036	0		092	X≠Y	
037	x	Y_h	093	RCL 7	H
038	STO D	----------	094	5	
039	ST-2	Yo_1	095	6	
040	P≠S		096	÷	
041	ST-2	Yo_2	097	x	
042	P≠S	----------	098	-	
043	2	Par.	099	RCL 8	m
044	1		100	5	
045	5		101	÷	
046	÷		102	x	
047	3		103	RCL 8	m
048	+		104	RCL B	s
049	INT	Par.	105	x	
050	ST+9	Σ Par.	106	+	
051	P≠S		107	ABS	Y_c
052	ST+9	Σ Par.	108	STO E	----------
053	1	----------	109	GSB b	Calculate θ_c.
054	ST+0	Hole number.	110	3	
055	P≠S	h	111	x	
056	ST+0	h	112	RCL 7	H

REGISTERS

0 h	1 S_1'	2 Y_1	3 x_1	4 D_{h1}	5 ϕ_{h1}	6	7 H_1	8 m	9 Σ Par
S0 h	S1 S_2'	S2 Y_2	S3 x_2	S4 D_{h1}	S5 ϕ_{h2}	S6	S7 H_2	S8	S9 Σ Par

A u_i	B s, θ_c	C W	D Y_h	E Y_c	I		

113	3	
114	6	
115	+	
116	↓IX	
117	x	
118	STOB	θ_c
119	RCL3	Is ball holed?
120	ABS	
121	RCLC	W
122	X≤Y?	$W \leq \lvert x_{n-1} \rvert$?
123	GSB9	Yes—in woods.
124	RCL4	No—escape woods.
125	4	
126	+	
127	RCLE	Y_c
128	X>Y?	$Y_c > D_h + 4$?
129	GTO4	Yes—missed hole.
130	RCL4	No—in hole?
131	5	
132	1/X	
133	-	
134	X>Y?	$D_h - .2 > Y_c$?
135	GTO4	Yes—missed hole.
136	LSTX	No—in hole?
137	RCL4	D_h
138	÷	
139	TAN⁻¹	γ: hole window
140	RCLB	θ_c
141	ABS	
142	X>Y?	$\lvert\theta_c\rvert > \gamma$?
143	GTO4	Yes—missed hole.
144	0	No—in hole!
145	DSP9	
146	PRTX	Print 0.000000000.
147	RCL1	S′ = total strokes.
148	RCL7	H
149	1	
150	8	
151	÷	H/18
152	RCL0	h
153	x	h (H/18)
154	-	S′ – h (H/18)
155	RCL9	Σ Par
156	-	[S′ –h(H/18)] – Σ Par
157	DSP0	
158	PRTX	Print S.
159	RTN	
160	*LBL4	Missed hole.
161	RCLB	θ_{cn}
162	RCL5	$\phi_{h\,n-1}$
163	+	
164	RCLE	Y_{cn}
165	→R	$Y_c, \theta + \phi \rightarrow y', x'$
166	RCL2	y_{n-1}
167	+	
168	STO2	y_n

169	X≠Y	x′
170	RCL3	x_{n-1}
171	+	
172	STO3	x_n
173	CHS	
174	X≠Y	
175	CHS	
176	→P	$-y_n, -x_n \rightarrow D_{h_n}, \phi_n$
177	STO4	D_{h_n}
178	X≠Y	
179	STO5	ϕ_{h_n}
180	RCLE	Y_c
181	RCLB	θ_c
182	RCL2	y_n
183	RCL3	x_n
184	PRST	Print Y_c, θ_c, y, x
185	ABS	In woods?
186	RCLC	W
187	X≤Y?	$W \leq \lvert x \rvert$?
188	GTO8	Yes: In woods
189	GTO7	No: No woods
190	*LBL8	Woods display
191	DSP6	
192	*LBL7	Print D_h, ϕ_h
193	RCL4	D_h
194	PRTX	Print D_h
195	RCL5	ϕ_h
196	PRTX	Print ϕ_h
197	DSP0	
198	RTN	
199	*LBL9	In woods.
200	RCLB	θ_c
201	ABS	
202	RCL5	ϕ_h
203	ABS	
204	SIN	sin $\lvert\phi\rvert$
205	3	
206	x	3 sin $\lvert\phi\rvert$
207	RCL3	x
208	ABS	
209	RCLC	W
210	-	$\lvert x \rvert - W$
211	÷	3 sin $\lvert\phi\rvert$/(W – $\lvert x \rvert$)
212	TAN⁻¹	β = woods window
213	ABS	
214	X>Y?	$\lvert\beta\rvert > \lvert\theta\rvert$?
215	RTN	Yes—escape woods
216	RCLE	No—hit trees
217	9	
218	÷	
219	STOE	$Y_c = Y_c'/9$
220	RCLB	θ'
221	9	
222	x	
223	STOB	$\theta = 9(\theta')$
224	RTN	

LABELS

A HOLE	B WOOD	C IRON	D PUTTER	E	0
a	b RAN, #	c	d	e	1
0	1	2	3	4 No hole	2
5	6	7 Prt D_h, ϕ_h	8 Wood disp.	9 In woods	3

FLAGS

	ON	OFF
0	☐	☒
1	☐	☒
2	☐	☒
3	☐	☒

SET STATUS

TRIG	DISP
DEG ☒	FIX ☒
GRAD ☐	SCI ☐
RAD ☐	ENG ☐
	n 0

The Dealer

```
001  *LBLC
002    SPC
003  *LBLE
004   STOA
005   GSBA
006   PRTX
007   RCLA
008     1
009     -
010   X>0?
011   GTO6
012    RTN
013  *LBLA
014   RCLB
015     9
016     9
017     7
018     X
019    FRC
020   STOB
021   RCLC
022     X
023   INT
024     5
025     ÷
026   STOI
027    FRC
028     1
029     0
030     X
031   10^X
032   STOD
033   RCLI
034     X
035    FRC
036   EEX
037     2
038     X
039   INT
040   STOE
041   RCLI
042   RCLC
043     5
044     ÷
045   STOI
046    FRC
047     1
048     0
049     X
050   10^X
051   1/X
052   LSTX
053   RCLi
054     X
055    FRC
056   EEX
057     2
058     X
059   INT
060   RCLE
061     -
062   EEX
063     2
064     ÷
065     X
066   ST-i
067    R↑
068   STOI
069   LSTX
070   RCLD
071     ÷
072   ST+i
073   RCLC
074     I
075     -
076   STOC
077   X<0?
078   GSBc
079   RCLE
080  *LBL5
081    F1?
082   GTO8
083     1
084     3
085     ÷
086     1
087     +
088   INT
089   LSTX
090    FRC
091     1
092     3
093     X
094     1
095     .
096     5
097     +
098   INT
099   10^X
100     X
101   SCI
102   RTN
103  *LBL0
104     1
105     +
106   FIX
107   RTN
108  *LBLc
109     2
110     3
111   ENT↑
112     5
```

Deal n cards.

Generate pseudo-random number.

Scale pseudo-random number according to number of cards.

Calculate register containing selected card.

Compute multplier necessary to move selected card up to decimal point.

Remove digits to left of decimal.

Select card and store card number in R_E.

Take card from bottom of deck.

Place selected card at bottom of deck.

Place card from bottom of deck in place of selected card.

Move bottom of deck up one card.

If all cards have been dealt, shuffle.

If bingo flag is set, go to zero.

Calculate suit.

Calculate card.

Combine for output.

Bingo output.

Shuffle:
Store 51 as number in deck for cards or 74 for bingo.

REGISTERS

0 .000102...	1 .050607...	2 .101112...	3 .151617...	4 .202122...	5 .252627...	6 .303132...	7 .353637...	8 .404142...	9 .454647...
S0 .505152...	S1 .555657...	S2 .606162...	S3 .656667...	S4 .707172...	S5 .757677...	S6 .808182...	S7 .858687...	S8 .909192...	S9 .959697...

A	B	C	D	E	I
#Cards	Seed	Deck Point	Used	Card	Hole

```
113      1
114    F1?
115      +
116   STOC
117    CLX
118    RTN
119  *LBLe
120    SF1
121   GTO0
122  *LBLa
123    CF1
124  *LBL0
125      1
126      8
127   STOI
128      .
129      0
130      5
131      0
132      5
133      0
134      5
135      0
136      5
137      0
138      5
139    CHS
140   ENT↑
141   ENT↑
142   ENT↑
143      .
144      9
145      5
146      9
147      6
148      9
149      7
150      9
151      8
152      9
153      9
154   STO9
155    P≠S
156  *LBL7
157      +
158   STOi
159   DSZI
160   GTO7
161      +
162   STO0
163      .
164      5
165      2
166      8
167      4
168      1
```

Set bingo flag.

Clear bingo flag.

Load cards as two digit numbers; five per register.

Store seed.

```
169      6
170      3
171   STOB
172   GSBc
173    RTN
174   STOB
175    RTN
176  *LBLE
177    SPC
178   RCLC
179   GSBc
180     R↓
181   RCLC
182   STOD
183    X≠Y
184   STOC
185  *LBL4
186   RCLD
187      5
188      ÷
189   STOI
190    FRC
191      1
192      0
193      x
194     10ˣ
195   RCLi
196      x
197    FRC
198    EEX
199      2
200      x
201    INT
202   GSB5
203   PRTX
204   RCLC
205   RCLD
206      1
207      -
208   STOD
209   X≠Y?
210   GTO4
211     R↓
212     R↓
213    RTN
```

Store number of cards.

Store user seed.

Set registers for review of cards dealt.

Pull values out of deck in order previously dealt for review.

Is review complete?

Display last value from review.

LABELS					FLAGS	SET STATUS		
A →Hit	B	C n→Deal	D	E Review	0	FLAGS	TRIG	DISP
a Cards; seed	b	c Shuffle	d	e Bingo; seed	1 Bingo	ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☒ GRAD ☐ RAD ☐	FIX ☒ SCI ☐ ENG ☐ n 0
0 Used	1	2	3	4 Review	2			
5 Suit/Card	6 Deal	7 Start	8	9	3			

Bowling Scorekeeper

001	*LBLa	Start
002	CLRG	Clear primary registers.
003	P≠S	
004	9	
005	STOI	
006	EEX	
007	4	
008	CHS	
009	*LBL9	
010	STOi	Store .0001 in secondary
011	DSZI	registers 0 to 9.
012	GTO9	
013	STOi	
014	CLX	
015	RTN	
016	*LBLA	Entry for other than spare
017	INT	or strike.
018	LSTX	
019	FRC	
020	ENT↑	
021	ENT↑	
022	1	
023	0	
024	X	
025	FRC	
026	X≠0?	Error if extra digits in entry
027	GTOB	e.g. 1.08.
028	R↓	
029	1	
030	0	
031	÷	
032	+	Original entry
033	STOI	Store and decrement for
034	DSZI	indirect address.
035	CF0	NOP
036	FRC	
037	EEX	
038	2	
039	X	Pin count
040	P≠S	
041	RCLi	Recall secondary register
042	P≠S	(CS.S1S2 PS).
043	ENT↑	
044	INT	CS = current sum
045	ENT↑	
046	R↑	
047	+	New CS
048	1	
049	1	
050	X>Y?	Less than 11?
051	GTO0	Continue
052	*LBL8	else error
053	ISZI	
054	RCLI	
055	GSBD	
056	GTOb	

057	*LBLB	Spare
058	*LBLC	Strike
059	INT	Remove extra digits.
060	.	
061	1	
062	+	
063	STOI	Store and decrement for
064	DSZI	indirect address.
065	CF0	NOP
066	P≠S	
067	RCLi	Recall secondary register.
068	P≠S	
069	ENT↑	
070	INT	
071	1	
072	0	10 pins
073	ENT↑	
074	*LBL0	
075	R↓	Pins down
076	STOA	New CS to A
077	R↓	
078	GSB1	Shift, get S1
079	STOB	S1 to B
080	GSB1	Shift, get S2
081	STOC	S2 to C
082	GSB1	Shift, get PS
083	STOD	PS to D
084	RCLi	Recall primary register.
085	CF1	Clear 2nd ball flag.
086	X<0?	If reg. neg.
087	SF1	set 2nd ball flag.
088	ABS	Remove sign.
089	EEX	
090	2	
091	X	
092	INT	
093	EEX	
094	2	
095	÷	
096	STOE	SSS.FS to E
097	RCLC	
098	X≠0?	If strike 2 balls back
099	GSB2	GSB2.
100	RCLB	Strike 1 ball back
101	STOC	now 2 balls back.
102	0	No strike 1 ball back.
103	STOB	
104	F1?	If 2nd ball
105	GTO3	GTO 3
106	RCLD	Add count
107	X≠0?	
108	GSB2	
109	0	
110	STOD	0 to PS
111	RCLA	
112	1	

REGISTERS

0 Used	1 Used	2 Used	3 Used	4 Used	5 Used	6 Used	7 Used	8 Used	9 Used
S0 Used	S1 Used	S2 Used	S3 Used	S4 Used	S5 Used	S6 Used	S7 Used	S8 Used	S9 Used

A CS	B S1	C S2	D PS	E SSS.FS	I ID.P

113	0	
114	X≠Y?	Strike?
115	GTO4	No strike
116	STOB	Store strike
117	GTO5	----------
118	*LBL4	2nd ball
119	SF1	
120	GTO6	----------
121	*LBL3	Spare?
122	CF1	
123	RCLA	
124	1	
125	0	
126	X≠Y?	CS ≠ 10?
127	GTO7	
128	STOD	
129	GTO5	
130	*LBL7	Add count
131	GSB2	
132	*LBL5	
133	0	
134	STOA	0 to CS
135	RCLi	Increment frame count.
136	ABS	
137	EEX	
138	4	
139	CHS	
140	+	
141	STOi	----------
142	*LBL6	Ready score and frame
143	RCLD	display, PS.
144	EEX	
145	2	
146	÷	
147	RCLC	S2
148	+	
149	EEX	
150	2	
151	÷	
152	RCLB	S1
153	+	
154	EEX	
155	2	
156	÷	
157	RCLA	CS
158	+	CS.S1S2PS
159	P≠S	
160	STOi	Update sec. reg.
161	P≠S	
162	RCLi	
163	ABS	Remove sign.
164	EEX	
165	2	
166	X	
167	FRC	.NF
168	EEX	

169	2	
170	X	
171	INT	NF.
172	RCLI	
173	FRC	Last ball
174	+	NF.LB
175	EEX	
176	4	
177	÷	.00NFLB
178	RCLE	
179	+	SSS.FSNFLB
180	F1?	If flag set.
181	CHS	Make negative.
182	STOi	Update print register.
183	PRTX	Print display.
184	RTN	----------
185	*LBL1	Subroutine to shift and
186	-	take integer part.
187	EEX	
188	2	
189	X	
190	ENT1	
191	INT	
192	RTN	----------
193	*LBL2	Scoring subroutine
194	RCLB	S1
195	RCLC	S2
196	+	
197	RCLD	PS
198	+	
199	RCLA	CS
200	+	
201	RCLE	SSS.FS
202	ABS	
203	+	
204	EEX	
205	2	
206	CHS	.01
207	+	Increment FS
208	STOE	Update E
209	FRC	Compare FS to .1
210	.	
211	1	
212	X>Y?	If less than .1
213	RTN	Continue
214	RCLE	Otherwise
215	ABS	
216	STOi	Update print register.
217	PRTX	Print and stop.
218	R/S	
219	*LBLD	----------
220	1	Recall score display.
221	-	
222	STOI	
223	RCLi	
224	RTN	

LABELS					FLAGS
A ID.P entry	B Spare	C Strike	D Recall score	E	0
a Start	b Error	c	d	e	1 2nd ball
0 Used	1 Shift sub.	2 Score sub.	3 Spare	4 2nd	2
5 Add frame	6 Display	7 Add count	8 Error	9 Initialize	3

SET STATUS		
FLAGS	TRIG	DISP
ON OFF 0 ☐ ☒ 1 ☐ ☒ 2 ☐ ☒ 3 ☐ ☒	DEG ☒ GRAD ☐ RAD ☐	FIX ☒ SCI ☐ ENG ☐ n 4

Biorhythms

```
001  *LBL2
002   ISZI
003   ISZI
004   ISZI
005    RTN
006  *LBLA
007   STOA
008    RTN
009  *LBLc
010   ENT↑
011    INT
012   STO3
013     -
014    EEX
015      2
016      X
017   ENT↑
018    INT
019   STO5
020     -
021    EEX
022      4
023      X
024   STO6
025      3
026      6
027      5
028   STO4
029      X
030      2
031   RCL3
032   X<>Y?
033   GTO0
034      X
035    CLX
036   RCL6
037      1
038      -
039   STO6
040   GTO1
041  *LBL0
042      .
043      4
044      X
045      .
046      3
047      +
048      +
049    INT
050      -
051   RCL6
052  *LBL1
053    CLX
054   RCL5
055      +
056   RCL3
```

Increment pointer by 3.

Store Birthdate

FUNCTION OF DATE

N (M, D, Y)

```
057      1
058      -
059      3
060      1
061      X
062      +
063   RCL6
064      4
065      ÷
066    INT
067   X<>Y
068      +
069    RTN
070  *LBLC
071   RCLC
072   STO9
073  *LBL7
074      1
075   ST+9
076   GSBb
077   GTO7
078  *LBLB
079   STOB
080   RCLA
081   GSBc
082   STO2
083   LSTX
084   STO0
085   RCLB
086   GSBc
087   LSTX
088   ST-0
089    CLX
090   RCL2
091      -
092   RCL4
093      2
094      ÷
095   ST÷0
096   X<>Y
097   STOC
098   STO9
099      2
100      3
101   STO3
102      2
103      6
104   STO2
105      3
106      3
107   STO1
108  *LBLb
109      3
110   STOI
111   DSP2
112  *LBL6
```

+1 loop

BIO DATE CYCLE
Store Bio date

Days between dates

Store cycles bases.

PRINT CYCLE
for a day

REGISTERS

0	1	2	3	4	5	6	7	8	9
1 or 2	33	28	23	Days	Days	Days	Used		Δ days
S0	S1	S2	S3	S4	S5	S6	S7	S8	S9

A	B	C	D	E	I
Birth date	Bio date	Δ days			

```
113  RCL9
114  RCLi
115    ÷
116  FRC
117  FI?
118  GTO8
119    2
120    ×
121   Pi
122    X
123  SIN
124  RND
125  GTO1
126 *LBL8
127  RCLi
128    X
129  GSB2
130  STOi
131  X≠I
132    3
133    -
134  X≠I
135  DSZI
136  GTO6
137  RTN
138 *LBL1
139  GSB9
140 *LBL8
141  DSZI
142  GTO6
143  SPC
144  RTN
145 *LBL9
146  F0?
147  PRTX
148  F0?
149  RTN
150  R/S
151  RTN
152 *LBLe
153  DSP0
154  F0?
155  GTO0
156    1
157  SF0
158  RTN
159 *LBL0
160    0
161  CF0
162  RTN
163 *LBLd
164    .4
165  STO7
166    1
167  RCLC
168  GTO0
```

PRINT/PAUSE

PRINT TOGLE

DAYS UNTIL NEXT MAX

```
169 *LBLD
170    4
171  ENT↑
172    3
173    ÷
174  STO7
175    1
176  RCLC
177  GTO0
178 *LBLE
179    2
180  STO7
181  RCLC
182 *LBL0
183  STO9
184  X≠Y
185  ST00
186  SF1
187  GSB6
188  CF1
189    3
190  STOI
191 *LBL3
192  GSB2
193  RCLi
194  X≠I
195    3
196    -
197  X≠I
198  RCLi
199  RCL7
200    ÷
201    -
202  CHS
203  X<0?
204  GTO3
205 *LBL4
206  PRTX
207 *LBL3
208  RCLi
209  RCL0
210    ÷
211    +
212  RCL1
213  X≠Y
214  X>Y?
215  GTO5
216  GTO4
217 *LBL5
218  SPC
219  DSZI
220  GTO3
221  RTN
```

DAYS UNTIL NEXT MIN

DAYS UNTIL NEXT CRITICAL

LABELS					FLAGS	SET STATUS		
A Birth date	B Bio date	C +1	D MIN	E Critical	0	FLAGS	TRIG	DISP
a	b Print cycle	c N(M, D, Y)	d MAX	e Print?	1	ON OFF 0 ☒ ☐ 1 ☐ ☒	DEG ☐	FIX ☒
0 Used	1 Used	2	3	4	2	2 ☐ ☒	GRAD ☐	SCI ☐
5	6	7	8	9 Print/Pause	3	3 ☐ ☒	RAD ☒	ENG ☐ n 2

Timer

001	*LBLA	INITIALIZATION
002	CLRG	
003	PSE	
004	CLRG	
005	5	C_b (MINIMUM
006	1	INTERVAL
007	3	CALIBRATION
008	4	CONSTANT)
009	1/X	
010	STOE	
011	5	
012	.	C_a (5 SECOND
013	7	PRIMARY)
014	8	
015	3	
016	0	
017	STOB	
018	.	K_a (5 SECOND
019	1	SECONDARY)
020	0	
021	7	
022	5	
023	STOC	
024	6	C_c (COUNT-UP)
025	0	
026	6	
027	0	
028	1/X	
029	STOD	
030	6	C_d (COUNT-DOWN)
031	7	
032	9	
033	0	
034	1/X	
035	STO5	
036	0	
037	RTN	
038	*LBL5	5 SECOND TIMER
039	PSE	LOOP
040	HMS+	
041	7	
042	2	
043	0	
044	1/X	0:00:05 HRS
045	+	
046	STOA	TIME
047	RCLB	C_a
048	RCLI	
049	+	
050	STOI	
051	*LBL1	FAST LOOP
052	DSZI	
053	GTO1	
054	RCLA	TIME
055	→HMS	
056	GTO5	

057	*LBLa	CALIBRATE 5
058	R↓	SECOND TIMER
059	GSB4	
060	R↑	
061	HMS→	
062	X≷Y	
063	HMS→	
064	−	
065	LSTX	
066	RCLC	K_a
067	×	
068	÷	
069	RCLB	C_a
070	+	
071	PRTX	
072	RTN	
073	*LBLC	COUNT-UP TIMER
074	GSBA	
075	R/S	
076	*LBL7	FAST LOOP
077	ISZI	
078	GTO7	
079	*LBLc	CONVERT TO TIME
080	RCLI	
081	RCLD	
082	×	
083	→HMS	
084	RTN	
085	PSE	SPLITS
086	RCL1	
087	STOI	
088	RCL2	
089	STO1	
090	RCL3	
091	STO2	
092	RCL4	
093	STO3	
094	RCL5	
095	STO4	
096	RCL6	
097	STO5	
098	RCL7	
099	STO6	
100	RCL8	
101	STO7	
102	RCL9	
103	STO8	
104	RCL0	
105	STO9	
106	PSE	
107	RCL1	
108	PSE	
109	STO0	
110	PSE	
111	RCL2	
112	STO1	

REGISTERS

0 SPLIT	1 SPLIT	2 SPLIT	3 SPLIT	4 t_s, SPLIT	5 C_d, SPLIT	6 SPLIT	7 SPLIT	8 SPLIT	9 SPLIT
S0 SPLIT	S1 SPLIT	S2 SPLIT	S3 SPLIT	S4 SPLIT	S5 SPLIT	S6 SPLIT	S7	S8	S9

A	B	C	D	E	I

113 RCL3 114 STO2 115 RCL4 116 STO3 117 RCL5 118 STO4 119 RCL6 120 STO5 121 GTOc 122 *LBLE 123 RCL5 124 STO6 125 RCL4 126 STO5 127 RCL3 128 STO4 129 RCL2 130 STO3 131 RCL1 132 STO2 133 Σ- 134 RCL0 135 Σ- 136 STO1 137 Σ- 138 RCL9 139 STO0 140 RCL8 141 STO9 142 RCL7 143 STO8 144 RCL6 145 STO7 146 RCL5 147 STO6 148 RCL4 149 STO5 150 RCL3 151 STO4 152 RCL2 153 STO3 154 RCL1 155 STO2 156 RCLI 157 STO1 158 4 159 . 160 4 161 2 162 + 163 STOI 164 Σ- 165 GTO7 166 *LBLB 167 GSBA 168 R/S	C_e SPLIT CONSTANT MINIMUM INTERVAL VISIBLE TIMER	169 *LBL6 170 PSE 171 RCLE 172 HMS+ 173 GTO6 174 *LBL6 175 R↓ 176 GSB4 177 X≠Y 178 R↓ 179 RCLE 180 GTO2 181 PRTX 182 RTN 183 *LBL2 184 X≠Y 185 HMS+ 186 × 187 X≠Y 188 HMS+ 189 ÷ 190 1/X 191 PRTX 192 RTN 193 *LBLd 194 GSB4 195 GSBc 196 R/S 197 X≠Y 198 RCLD 199 GTO2 200 *LBLD 201 GSBA 202 R/S 203 STO4 204 HMS+ 205 RCL5 206 ÷ 207 STOI 208 RCL4 209 R/S 210 *LBL3 211 DSZI 212 GTO3 213 0 214 RTN 215 *LBLe 216 GSB4 217 RCL4 218 X≠Y 219 RCL5 220 GTO2 221 *LBL4 222 CHS 223 HMS+ 224 RTN	FAST LOOP CALIBRATE MIN. INTERVAL TIMER CALIBRATE SUBROUTINE CALIBRATE COUNT-UP TIMER COUNT-DOWN TIMER START TIME t_s FAST LOOP CALIBRATE COUNT-DOWN TIMER START TIME t_s C_d CALCULATE SWEEP SECOND HAND TIME INTERVAL T_c

LABELS					
A 5 SEC	B MIN INT	C COUNT-UP	D COUNT-DN	E SPLITS	0
a 5 SEC CAL	b MIN CAL	c C-U to TIME	d CAL C-U	e CAL C-D	1
0	1 5 SEC LP	2 CAL SUB	3 C-U LOOP	4 T_c	2
5 5 SEC LP	6 MIN LOOP	7 C-U LOOP	8	9	3

FLAGS		
	ON	OFF
0	☐	☒
1	☐	☒
2	☐	☒
3	☐	☒

SET STATUS		
TRIG		DISP
DEG	☒	FIX ☒
GRAD	☐	SCI ☐
RAD	☐	ENG ☐
		n 4

Appendix A
MAGNETIC CARD
SYMBOLS AND CONVENTIONS

MAGNETIC CARD SYMBOLS AND CONVENTIONS

SYMBOL OR CONVENTION	INDICATED MEANING
White mnemonic: x [A]	White mnemonics are associated with the user definable key they are above when the card is inserted in the calculator's window slot. In this case the value of x could be input by keying it in and pressing [A].
Gold mnemonic: y x [f] [E]	Gold mnemonics are similar to white mnemonics except that the gold [f] key must be pressed before the user definable key. In this case y could be input by pressing [f] [E].
x↑y [A]	↑ is the symbol for [ENTER↑]. In this case [ENTER↑] is used to separate the input variables x and y. To input both x and y you would key in x, press [ENTER↑], key in y and press [A].
[X] [A]	The box around the variable x indicates input by pressing [STO] [A].
(x) [A]	Parentheses indicate an option. In this case, x is not a required input but could be input in special cases.
→x [A]	→ is the symbol for calculate. This indicates that you may calculate x by pressing key [A].
→x, y, z [A]	This indicates that x, y, and z are calculated by pressing [A] once. The values would be printed in x, y, z order.
→x; y; z [A]	The semi-colons indicate that after x has been calculated using [A], y and z may be calculated by pressing [R/S].
→"x," y [A]	The quote marks indicate that the x value will be "paused" or held in the display for one second. The pause will be followed by the display of y.
◁▷ x [A]	The two-way arrow ◁▷ indicates that x may be either output or input when the associated user definable key is pressed. If numeric keys have been pressed between user-definable keys, x is stored. If numeric keys have not been pressed, the program will calculate x.

SYMBOLS AND CONVENTIONS (Continued)

SYMBOL OR CONVENTION	INDICATED MEANING
P? A	The question mark indicates that this is a mode setting, while the mnemonic indicates the type of mode being set. In this case a print mode is controlled. Mode settings typically have a 1.00 or 0.00 indicator displayed after they are executed. If 1.00 is displayed, the mode is on. If 0.00 is displayed, it is off.
START A	The word START is an example of a command. The start function should be performed to begin or start a program. It is included when initialization is necessary.
DEL A	This special command indicates that the last value or set of values input may be deleted by pressing A.



Sales and service from 172 offices in 65 countries.
1000 N.E. Circle Blvd., Corvallis, OR 97330

00097-90134

● B C D E